

SCIENTIFIC AMERICAN

[Entered at the Post Office of New York, N. Y., as Second Class Matter. Copyright, 1910, by Munn & Co., Inc.]

A POPULAR ILLUSTRATED WEEKLY OF THE WORLD'S PROGRESS


Vol. CII.—No. 8.
ESTABLISHED 1845.

NEW YORK, FEBRUARY 19, 1910.

10 CENTS A COPY.
\$3.00 A YEAR.



The Rue Surcouf was converted into a Venetian canal.



Soldiers and sailors assisting in relief work.

THE GREAT FLOOD OF PARIS.—[See page 164.]

SCIENTIFIC AMERICAN

ESTABLISHED 1845

MUNN & CO., Inc., - Editors and Proprietors

Published Weekly at
No. 361 Broadway, New YorkCHARLES ALLEN MUNN, President
FREDERICK CONVERSE BEACH, Sec'y and Treas.
361 Broadway, New York.

TERMS TO SUBSCRIBERS.

One copy, one year, for the United States or Mexico \$3.00
One copy, one year, for Canada 4.75
One copy, one year, to any foreign country, postage prepaid, 18c. 6d. 4.50

THE SCIENTIFIC AMERICAN PUBLICATIONS.

Scientific American (established 1845) \$3.00 a year
Scientific American Supplement (established 1876) 5.00 " "
American Homes and Gardens 3.00 " "
The combined subscription rates and rates to foreign countries, including Canada, will be furnished upon application.
Remit by postal or express money order, or by bank draft or check.
MUNN & CO., Inc., 361 Broadway, New York.

NEW YORK, SATURDAY, FEBRUARY 19th, 1910.

The Editor is always glad to receive for examination illustrated articles on subjects of timely interest. If the photographs are sharp, the articles short, and the facts authentic, the contributions will receive special attention. Accepted articles will be paid for at regular space rates.

SECRETARY MEYER'S PLAN FOR THE REORGANIZATION OF THE NAVY.

THAT one of the first acts of Mr. Meyer on assuming the extremely difficult and responsible position of Secretary of the Navy, would be to make a thorough investigation of conditions, with a view to placing that very complicated department upon a more practicable working basis, was inevitable; as everyone must have foreseen who is familiar with the excellent work of reorganization which he achieved while holding the position of Postmaster-General.

The changes introduced by Mr. Meyer are necessarily supplemental to the work of his predecessor, Mr. Newberry, who had formulated and put into effect a system of consolidation, which, in the brief period of its operation, had shown excellent results. Mr. Meyer has assured us that the changes which he has instituted in the Newberry plan have been made not for the purpose of reversing but rather of amplifying the work of consolidation inaugurated by his predecessor. The essential changes involved in Mr. Meyer's plan are summarized under the following heads:

- (1) The provision of four responsible advisers (of the Secretary) on subjects within the groups into which duties of the Department logically fall.
- (2) The grouping of the Bureaus into two divisions of material and personnel, according to the nature of their duties.
- (3) The establishment of a Division of Operations of the Fleet.
- (4) The establishment of a comprehensive inspection system of a permanent organization, whose officers shall be periodically changed, who will come mainly from the active fleet and be conversant with the latest ships, and the modern methods of drill and organization.
- (5) The establishment of a modern and efficient cost-keeping system in the Navy Department and at navy yards.
- (6) The separation of navy-yard work into the two natural divisions of hull and machinery.
- (7) He intends to require that commandants and captains of yards for navy yards shall be selected for their knowledge and experience, and that their tenure of office shall be long enough to insure continuous administrative policy.

The SCIENTIFIC AMERICAN has before it the printed record of the hearing of the Secretary and various Bureau chiefs before the House Naval Committee appointed to consider the proposed reorganization; and, after giving the same a most careful reading, we have come to the conclusion that, with one very serious exception, the measures proposed by Secretary Meyer are well adapted to promote that consolidation which Mr. Newberry began, and which the present Secretary is endeavoring to place upon a lasting, workable basis. The appointment of four aides, independent of the Bureaus, whose duties will be to inform and advise the Secretary on matters coming under the four general heads, is an excellent arrangement, the need for which had been keenly felt by previous secretaries. The Aides for Operations of the Fleet, for Personnel, and for Inspections are to be line officers. The question as to whether the Aide for Material should be chosen from the line or staff is left open. We are decidedly of the opinion that in seeking for advice on the question of material, that is, ships, engines, navy yards, etc., the Secretary should have as his aide the Chief, or some high ranking, Naval Constructor, who by training and experience is best qualified to advise upon these subjects. A proportion of three line officers to one staff officer among the aides would give a fair representation of both branches of the service, and would put the Secretary adequately in touch with the

whole range of active work in his Department.

The feature of Secretary Meyer's plan which we consider to be open to very grave question is the proposal to separate the navy-yard work into two divisions of hull and machinery, with a separate and independent manager for each; for the change involves the defeat of one important object of the Newberry plan as affecting the navy yards, namely, the securing of efficiency, and the avoidance of confusion and delay, by placing the whole of the work affecting the construction of the ship in charge of the officers of a single corps, with a member of that corps as general works manager of the yard. Mr. Meyer recognizes that a navy yard is a military establishment and must be under military government; but this condition was met under the Newberry plan by placing at the head of the yard a commandant who is always a line officer of high rank. Under him came the manager, a naval constructor, whose executive powers were recognized as covering, not the military, but the industrial side of the work. In view of this distinction, we fail to see how the management of the yard as to its non-military and purely industrial features by a staff officer of the naval construction corps is, in any possible sense, a violation of that law of Congress, according to which a staff officer cannot exercise military command over any other than members of his own corps. Under the former or Newberry plan, line (sea-going) officers of the Engineering Corps, who were temporarily assigned to the steam engineering department at the navy yard, were subject to the naval constructor manager, purely in the industrial and not in the military sense.

If it is advisable for economy and efficiency, and the consensus of evidence is overwhelming on this point, that the navy yards should be under a single industrial management, and that this management should rest in the naval construction corps; and if under such an arrangement, any legal question is involved as to the right of the constructor-manager to exercise non-military authority over engineer officers of the line, who may be temporarily assigned to duty at the yard, then the sooner the law is modified the better for the interests of the navy, and of the American people as a whole.

If it be asked why both hull and machinery should be placed under the control of a single head, and that lead the naval constructor, we reply that the hull and the machinery are merely subdivisions of one organic whole, and that the two are so greatly interdependent as to make it necessary that their design, construction, and subsequent repair be under the management of a single corps, who are qualified for the work by training, knowledge and practical experience. Now, we venture the statement, without any fear of successful contradiction, that the one body of men who combine the necessary knowledge of naval architecture, and steam and electrical engineering, to qualify them for the oversight of the construction and repair both of the hull and the machinery, is the corps of naval constructors. Unfortunately, much of the evidence which has been given before the committee has been directed to proving that the naval constructor is ignorant of steam and electrical engineering, and therefore not qualified to take charge of the shops devoted to these branches at the navy yards. That nothing is further from the truth is shown by the following consideration of their training and experience:

In the first place, the naval constructors are the pick of the Naval Academy graduates. They are selected from the highest numbers in their class, and, as a rule, have been taken from the first two or three. In making the selection, in addition to their academic standing, careful consideration is made of their general aptitude for the service as shown during their three or four years at sea; of their general officer-like qualities; and of their aptitude for the handling of men, and for general administration. The principle of selection is the same as is followed in the case of that other highly specialized and most efficient body of professional men, the corps of engineers of the army. After their education as line officers at sea, the constructors are given at the famous Massachusetts Institute of Technology a post-graduate course in naval construction, which is the most thorough of any in the world.

Furthermore (and we cannot too strongly insist that the impression that the naval constructor is not a qualified steam engineer is absolutely erroneous) the course at the Massachusetts Institute of Technology involves also thorough instruction in steam and electrical engineering, during which the prospective constructors are given a course of practical training in the machine shops and laboratories of the institution.

The life work of the naval constructor will be done on shore and mainly at the various navy yards; and by virtue of his long residence at these yards, or as inspector at the various private shipbuilding yards, he gathers an ever-increasing and immensely valuable knowledge of the operation of these great industrial plants. Future promotion and distinction for him lie along these lines. There is every incentive for him to become thoroughly proficient.

With the line officer, however, into whose hands Mr. Meyer's plan would commit the construction of all electrical and steam machinery, and the management of the large and elaborate plants at the navy yards where this work is done, the case is entirely different. After his four years' course at Annapolis, the prospective naval engineer goes to sea with the expectation of spending practically all of his time afloat; and, naturally, his sympathies, interests, and above all his ambitions, will be connected with sea duty. An assignment for service ashore is merely a break in the routine of his chosen life work. If the line officer be an engineer officer, he will enlarge at sea his knowledge of the care and operation of a ship's machinery; but since by far the greater part of his time is spent afloat, his opportunities for becoming acquainted with the complicated and difficult work of managing such large industrial concerns as the steam machinery shops of the navy yards are, in the nature of things, very limited. His work is to run, not to build, the engines; just as it is the work of the captain of the ship to run and not to build the hull.

Even when the line officer is ashore, his interests and future aims are still upon the sea; and, as a rule, he is only too glad when the next assignment for sea duty comes. Proof of this is found in the fact that during the past six years there have been at our seven leading naval yards, no less than 29 commandants and 41 captains of the yard. Evidently, the sea-going officer cannot too quickly get back to his natural sphere of service.

If there were available at the present time a corps of engineering officers who, like the naval constructors, had been specially trained for shore duty in the management of the machinery shops, etc., at the navy yards, we would have more hope of the success of this particular part of Mr. Meyer's plan; but outside of a few of the older engineers, trained under the system which obtained before amalgamation, no such body of men is available. Furthermore, it is our conviction that, were such a body existent, it would still make for economy and efficiency, if both hull and machinery were placed under the single management of a naval constructor.

That part of the Newberry plan which affected the navy yards was giving very promising results at the time Mr. Meyer took office. We have little doubt that his determination to separate hull and machinery was governed largely by certain alleged instances of incapacity of the naval constructors in their management of the machine shops, which were supplied to the Secretary, most of them over the signature of the Engineer in Chief. The testimony before the House Naval Committee now before us, however, shows that a subsequent examination of these reported cases has elicited from the commandants of the various yards (all of them line officers) a complete disproval of the charges as made—a very gratifying vindication of the work of the naval constructors in this particular regard. We cannot but feel that with this later evidence before him, the Secretary will be disposed to reconsider that part of his otherwise excellent reforms, which proposes to separate hull and machinery, and that he will allow the Newberry plan of a single management sufficient time to further demonstrate the economy and all-round efficiency of which it gave, in the few months of its operation, such great promise.

ELECTROLYTIC REMOVAL OF GREASE.

AN electrolytic method of removing grease from objects has been introduced in Germany. Grease can be rapidly removed from metallic objects by employing it as a cathode in a hot solution of potash or soda lye. It was supposed that the alkali metals set free at the cathode transformed the fatty matter into soap, but Barth has now shown that substances which cannot be saponified, such as machine oil, paraffine oil and paraffine, are removed very quickly by the current, and he explains this fact by mechanical action caused by bubbles of hydrogen which come off at the cathode. This action is produced only when the fatty matter is liquid. If the temperature of the bath is too low so that the grease is consistent, the removal is very slow and is incomplete. He operates with a moderately concentrated solution of carbonate of potash heated between 85 and 100 deg. C. As the anode he uses sheet iron or carbon pieces. When a piece of sheet iron covered with oil or paraffine is dipped into this bath it remains covered with oil ten minutes after immersion when the current does not flow, but upon sending the current all traces of oil disappear in a few minutes.

To permit two steamers to pass from the Wisconsin River to the Mississippi River, near Prairie du Chien, Wis., a railway bridge on the Chicago, Burlington, and Quincy Railway was raised by breakdown cranes a few weeks ago. There is no navigation on the Wisconsin River, but the two steamers were sent down to enter service on another route. The railway crosses the river near its mouth, and a 65-foot span was raised about 6 feet to clear the steamers' funnels.

ENGINEERING.

George W. Melville, Engineer in Chief of the United States Navy, states that there is every reason to believe that two ships of the navy will be fitted with the turbine reduction gear which we illustrated on the front page of our last issue. It is proposed to re-engine the "Baltimore" with turbines of 12,000 horse-power, and equip one of the new colliers with turbines of 6,000 horse-power, both employing this reduction gear.

The number of persons killed in train accidents during the months of July, August, and September, 1909, as shown in reports made by the railroad companies to the Interstate Commerce Commission, was 193, and of injured, 3,752. Accidents of other kinds, including those sustained by employees while at work and by passengers in getting on or off the cars, etc., bring the total number of casualties up to 20,093 (852 killed and 19,241 injured).

The Shoshone dam in Wyoming, which forms the leading feature of one of the projects of the Reclamation Service, has recently been completed. It is built of concrete, and measures 328.4 feet from foundation to the crest. It is 175 feet long at the top and 85 feet long at the bottom, where its thickness is 108 feet. The reservoir back of the dam, which has a capacity of 456,000 acre feet, will serve to irrigate 130,000 acres of land, situated about 75 miles east of the Yellowstone National Park.

The grand total of canal excavation at Panama for the month of December was 2,811,681 cubic yards. This is 362,366 cubic yards more than the total for November, but 1,068,656 cubic yards less than the highest record, made in March, 1909. Of the grand total, 1,455,611 cubic yards was dry excavation, removed principally by steam shovels. The dredges removed 1,356,070 cubic yards, in addition to the amount pumped into Gatun dam by the suction dredges engaged on that work.

In recognition of the culmination of his life work in the discovery of the North Pole, the Senate has passed a bill making Commander Robert E. Peary a rear admiral on the retired list. This signal recognition of the explorer followed closely upon the recent gathering, presided over by the Governor of the State of New York, at which Peary received a gift of \$10,000, which, by the way, he immediately contributed to the proposed American expedition for the discovery of the South Pole.

Major Mason M. Patrick of the United States army, speaking on the subject of the construction of an artificial island and additional fortifications near the entrance to Chesapeake Bay, drew attention to the fact that the two largest and fastest merchant vessels afloat to-day could each carry 10,000 men with all their munitions of war, and, if unopposed, could land them on our coast in less than one week; and he also stated that more than one foreign power possesses a fleet of swift transports which can carry at one time over 100,000 men.

Secretary Meyer has asked for a large appropriation for the enlargement of the government drydocks to suit the huge battleships now under construction. He also asks for the construction of a \$2,000,000 drydock at Norfolk; for an additional \$1,000,000 for increasing the new dock at the New York navy yard to a length of 700 feet; for an additional \$1,500,000 for increasing the Puget Sound dock to a width of 110 feet; and for the enlargement of the width of the Pearl Harbor dock, Hawaii, to the same width, at an increased cost of \$450,000.

The new terminal station of the Pennsylvania Railroad Company at 33rd Street and Seventh Avenue, Manhattan, is so far advanced that it will be practically completed by the end of next month. The first service to be put in operation will consist of multiple-unit, standard size, electric trains running to Jamaica, Long Island, over a four-track road, which will soon be increased by the addition of two more tracks. This will be followed by the opening of the through express service to the West, which will be operated by the 4,000-horse-power electric locomotives illustrated in our issue of December 18th, 1909.

Were **Jules Verne** with us to-day, he would be greatly interested in two instances of rapid travel recorded during the past week. A traveler from London to San Francisco won a wager by covering the distance in two hours and thirty-five minutes less than ten days; the trip being made by the "Mauretania" to New York, the 20th Century Limited to Chicago, and the Overland Limited to San Francisco. A passenger from Lima, Peru, in making a hurried trip in response to a call to London, left Lima the same day by steamer to Panama; crossed by the Panama Railroad; made close connections with a steamer for New York; and caught the "Mauretania" for England. If the ship makes an average passage, the whole trip will have been covered in 19 days.

AERONAUTICS.

The first exclusively aeronautic show to be held in America is open at present in Mechanics' Building at Boston. A score of full-sized representative aeroplanes of all types, together with a large number of models, are on view. Several competitions for models will be held, and some of the gliders and motor-driven aeroplanes may be tried out upon the ice of the lake in Franklin Field. This exhibition will give one a good idea of the state of aeronautics in the United States to-day.

On the 10th instant Wilbur and Orville Wright were presented with the Langley medals of the Smithsonian Institution by Chief Justice Fuller at Washington. Dr. Alexander Graham Bell and Senator Henry Cabot Lodge made brief addresses. Wilbur Wright announced that as soon as he and his brother get their American company under way, they expect to devote their time to research work in aviation. The two gold medals were designed by J. C. Champlain, a member of the French Academy, the reverse being from the seal of the institution, which was designed by St. Gaudens.

Paulhan has expressed a willingness to fly in the vicinity of New York if Curtiss or some other interested person will have that injunction dissolved which now hangs over the heads of aviators using warpable planes or hinged wing tips. His brilliant success in California leads one to hope that his desire may be gratified in the interests of a sport of which the United States in general and the East in particular knows lamentably little. If Paulhan really gives an exhibition in these parts he will do much to stimulate New York's interest in aviation. The Hudson-Fulton flights were after all a fiasco, and yet they roused New York to an intense pitch of excitement. Paulhan ought to do better.

The first week of February the suit of the Wright brothers against Paulhan for an injunction restraining him from giving exhibitions in his Farman biplane was tried before Judge Hand in the United States Circuit Court in New York city. Judge Hand manifested great interest in the case, and his decision is awaited with interest. It is uncertain whether he will grant a preliminary injunction, as Judge Hazel did at Buffalo last December. In defending the attack of the Wrights upon the Bleriot monoplane, Mr. E. R. Newell asserted that Prof. S. S. Montgomery's patent, which antedates the Wright patent, covers the same system of plane warping as the Wrights themselves claim, and he further says that the machine as built to-day does not correspond with the patent. A full report of the Wright-Curtiss case and the text of Judge Hazel's decision appears in the current SUPPLEMENT.

As soon as he had finished flying at Los Angeles, **Charles K. Hamilton** went to San Diego, where he made a number of daring flights with his Curtiss biplane. On January 23d, after starting from the vast plain near the Hotel Del Coronado, Hamilton twice flew out over the ocean so far that he disappeared from view for ten minutes. When he re-appeared he came from a different direction. In the first flight he covered about 10 miles, and in the second one 15. The wind was blowing at times as high as 20 miles an hour. After circling upward to a height of about 800 feet, Hamilton stopped his motor and made a wonderful long straight glide to earth. This is probably a record performance, certainly the longest glide ever made in America. A week later, at Bakersfield, Cal., he made two excellent flights under difficult conditions. Starting from a half-mile track, he flew about the town and out over the desert and adjoining oil fields, finally landing successfully at the starting point. His mastery of the biplane seemed complete.

Subsequent to the Los Angeles aviation meeting, **M. Paulhan** made excellent exhibition flights at San Francisco, Denver, and New Orleans. At San Francisco, on January 24th, he made several flights in a strong wind, the last and highest of which, of 12 minutes duration, was made after sunset. Two days later he rose to a height of 1,300 feet in a flight of 31 minutes' duration. On February 1st, at Denver, he was mobbed by a crowd of 30,000 people eager to see him fly. After three preliminary attempts, he finally left the ground and made two circuits of the course at Overland Park. The next day he made a 15-mile cross-country flight in a driving snow-storm. In starting, he ran his Farman biplane through snow three inches deep, and when he alighted, the planes and struts of the machine were in many places covered with snow, while Paulhan himself was suffering from the bitter cold. Previous to this long flight, he made a preliminary flight of 8 miles. On February 4th, after circling the Park successfully a dozen times, Paulhan twice was unsuccessful in starting in the distance at his disposal. The first time one of the wheels of his machine struck the fence and was knocked off, while the second time the machine crashed into the fence and was demolished. Paulhan was unhurt, but several spectators were injured.

SCIENCE.

The American Museum of Natural History in New York city has commissioned William Couper to model a statue of Commander Robert E. Peary for the Museum. The statue is to be life size and of marble.

In a bulletin issued by the United States Department of Agriculture Mr. Ned Dearborn writes on methods of destroying English sparrows. The evidence of the destructiveness of the sparrow is overwhelming, for which reason some means should be adopted to check the spread of the bird. Mr. Dearborn recommends the destruction of the nests from two to twelve days throughout the breeding season. Thus the number of English sparrows could be reduced without resorting to shot, poison, or traps.

The Smithsonian Institution has received a letter from ex-President Roosevelt, dated December 15th, 1909, from Nairobi, informing the secretary of that Institution that his expedition has finished its work in British East Africa. The collections made in that country aggregate 8,463 animals, which include mammals large and small, birds, reptiles, and batrachians, fresh-water and marine fish. Considering the fact that probably over 95 per cent of these animals find their duplicates in the natural history museums of this country and of Europe, ex-President Roosevelt seems to have been doing much unnecessary killing.

The Radium Institute of America has been incorporated. Its purposes are to study radium and radioactive substances, rays, and emanations in the interests of science and humanity, and to maintain a chemical laboratory, library, meeting room, and offices, and to acquire and hold patents and licenses to deal in radium and properties pertaining to radium. The headquarters of the institute will be located in New York. The twelve incorporators are: Dr. Robert Abby, Dr. Nicholas Murry Butler, Charles F. Chandler, Bergen Davis, William J. Gies, William Hallock, Ellwood Hendrick, Hugo Lieber, Dr. Willy Meyer, George B. Pegram, Hugo Schweitzer, and Edgar F. Smith of the University of Pennsylvania.

An expedition to observe and photograph Halley's comet from the Hawaiian Islands is to be sent out by the Astronomical and Astrophysical Society of America. In view of the possible perturbations arising from the close approach of the comet to the earth on May 1st and to Venus on May 16th to 18th, meridian observations are especially desired during the period in which the comet is sufficiently bright for that purpose. The close approach of the comet to the earth will afford an unusual opportunity for a study of the physical condition of comets. The comet's close proximity to the sun at the time of maximum brilliancy imposes serious limitations upon the Society's programme. Widely extended co-operation will be required throughout the whole world if a continuous photographic record is to be even remotely realized.

The American Museum of Natural History has been presented with a life-size marble statue of Morris K. Jesup by J. Pierpont Morgan, Henry Fairfield Osborn, Cleveland H. Dodge, Charles Lanier, J. Hampden Robb, Joseph H. Choate, and others. At the unveiling of the statue addresses were delivered by Prof. Osborn (who succeeded Mr. Jesup as president of the Museum), Mayor Gaynor and Joseph H. Choate.

Commander Robert E. Peary has contributed \$10,000 to a fund for the equipping of an American expedition to the South Pole. The check for the amount of his contribution had been handed to him by Gov. Hughes on behalf of the people of New York as a testimonial of appreciation of his achievement in finding the North Pole, and the Metropolitan Opera House was crowded with people who had come to take part in what the fostering Civic Forum called a "national testimonial" to the explorer.

There is a gaseous element, discovered in the atmosphere by Ramsay, which is remarkable for its chemical inertness, but though destitute of chemical properties it possesses a very curious physical property which was discovered by J. Norman Collie. When a sealed glass tube, containing mercury in an atmosphere of neon at low pressure, is shaken it becomes strongly luminous. Similar effects are obtained when other gases are substituted for neon, but the light emitted by neon in these conditions is especially bright. If the shaking is repeated at intervals during two or three hours, the intensity of the light diminishes for a time and thereafter remains constant. The original luminosity can be restored by passing an electric discharge through the tube. If one end of the tube is heated to 750 deg. F. while the other end is cooled by immersion in liquid air, and the tube is then allowed to return to the ordinary atmospheric temperature, the part which has been heated glows much more brightly than before. The luminosity is also greatly increased by substituting a tube of fused quartz for the glass tube. G. Claude is endeavoring to utilize this remarkable property of neon as a source of light, and claims to have constructed neon lamps of an efficiency equal to about 1 watt per candle-power.

DID GREAT BRITAIN HAVE THE FIRST "DREADNOUGHT"? THE "ROYAL SOVEREIGN" OF 1862

BY PERCIVAL A. HISLAM

The *SCIENTIFIC AMERICAN* for November 20th, 1909, contained a description by Mr. William Boerum Wetmore of the U. S. S. "Roanoke," a converted steam frigate, which he claimed to have been the original prototype of the "Dreadnought." The date of the conversion of the "Roanoke" from the frigate into the three-turreted ironclad was 1863; but England, the birthplace of the twentieth century "Dreadnought," has a similar instance to the "Roanoke," but which dates from the previous year—1862.

The "Royal Sovereign," as this ship was named, was built as a three-decked sailing ship of 3,144 tons and 120 guns; and in 1860 had been fitted with engines of 800 horse-power. The sides of the "Royal Sovereign" after conversion were composed of three feet of solid timber, strengthened internally with diagonal iron bands and clothed externally to some distance below the waterline with 5½-inch rolled armor plates. One-inch iron plating was laid upon the deck beams, and over the iron plating was laid the deck proper, consisting of 6-inch and 8-inch oak planking. From the sides of the ship the deck sloped upward to the outer circumference of the turrets, which thus appeared like circular forts on the apex of a glacis.


The following description is taken from a contemporary account in the London Times newspaper: "Stepping on the 'Royal Sovereign's' upper deck, we find that her light iron bulwarks, 3 feet 6 inches in depth, are thrown down outward on hinged stanchions. On the crest of the deck stand the four turrets and pilot house, funnel casing, hatchways, and ventilating shaft. The foremost turret, standing five feet above the deck, has its top covered by a grating, and is surrounded by a handrail, and thus affords a deck promenade for the officer of the watch or lookout man. The single-gun turrets are 4 feet 3 inches above the deck."

It was claimed at the time that the method of mounting and working the guns in the "Royal Sovereign" was superior to anything which had then been applied in any American turret ship. In American designs the turret rested upon the upper deck, and was thus liable to easy disablement; but in the English vessel the base of the turret was on the lower deck, and the citadel was therefore much less likely to be disabled by a hit. The American method resulted in the turret being nine feet above the deck, while in the "Royal Sovereign" only five feet or four feet three inches, as

the case might be, was exposed to the enemy's fire. Further, the latter ship's turrets could be worked by rack and pinion inside the turret, by the same method from the outside, and by handspikes worked like capstan bars, as well as by steam.

It will be seen that the "Royal Sovereign" had four turrets—one more than the "Roanoke"; but she had one gun less, for while the foremost contained two guns, the others had only one each. All the turrets were mounted on the center line of the ship, and the guns were muzzle loaders of 12½ tons, firing a 300-pound shot.

The original speed of the "Royal Sovereign" had been 12.25 knots, but after conversion this fell to 11, a difference which was fully accounted for by the increased immersion of three feet. Her freeboard re-



Converted British three-decker "Royal Sovereign" changed to an all-big-gun battleship in 1862.

WAS THIS THE FIRST "DREADNOUGHT"?

mained at seven feet after conversion. The cost of the work was \$699,900.

The "Royal Sovereign," besides having been, at any rate, one of the prototypes of the modern "Dreadnought," is interesting as having been the first vessel in which the turret principles of Capt. Cowper Coles were put into practice. The first vessel actually built in England embodying those principles was the "Captain," an ironclad of 4,272 tons, which capsized in the Bay of Biscay on September 6th, 1870.

According to contemporary accounts, the speed of the "Roanoke" was only 5 knots. This is inferior to the "Royal Sovereign's" speed by 6 knots. The latter vessel, again, had four turrets to the "Roanoke's" three; both ships had 5½ inches of side armor in a rolled plate, although up till then most American ships

had been armored on the inferior laminated system; both ships were practically mastless, for the three poles of the "Royal Sovereign" reached only just above the top of the funnel. In freeboard there was little to choose between the two, while in the method of placing the turrets the British ship was decidedly superior.

Much, therefore, as we owe to America in the development of modern navies, and more especially, perhaps, in the introduction of steam navigation and in the correct placing of turrets in modern battleships, I think it must be admitted that Great Britain was the first to possess a prototype of the modern "Dreadnought."

I have been unable to procure a picture of the "Royal Sovereign" for reproduction, but the accompanying elevation and plan will convey an idea of the appearance of the ship.

It may be mentioned that Russia launched in 1867 the "Admiral Lazareff," a three-turreted ironclad of 2,754 tons, very similar in general design to the "Roanoke." She carried in each turret two 15½-ton guns; but it was seen fit later to alter this to one 11-inch for each. In view of the diagonal (or echelon) arrangement adopted in the British "Dreadnought" cruisers of the "Invincible" type, it is interesting also to note that Italy led the way with this system of mounting with the "Dulio" (1876), Great Britain following with the "Inflexible" in 1881, and with four other ships a few years later. The only American examples of this system of mounting were seen in the "Maine" and "Texas," the first with two 10-inch and the second with one 12-inch gun in each turret.

The arrangement of the turrets in the British "Dreadnought" had a prototype in the French "Admiral Duperré," launched in 1879. This ship had two turrets on the center line and on the same level aft, and a turret on each beam just forward of the funnels. The guns had a freeboard of 27 feet 5 inches, giving them a great command of fire. Each turret contained one gun of 13.5 inches caliber; and if another center-line turret be added forward of the two beam turrets, it will be seen that the arrangement of the "Dreadnought" is almost exactly reproduced. It is strange how often we are confronted with the fact, in reading old books and other records, that there is "nothing new under the sun."

OTHER WORLDS IN SPACE

BY PROF. S. A. MITCHELL, COLUMBIA UNIVERSITY


If one should look at the heavens on any clear moonless evening, he would see them shining with countless orbs of light apparently millions in number. It is a fact that from our earliest education we have regarded the terms "numberless as the sands of the seashore," and "countless as the stars," synonymous with quantities almost infinite; but if by the stars we mean those that can be seen by the naked eye (and the expression originated thousands of years before the invention of the telescope), our ideas have been utterly at variance with the truth. The unaided eye cannot see millions of stars as is commonly supposed, nor yet hundreds of thousands, for at any one time we could count only two to three thousand separate stars, and in the whole heavens there are less than six thousand which can be seen without a telescope. A small glass, however, increases this number largely, and with greater and greater telescopes more and more stars are brought to our ken. It is estimated that the astronomer of to-day can see and photograph upward of a hundred million of stars. Each of these is a sun shining by its own light; the new astronomy tells us that thousands of these suns

have systems around them possibly resembling our own solar system, and it is not outside the bounds of probability that many of the planets about these distant suns may be inhabited by people who live and move and think. Indeed, this earth of ours, of so much importance to us, is a most insignificant speck in the almost limitless universe.

mous distances we are from them are however very small, and the changes of position in the sky so slight from year to year that they could not be found without the most careful measurements. So from this point of view the stars are fixed, and the constellations appear the same now as they did to the Chaldean shepherds thousands of years ago. Still the motions are there none the less. The old astronomy was able to measure motions athwart the sky, at right angles to our line of vision; the new astronomy is able to supplement this by a knowledge of their movements toward us or away from us in the line of sight. The revelations of this new branch of astronomy are revolutionary in their importance, and of the greatest moment to our ideas of the universe as a whole.

The principles underlying the use of the modern spectroscopic telescope applied to the stars are given in *SCIENTIFIC AMERICAN*, December 25th, 1909. There is required for this purpose a powerful telescope, and a most accurate spectroscopic telescope attached, whose temperature must be kept absolutely uniform during the two or three hours that may be consumed while the photo-

(Continued on page 176.)



PHOTOGRAPHS OF THE SPECTRUM OF μ ORIONIS, JANUARY 5th AND 6th, 1906.

The upper spectrum shows a velocity of 28 miles per second away from the earth, and the lower one of 48 miles per second in the same direction.

Astronomers by their meridian circles have been able to measure the exact positions of these distant so-called "fixed" stars, and have come to the conclusion that in spite of their names, there is none of them absolutely fixed in space, i. e., without motions. The movements of these heavenly bodies at the enor-

mal distances we are from them are however very small, and the changes of position in the sky so slight from year to year that they could not be found without the most careful measurements. So from this point of view the stars are fixed, and the constellations appear the same now as they did to the Chaldean shepherds thousands of years ago. Still the motions are there none the less. The old astronomy was able to measure motions athwart the sky, at right angles to our line of vision; the new astronomy is able to supplement this by a knowledge of their movements toward us or away from us in the line of sight. The revelations of this new branch of astronomy are revolutionary in their importance, and of the greatest moment to our ideas of the universe as a whole.


CONCRETE CONSTRUCTION ON THE PANAMA CANAL

HOW THE EIGHT MILLION CUBIC YARDS OF CONCRETE IS HANDLED

To the untrained eye the work which has hitherto been done on the construction of the Panama Canal necessarily appears more or less confused and chaotic. Although over one-half of the excavation has been completed, very little if any of the prism of the canal has been excavated to its finished dimensions, and the


works in the aggregate will probably represent the largest mass of masonry of any kind whatsoever hitherto placed in a single engineering work of magnitude. It is questionable whether an exception would have to be made even in the case of some of the famous masonry aqueducts built in ancient times; and the

Gatun on the Atlantic side of the Isthmus, one at Pedro Miguel and two at Miraflores on the Pacific side, and the great spillway in the center of the Gatun dam for carrying off the surplus waters. All of the locks will be 110 feet wide by 1,000 feet long, with a depth over the sills of 45 feet. The three locks at



Note the wooden forms in which the walls are molded.

Building concrete side wall—Gatun Spillway.



Millions of tons of sand are needed for the concrete.

Sand cranes and pockets at Balboa.

outline of the completed work is therefore irregular and ragged.


Some few months ago, however, the work of putting in the permanent concrete structures began, and from now on this great work will begin to take on definite shape and present visual evidence of its massive and permanent character.

The masonry works will not only be the largest of their kind ever built, the locks and spillways being on a scale of unprecedented proportions, but these


Pyramids or the Great Wall of China are not to be seriously reckoned in comparison with difficult hydraulic works of the character of those on the Panama Canal. In the accompanying series of photographs, which were recently taken on the Isthmus, one is able for the first time to gain some impression of the massive character of the concrete and reinforced-concrete structures the construction of which is now proceeding with gratifying rapidity.

The concrete work embraces six huge locks, three at

Gatun will form a continuous structure which, with the piers forming the approaches at each end, will have a total length of 3,800 feet, the whole work forming one huge monolithic mass of concrete. The Pedro Miguel lock with its piers will be 1,800 feet, and the two locks and piers at Miraflores will have a length of 2,800 feet. Into the construction of these locks will enter about 8,000,000 cubic yards of concrete, and of this 900,000 tons will consist of cement. The spillway through the Gatun dam has been cut through a low



Huge cantilever crane for placing concrete at Pedro Miguel locks.



New 600-foot highway suspension across Culebra Cut.



Stone for the concrete is brought from twenty miles east of the canal. The stone crushers at Balboa.

CONCRETE CONSTRUCTION ON THE PANAMA CANAL.

hill situated at about the center of the dam, and within the excavation thus formed is now being laid the deep concrete flooring, the massive retaining walls, and the piers between which will swing the gates for regulating the height of the water in that great artificial inland sea which will be formed by the dam.

It can readily be understood that the economical and expeditious laying of 8,000,000 cubic yards of concrete in structures of this magnitude called for a special plant of great size and capacity. At Gatun about 4,000,000 cubic yards of concrete will be employed. The crushed stone, the sand, and the cement for this concrete is handled in the following manner: The crushed stone comes from Porto Bello, a small hamlet about 20 miles east of Colon along the Atlantic coast. The rock is taken from the quarry by steam shovels, and sent by gravity to the giant crushers, and thence by gravity to the barges in the harbor. From this point it is carried to Cristobal, at the Atlantic entrance to the canal, and thence, via the old French channel, to the docks at Gatun. Here it is unloaded into storage bins by giant grab buckets, operated from cableways suspended between two sets of towers on either side of the channel.

The sand is brought from Nombre de Dios, about 40 miles along the coast from Colon. It is taken from the sand pits by clamshell buckets, loaded into steel barges, and taken to Gatun, where it is unloaded by a process similar to that of unloading the crushed rock. The cement is now being shipped from New York. At Colon the cement is transferred to barges and taken via the old French channel to Gatun and unloaded to the storage yards. The rock and sand storage piles have a capacity of about 300,000 cubic yards, while the cement yard accommodates about 100,000 barrels. From these storage buildings, the rock, sand, and cement are delivered through valves to charging cars running underneath. These cars, which are electrically operated, carry the materials to the concrete-mixing machines located nearer the locks' site and discharge it direct to the machines. After the concrete is mixed, it is dumped into buckets set on flat cars, and the cars are run to position under the wide cableways spanning the locks' site, and from these cableways the buckets filled with concrete are swung to position on the locks under construction.

The general principles upon which the plant at the locks on the Pacific side is designed are the same as those employed at Gatun; the mechanical details have been varied to meet the local conditions.

The latest report of the work, namely, that for December last, shows that during the month the total work of excavation amounted to 2,618,662 cubic yards, and that the total canal excavation of all kinds amounted to 2,811,681 cubic yards. The material placed in dams, mainly at the Gatun dam, amounted to 340,610 cubic yards, and during the month 57,265 cubic yards of concrete were built up in place.

HALLEY'S COMET.


Some interesting measures of Halley's comet, made with the micrometer of the Yerkes 40-inch refractor, are published by Prof. Barnard in No. 605 of the *Astronomical Journal*. With this large telescope the comet was quite an easy object, and the measures should be good; but, as Prof. Barnard suggests, the edges of such a nebulous body are not easy to set on.

The measures extend up to November 30th, 1909, when the estimated magnitude was about 11.0, and the comet showed a condensation of some 7 inches diameter. The diameter of the whole object was 41 inches, and possibly an ill-defined nucleus was seen, but this feature was very doubtful. From September 17th to November 14th the measured diameters, reduced to miles, ranged from 16,400 to 9,200 miles, the mean being 12,800 miles, or about $1\frac{1}{2}$ times the earth's diameter.

At the December, 1909, meeting of the Royal Astronomical Society, reported in No. 418 of the *Observatory*, the Astronomer Royal announced that a photograph secured with the Reynolds reflector at Helwan, on August 24th, shows the comet's image; its position agrees within 0.12s. in R.A. and 1.7 min. in declination with the position calculated from the Cowell-Crommelin orbit corrected by the Greenwich observations. Messrs. Keeling and Knox-Shaw are to be congratulated heartily upon securing the first known photograph of the comet.

In No. 25 of the *Gazette astronomique*, Signor Pio Emanuelli discusses the probable encounter between the earth and the comet's tail in May next. At 10 A. M. (G.M.T.) on May 18th the comet will pass the descending node of its orbit, while the earth will pass the same point eighteen hours later. For an encounter between the tail and the earth to take place, it is shown to be necessary that the latter should be 22,100,000 kilometers (13,732,277 miles) long, and that its breadth should be such that it extends, from its axis earthward, 400,000 kilometers (2,485,550 miles).

The accompanying chart shows approximately the



The sluiceways, etc., for rapidly emptying and filling the locks are of unusual size.

WOODEN FORMS FOR GATUN LOCK CONDUITS.

apparent path of the comet, according to Mr. Crommelin's ephemeris, up to April 5th.—Nature.

The Occluded Gases in Coal.

Prof. S. W. Parr and Mr. Perry Barker of the University of Illinois have made an elaborate study of occluded gases in coal, which is published in a bulletin recently issued by the university. As a result of their work it seems that two active processes are set up immediately upon the liberation of the coal from the vein. The first is an exudation of hydrocarbons, mainly consisting of marsh gas (CH_4); the second is an absorption of oxygen. There can be little question, moreover, that the alterations proceed simultaneously. There are present in the gases from all the samples of fresh drillings, notable quantities of methane, ranging from 18 per cent to 86 per cent of the various gas volumes. At the same time the oxygen present drops in a very positive manner, in some cases even reaching the vanishing point. That this transpiration of gases is interdependent and is of the nature of an osmotic exchange can hardly be affirmed as an explanation of

yield more methane, though in relatively small quantities. On the other hand, the avidity of the coal for oxygen seems to be pronounced at the very beginning of the exposure of the freshly-mined material; and while there are a number of cases where a certain agreement seems to exist between the in-going and the out-going marsh gas, still there are more cases where the absorption of oxygen is pronounced without any evidence of marsh gas being present. In all cases the oxygen-nitrogen ratio shows a positive diminution of the oxygen from the normal ratio of approximately 1 to 4 with practically no evidence of marsh gas being present. It seems fair to conclude, for the present,

that there is no necessary connection, at least of a strictly chemical nature, between the exudation of marsh gas and the absorption of oxygen.

Again, the liberation of CH_4 , while very active in the first few days after removal of the coal from the ground, diminishes in amount quite rapidly till, after the second month, there is very little of this gas in evidence. The activity of the coal for oxygen, on the contrary, seems to be of longer duration. Samples collected June 1st, 1906, were tested in May and June, 1908. There is marked absorption of oxygen in the sample after two days' exposure in the flask to normal air, while in a second, with five days' exposure, a still further reduction in the oxygen ratio without accompanying evidence, also, it should be noted, of marsh gas, was obtained. A marked avidity for oxygen was shown after two years from the time of collecting.

These facts have a direct bearing on the topic of deterioration as substantially defining the limit as to time of that form of alteration.

While varying somewhat in different coals, the loss of hydrocarbons for the most part is practically complete at the end of two months. These facts have a bearing also upon the matter of weathering, and indirectly upon the matter of spontaneous combustion. The absorption of oxygen is undoubtedly closely associated with both of these phenomena. The studies upon the weathering processes coincide with these studies in gases, namely, that in all probability this low type of oxidation extends over an indefinite length of time. Moreover, while under normal conditions there is effected but a very slight oxidation and loss of fuel values, the conditions are favorable, as, for example, for bringing about a very rapid combination with oxygen upon an increase of temperature.

How far this absorption of oxygen is a chemical reaction, or low combustion resulting in CO_2 and H_2O , and how far an absorption into the molecular structure and composition of coal must be left for study.


Dying Pearls.

In the Museum of the Louvre in Paris lies a collar of pearls at the point of death! Its death-bed is a plaque of velvet; and it is the large collar that was part of the personal estate of Thiers and once belonged to his wife. It is simply set and has no artistic value; its material value, however, is estimated at \$60,000. It consists of 145 pearls in three rows, the total weight of which is 2,097 grains, the three largest pearls of the collar weighing 36, 39, and 51 grains respectively. This collar must "die"; every day it loses another degree of its luster, and in the course of the present decade it will become as dingy as a much-worn wreath of roses.

Why? Because pearls keep their incomparable sheen only when worn by women and come into habitual contact with the gentle, soft, and warm skin of the wearer. When, for instance, Queen Augusta died it was found that her magnificent strings of pearls were likewise in a persistent decline, and for the reason, indeed, that for many years she had not worn them on her bare neck (which fact was explained by her age) but only around the fabric of the neck of her waist. At that time a treatment of baths in sea-water was prescribed for them by experts; and for several months, under obvious necessary precautions, they were sunk into the sea and thus recovered their old luster.

When, for instance, a collar of pearls is taken from the neck, where, subject to a temperature of 40 deg. C. approximately, it has lain for hours, and is laid upon the marble plate of the dresser, which is perhaps only 20 deg. C. warm, it feels, so to speak, a

(Concluded on page 172.)



APPARENT PATH OF HALLEY'S COMET FROM JANUARY 5th TO APRIL 5th.

the phenomenon. On the contrary, there seems to be evidence that the gases operate independently of each other.

In the case of samples of marsh gas the exudation of CH_4 seems to have spent itself in those samples held in laboratory containers for two years. In no case is there evidence of further liberation of this gas, even with thorough application of the vacuum. An evacuation of the gases from two-year-old samples shows no marsh gas present. The completion of this exudation would seem to be reached after two months, though it is well to note that by forcing, as with a vacuum, the two-months-old sample may be made to

Correspondence.

MR. RIEDERER'S PROBLEM.

To the Editor of the SCIENTIFIC AMERICAN:

Your correspondent who replies to my problem certainly has not studied the question very closely. There is absolutely no doubt as to the possibility of the solution, for taking any single number, it is quite evident that the remaining 14 numbers will make 7 pairs, each one of which with the taken number forming a different combination of three. What one number is capable of doing, every other is, likewise. So that certainly proves that 7 combinations as told are possible. The question is, how can this or any other similar problem be worked out without a haphazard shifting till you get the solution?

Find the system. The problem is all right.

New York city. HERMAN S. RIEDERER, Ph.D.

OBSERVATIONS OF A METEOR IN FLIGHT.

To the Editor of the SCIENTIFIC AMERICAN:

I have seen no mention in the newspaper of the meteor that fell west of Corrington, North Dakota, on January 10th. It was seen for seventy miles south of Streeter, North Dakota, and passed over us with great speed. It buried itself six feet in the ground about seventy miles north of Streeter. The heat produced was so great that for forty-eight hours no one could approach it closely, notwithstanding the fact that the ground was covered with snow and was frozen to a depth of four feet. When the meteor passed over our heads from a southwesterly direction to northeast, it shone most brilliantly. The noise which it produced can be likened only to that of a very large cannon ball in flight. The diameter of the meteor is 56 inches. It has been taken out and sent to Bismarck.

J. J. ROTT.

Streeter, N. D.

SOME STRANGE ANIMAL INSTINCTS.

To the Editor of the SCIENTIFIC AMERICAN:

Two items in your science column of January 8th, 1910, interest me. That about the return home of the kitten and cat, because there are scientists in your own city and elsewhere who have held doggedly that the special sense of this wonderful ability to go back home is not a special sense, but the result of some sort of observation, although the cat may be blindfolded. They even claim that homing pigeons find their way back by observing "the lie of the country." While this instinct is by no means unerring, and is developed to a much greater extent in some individuals than in others, there seems no justification of the denial to these lower creatures of a faculty of orientation or traversing which man possesses in only a small degree. There are many instances where the return has been made over a route very different from that of the outgoing journey, and could not have been influenced by the topography, even if it could have been observed.

The other instance is that of the magpie which was fond of rubbing tobacco and its ashes into its plumage, as mentioned by the writer in *Kosmos*. This is of special interest to me, because I had made a similar observation on a bluejay—a relative of the magpie—and had never so far been able to confirm it from any other source. Fortunately as long ago as 1896 I recorded it in my little book "The Story of the Birds" (Appleton) from which I venture to quote:

"I saw him (the jay) engaged in the walnut tree one day in late summer in a manner that made me fear that his bath had not been sufficiently effectual. He would pluck off a leaf, lift his wing and rub it into his plumage. I saw him do it repeatedly; and since walnut trees have a pungent odor and are disagreeable to insects, I feared that he had some guests that he was trying to get rid of. If this theory should be correct, here was a case of a bird using perfumes with at least good intentions." (Page 243.)

It is well known that dogs and other mammals will rub their bodies into or against something that is strikingly odorous, for the sake of the perfume only in which they seem to delight, but these two are the only instances that I know of where birds are recorded as doing the same. It would be interesting to hear from any other instances—if there are any, as is likely.

JAMES NEWTON BASKETT.

Mexico, Mo.

RE-ARMING OUR WARSHIPS.

To the Editor of the SCIENTIFIC AMERICAN:

In a letter to the SCIENTIFIC AMERICAN of September 5th, 1908, a correspondent, Mr. A. B. Wingfield, suggested the re-arming of our "Connecticut" class of battleships with four 12-inch guns in place of the eight 8-inch that are now carried in the main battery of this type. The Editor's comment at the time was that the greater weight of 12-inch gun emplacements on the beam would necessitate too costly structural strengthenings to justify the change, that the 6-inch armor protection would be too light for these emplacements,

and that the increase in dead weight would sink the already low armor belt even lower in the water. A previous letter appeared in your issue of August 15th, 1908, and since then changes of this character have been under consideration.

I know that if the SCIENTIFIC AMERICAN takes up this matter, its influence will be brought to bear on naval men, the object in view, of course, being to make dreadnoughts of the "Connecticut" type and semi-dreadnoughts of the "Georgia" class. The younger officers in the navy whom I have questioned in regard to this matter are unanimously in favor of these improvements.

As armed at present, the "Connecticut" and "Georgia" classes are not as efficient as a comparatively small additional expense could make them; and in view of the conceded superiority of the all-big-gun type of ship, it seems worth while to consider how it would be possible to so reconstruct the above types as to make them more formidable against dreadnoughts.

The pre-eminent function of a battleship is to concentrate the greatest efficiency and power possible in a single vessel. The armament of the "Connecticut" class consists of four 12-inch, eight 8-inch, 12 7-inch, and twenty 3-inch, of which four 12's, four 8's, six 7's, and eight 3's can fire on broadside. The "Georgia" type mounts four 12-inch, eight 8-inch, twelve 6-inch, and twelve 3-inch, of which four 12's, six 8's, six 6's, and six 3's fire on broadside. Now to convert these ships to dreadnoughts it would be necessary to mount one 12-inch gun in place of the two 8's in each of the beam turrets, keeping the emplacements as they are.

As the 7-inch guns are too small for battle ranges and too slow for torpedo defense, they could be substituted by the 5-inch rapid fires which are now being mounted on all our new dreadnoughts. With say eighteen of these and a few more 3-pounders in place of the present twenty 3-inch guns, the change is complete and you have a vessel the equal of the "Michigan" type, which are really powerful dreadnoughts on a "Connecticut" displacement.

In the "Georgia" class the same renovations could be made, except that the four superposed 8's would have to be retained and the six additional 5's omitted. The "Idaho" and "Mississippi" could be similarly treated. Under this arrangement the armament of the two classes would now be: "Connecticut": eight 12-inch and eighteen 5-inch, with a broadside fire of six 12's and nine 5's. "Georgia": six 12-inch, four 8-inch, and twelve 5-inch, with a broadside fire of five 12's, four 8's, and six 5's. Then our two "Idahos," four "Georgias," six "Connecticuts," two "Michigans," and two "Delawares" would mount 124 12-inch guns instead of 84 as at present, and would practically be a dreadnought fleet. The benefits from these changes are as follows:

1. A homogeneous broadside, giving greater concentration of fire at battle ranges.
2. A simpler system of spotting and fire control, with only one range to get and only one caliber of gun (excepting the four "Georgias") in the main battery.
3. A greater efficiency of ordnance resulting from more uniformity in ammunition and consequent speed in handling.
4. A better organization for and the quicker delivery of shell.
5. An opportunity offered to hold former 7-inch gun crews in reserve for turret crews.
6. The elimination of unwieldy and inaccurate middle batteries with large crews necessary to their service in exposed positions.
7. A smaller number of men in action at the same time and behind heavier armor (i. e., turrets only) at battle ranges.
8. An increase in the efficiency of torpedo defense by a gun more practicable in every way than the old caliber, which was ineffective at 3,500 yards and required the same number of men to handle it.
9. The lightening of the armor belt and bringing it higher out of the water, where it belongs.
10. The placing of the entire main battery behind turret armor.

Now as to the cost. For one battleship of the "Connecticut" class to be improved as shown above, the expense would consist chiefly of the price of four 12-inch and eighteen 5-inch rifles, and the remodeling of the 8-inch turrets and handling rooms. The 5-inch guns could occupy positions behind the old 7-inch barbettes, on the gun deck, the 3-inch casemates (slightly enlarged) on the main deck and new mounts for the superstructure. I do not believe that the structural part of the ship would need strengthening in any way. Moreover, all these discarded eights, sevens, sixes, and threes could be mounted on smaller cruisers, where they could do the work required of them, and thus money on new construction could be saved.

I think that you will agree with me in saying that with these improvements made, our pre-dreadnought type will not only possess far greater efficiency than they do now, but also that they will be able to stand

in the first line of battle with future dreadnoughts. The real question is this: Is this greater efficiency worth its cost? In view of the slight difference in the cost of maintaining in commission a "Connecticut" and a "Delaware," I think it is, and the SCIENTIFIC AMERICAN can do a lot toward making these paper changes realities.

HAROLD M. KENNARD.

Brooklyn, N. Y.

[In publishing this interesting study of a much-mooted question, we would point out that it seems to be the unanimous opinion of naval men in all navies that the re-arming of the older ships does not pay; that all appropriations for construction should be put into new ships. Such changes as are suggested above would involve enormously costly structural work on the hulls. There is no room for 12-inch guns in the 8-inch turrets.—Ed.]

The New Supplement Catalogue.

The publishers of the SCIENTIFIC AMERICAN have issued a new catalogue of the SCIENTIFIC AMERICAN SUPPLEMENT, in which 20,000 articles are listed. Many of these articles have been translated from foreign publications which are ordinarily inaccessible to English-speaking readers. Many of them also are papers read before the learned scientific societies of the world and accessible only in a few large public libraries. The articles are all carefully indexed so that the best information on any particular scientific subject may be found in a few minutes. The catalogue will be sent gratuitously to all who apply for it.

The Current Supplement.

The current SUPPLEMENT, No. 1781, contains some remarkable pictures of the Seven Wonders of the World, together with a good article on them. "The Practical Utilization of Insect Parasites" is the title of an article which will interest the farmer. Another installment of the Munroe and Hall paper on "Combustion and Explosion, a Primer on Explosives for Coal Miners," is published. Some new uses of paper are described. Mr. D. A. Arthur contributes an article on Chinese calendars. Since the Chinese have just celebrated their new year, this article comes out with particular timeliness. H. A. Humphrey's paper on an internal-combustion pump is concluded. Leonardo da Vinci, perhaps the only truly all-around genius of the world, is the subject of an excellent article by Edward P. Buffet. The Wright injunction is summarized and illustrated.

Comets Due to Return This Year.

In addition to Halley's, two other comets are due to pass through perihelion this year. The first is known as Tempel's second periodical comet, discovered in 1873 July 3rd at Milan. Its period is about 5½ years, and it was re-observed in 1878, 1894, 1899, and 1904, making its perihelion passage, on the last occasion, in November; it should therefore return this coming spring. D'Arrest's comet, discovered in 1851, is the second object, and is due to return during the summer of this year. Its period is about 6½ years, and it was re-observed at its return in 1857, 1870, 1877, 1890, and 1897, but it escaped observation, being unfavorably placed, in 1903.

Mr. Lynn, who gives these particulars in No. 418 of the Observatory, also recalls some of the historic occurrences which have coincided with the returns of Halley's comet.

The Scientific American Fourth Dimension Book.


The readers of the SCIENTIFIC AMERICAN have hardly forgotten the SCIENTIFIC AMERICAN'S Prize Competition for the best simple explanation of the Fourth Dimension. The prize of \$500 was awarded to Lieut.-Col. Graham Denby Fitch, U.S.A. His essay was published in the SCIENTIFIC AMERICAN for July 4th, 1909, and three others, which were accorded honorable mention by the judges, followed in successive issues.

It seemed to the judges that of the 245 essays submitted, a certain number showed more than passing merit. Inasmuch as the popular literature on the subject is by no means extensive, the publishers decided to intrust to Prof. Henry P. Manning of Brown University, one of the judges, the task of selecting some of the best contributions. This Prof. Manning has done. These essays, together with the essays which were awarded the prize and honorable mention, are now published in a book which has just been issued by Munn & Co., publishers of the SCIENTIFIC AMERICAN. An elaborate introduction is provided by Prof. Manning, in which he critically and yet simply discusses fourth-dimensional geometry and gives an excellent bibliography on the subject. The book sells for \$1.50 and can be ordered through any newsdealer or book-seller.

The deepest coal seams mined in America lie above a depth of 2,200 feet; some of the coal mines in England are developing seams at a depth of 3,600 feet, while coal mining is carried on at a depth of about 4,000 feet in Belgium.

THE GREAT FLOOD OF PARIS

BY THE PARIS CORRESPONDENT OF THE SCIENTIFIC AMERICAN



The Seine near the mint.

The inundation of Paris made many of the streets of that metropolis as navigable as the canals of Venice. The highest point reached by the water was 31 feet 4 inches above the normal at the Pont Royal. Not since the historic flood of 1615 has Paris been visited by such an inundation. On January 29th the waters began to fall, and the city for the first time began to feel safe. Even as it was, the Seine was swollen to thirty times its ordinary volume, and the current raced to the sea twenty times faster than usual. The banks have been overflowed for from half a mile to a mile on either side. That vast and wonderful sewer system which figures so dramatically in Victor Hugo's "Les Misérables," and which has been dwelt upon time and time again in every guide book of Paris, and that intricate system of subways which handles the vast traffic of Paris, have both played their part in this catastrophe. They served as conduits for the flood. Huge as they are, they were unable to cope with the turbulent waters. Pavements were pressed upward, and the water bubbled up into the streets. Apprehension was felt for the safety of the monuments of the French capital, an apprehension which is not yet stilled. It seemed almost certain that their foundations would be sapped. It speaks well for the work of French engineers that none of the twenty-four bridges that span the Seine was carried away, and that it was found necessary to close but eight of them. On the other hand, these bridges undoubtedly helped to dam the waters and to aid in the city's inundation. It speaks well for the architects and masons of the middle ages that the famous Cathedral of Notre Dame

should have stood in a lake for days and days without suffering injury. Many of the historic buildings of Paris were flooded, but fortunately the art treasures seem all to have been preserved with little or no injury. When the saturated ground dries out and contracts, it may be that some of the buildings will settle and possibly collapse. The Louvre, although flooded, was still able to serve its function of housing its priceless paintings and its statues. The great shops could not be opened on account of the water. The famous Theatre Français still gave its performances, but it used candles as it did back in the days of Molière.

It was but natural that the Chamber of Deputies should have continued its sessions. An exhibition of fright on the part of the legislators would undoubtedly have heightened the public terror. As it was, the members were ferried across the square to the chamber. The old Latin Quarter and the Champ de Mars, the Rue Royale, the Boulevard Haussmann, the Place de la Concorde, the Champs Elysées, were swamped.

Naturally the subways suffered heavily. Only the Gare du Nord seems to have escaped. The station of St. Lazare seems to have suffered most severely. As it was, the suburban traffic was entirely cut off, so that the sparing of the Gare du Nord served simply to give the frightened populace a place of questionable refuge. Fortunately the waters rose so gradually that the inhabitants of the sewers (the theme of many a thrilling French short story) and of the basements and sub-cellars of Paris were able to escape. Suburban towns lying somewhat lower than the city have suffered. The breaking of a dyke completely inundated

Gennevilliers. Its community of 10,000 persons was driven out by ten feet of water.

Paris may now be considered safe from water, but the danger from sickness still prevails. The stench of the stagnant water and of the drowned animals will undoubtedly continue for days. The Paris health authorities will find difficulty in coping with that situation.

The actual cause of the flood has not been fully revealed. Some explain it geologically by arguing that the basin of the Seine had become saturated during a mild winter, characterized by heavy rains and little evaporation. It will be safer before accepting this theory to await the investigation of the municipal engineers. Only when the floods have subsided and a careful examination can be made, will the full measure of the disaster be ascertained. The accounts of bursting sewers and subways and caving streets point indubitably to the necessity of reconstructing much of the famed Parisian sewer and subway systems. It will probably be months before Paris will conduct business as it did before the flood.

The engineering aspects of the flood have been sufficiently discussed in our editorial of February 5th. For that reason the results of this Parisian inundation need not here be dwelt upon again. It is clear that either the channel of the Seine must be widened by dredging, by the removal of river piers, or by the inordinately expensive construction of an artificial waterway around the city, a waterway which will serve the purpose of diverting the surplus of the Seine in time of flood and of discharging it below the city.



The gondollers of Paris.



A cart-ferry in one of the streets.

Reclamation of the Friedeburg Peat Bogs.

The total area of the peat bogs and moors of Germany is more than 3,000 square miles, of which about two-fifths are situated in Hanover and Schleswig-Holstein. The Prussian government possesses in East Friesland nearly 40,000 acres of upland moors, of which about 16,000 acres, known as the Anrich, or Friedeburg bogs, have for some years been the scene of an attempt at reclamation, which is being carried on with great skill and energy, though unfortunately with a degree of secrecy which makes it difficult to ascertain the exact facts, although the undertaking is of the greatest and most general importance. It is contemplated not only to reclaim the moors for cultivation and settlement, but also to make them the source of energy which will supply electric current for light and power to the surrounding region within a radius of thirty miles. Electric light, thus obtained, is already supplied to Emden, Wilhelmshaven, and several other cities and towns, and large quantities of ammonia, hydrogen sulphide, and other gaseous products are sold for use in various industries. The district to be reclaimed lies between the Ems-Jahde canal on the north and the Nordgeorgsfehn canal on the south, between which a connecting canal will be constructed. Short canals will connect the system with the canals of the older moor colonies to the westward. In all, 38 miles of new canals will be required. Their construction will necessitate the stripping of about 650 acres of moor, from which it is estimated that nearly 250 million cubic feet of peat will be obtained. If this work were done by the old Dutch method, the canals would not be finished in several decades, during which period the price of peat, already very low in this district, would continue to decline. Both of these difficulties were avoided simultaneously by the adoption of electrical methods, by which the work of excavation is carried on very rapidly and supplies its own fuel. In the center of the moor is a boiler plant, which consumes peat exclusively. The problem, of course, will be still more simplified when a method of producing electricity directly from heat is developed.

The first settlers established on the Friedeburg moor will carry on what is known as surface cultivation, and will at the same time gather peat, which they will sell to the electrical company, the charter of which runs for seventy-five years. As the high moor is thus cut down, the method of cultivation will be gradually changed to that which is employed in the low-lying moors of Holland.

All of the energy is supplied from the central power station of the Siemens-Schuckert Company, situated

on an island in the bog at the intersection of two main roads. From this point wires, supported by poles, radiate in all directions, supplying light and power to the whole country for many miles around. The main canal is bordered by several rows of poles and wires, one for the telephone, another for the peat-digging and agricultural machinery, a third for the high-tension alternating-current long-distance service. Current was to be supplied to the surrounding cities in November of this year. The station is equipped with two steam turbines of 1,800 horsepower each. The great plows used for the excavation of the canals have long been driven by electricity. The peat dug each day is compressed by electric presses into 4,000 blocks, which when dry are used as fuel in the central

when dried will furnish $1\frac{1}{3}$ million tons of fuel peat. This amount of fuel alone would supply the central station, producing five million kilowatt hours of energy for sixty-six years. On each side of each canal, a strip 165 feet wide is to be cleared of peat for cultivation and settlement. The peat thus obtained, added to that obtained from the canals, would enable the capacity of the station for the duration of its charter to be tripled.

An idea of the cost of the electric light and power thus furnished may be gained from the contract recently concluded with the town of Baut, in which the price of lighting current is fixed at about 10 cents, and that of power current at 5 cents, per kilowatt hour. At these rates a 16-candle carbon incandescent

lamp or a 40-candle metal filament lamp would cost about $\frac{1}{2}$ cent per hour, and an arc lamp from 2 to $6\frac{1}{2}$ cents per hour, according to its candle power. Thus the Friedeburg bogs are to be utilized as a field for colonization, as a source of light for the surrounding country within a radius of 30 miles, and as a cheap and reliable source of power for all the cities and farms of East Friesland. Although all the hopes which have been built on the enterprise may not be fulfilled, it is already certain that the reclamation and cultivation of bog land has entered upon a new and promising stage of development in consequence of this application of electricity. It must be admitted, however, that on the Friedeburg moor the conditions for reclamation are especially favorable. The land is in general level, and it has already been superficially dried and smoothed by burning. The roads through the moor are already bordered



Scenes from the great Paris flood.

station. In the gas generators 40,000 cubic feet of fuel gas and 30 pounds of ammonium sulphate are obtained from 100 pounds of peat. The combustion of this quantity of fuel gas generates 273 horse-power hours of energy, while the sale of the ammonia compounds pays a good interest on the capital invested. Contracts for supplying light and power to most of the surrounding towns and cities have already been signed. The duration of the contract in most cases is forty years, while the charter of the Siemens-Schuckert Company will remain in force seventy-five years. The area assigned for cultivation and settlement comprises about 17,000 acres. The digging of the canal requires the peat to be removed from a strip about 150 feet wide, so that the construction of the 38 miles of canal will involve the stripping of 650 acres. The average depth of the peat is $11\frac{1}{2}$ feet. Deducting the superficial stratum of 30 inches, which is comparatively worthless, the digging of all the canals will produce about 247 million cubic feet of peat, which


with rankly-growing grass.

Peary a Rear Admiral.

Commander Robert E. Peary has been made a rear admiral of the highest grade and with maximum pay, so far as the Senate can accomplish such recognition of his services. The bill recently introduced by Senator Hale was favorably reported from the Committee on Naval Affairs and promptly passed without discussion.

The bill authorizes the President to appoint Commander Peary a rear admiral with an extra number and places him on the retired list. An amendment was adopted giving him the pay of a rear admiral of the first grade.

The top notch pay of a rear admiral is \$8,000 a year and that of the same officer on the retired list three-fourths of his active compensation. Thus Admiral Peary will receive \$6,000 a year for the remainder of his life.



The Gare du Quai d'Orsay flooded.



The submerged Rue de Lyon.

Industrial Chimneys and Water Towers of Concrete Blocks

BY H. PRIME KIEFFER

The employment of concrete blocks for the construction of factory or industrial chimneys and water towers, is one of the most natural uses of that new form of building material. It is very surprising that the idea of utilizing separately molded blocks for this purpose should have come from Europe instead of America, where blocks have found a wider range of use than in any country in the world. The system is the ideal one for the rapid erection of factory chimneys. In the United States there have been in use some twenty different systems in which armored concrete is employed, but they all have some primary form of scaffolding in their designs. This is the underlying reason why those chimneys cannot be constructed more economically and rapidly. The method of constructing chimneys of separately molded concrete blocks is the invention of M. Dumas, an engineer and architect of Brussels, Belgium. It is controlled by Leon Monnoyer et Fils, also of Brussels, who furnished the data and photographs for the present article. The system is notable for its simplicity, its beauty of form, its economy in cost, and its adaptability to rapid construction.


The chimneys are like all others in that they are composed of three parts, the foundation, the base, and the shaft. The shaft is formed of reinforced concrete of a special design. The form of the blocks is shown in the accompanying diagram. The number of blocks in each course always remains the same, yet there is a taper to the chimney. They are placed in regular horizontal courses to the required height, and upon the top is placed a special capping block of either concrete, cast iron, or cut stone.

The builders work on a rough platform and from the interior of the structure, and each block is received by them ready for its particular position. Two men are usually employed above in laying the blocks, and two below to hoist them to the platform. The blocks in each succeeding course are placed in the opposite direction; that is to say, all the even courses will have the same direction and all the odd courses will take the reverse of this. In this manner, the joining of the blocks of one course, where they do not meet perfectly, will be covered by the blocks in the course above. As shown in the diagram, each block has at one of its extremities, a "hook" similar to the shape of the letter "U." This "hook" forms a hollow space which extends the full length of the chimney, and of course there will be just as many of these hollow spaces as there are sides to the chimney. Through these vertical hollow spaces are placed vertical iron rods B, varying in diameter according to the height of the structure. At each course these rods are tied or bound to the courses by U-shaped flat iron yokes E. These, in turn, are wired to a small iron rod D which is placed between the courses horizontally and in a groove made for it in the top of the blocks.

The placing of the vertical rods in the openings and not in the substance of the shaft proper, forms an important advantage of this system. The reinforcement is thus kept at a low temperature, and is not subject to the injurious effects which would arise from unequal expansion if the steel was in the center of the mass. Ferro-concrete is indestructible by fire, so long as the temperature of decomposition of concrete is not reached; but it must be remembered that although the coefficients of expansion of cement are the same, the coefficients of conductivity are

very different, and fracture is likely to arise if, from this cause, the temperature of the iron exceeds that of the concrete. Consideration of this condition is especially important in the case of a structure which is heated on one side only, such as a chimney.

A clever idea in connection with the design of the blocks is that there is need for only three, or at the most, four sizes of blocks for the average chimney of



- A. Indicates the hidden reinforcing rods of the blocks.
- B. The vertical steel reinforcing rod.
- C. The concrete of the block.
- D. The reinforcing rod connecting all the blocks in any one course.
- E. A flat U-shaped iron brace which holds the vertical rod at a fixed position in the hollow space.
- F. Mortar filling.

Cross section of a portion of a concrete water tower. Section at one end of the joining of two of the courses.



Concrete-block chimney carrying two reservoirs of reinforced concrete.



Concrete-block water tower for the 1910 International Exposition at Brussels, Belgium.

INDUSTRIAL CHIMNEYS AND WATER TOWERS OF CONCRETE BLOCKS.

150 feet high and with a taper of one to three per cent. This is made possible by the following arrangement: The molds by which the blocks are made consist of but three cast-iron plates, held together by wooden stop blocks, and three ordinary iron clamps. Different sizes of blocks can be made therefore, by simply changing the relative positions of the plates and the wooden stop blocks. After the blocks are molded, they are placed in the following manner. Take, for instance, the first row, at the base. Here, naturally, the blocks are of the largest size, and the arm of the block the longest. The arms of the blocks in this course are placed just to the edge of the hooks of the blocks, and in the next course the arms are placed just a little farther into the hooks, and thus

each succeeding course has a diameter smaller than the one below it, and in this manner, the taper of the chimney is obtained. As the longest blocks are some three feet in length and the distance across the semi-circular opening about six to eight inches, it is possible to make a considerable taper in this manner. For a taper of $1\frac{1}{2}$ to 2 per cent, the size of the blocks is changed every forty or fifty feet. The blocks may, of course, be laid with absolutely no taper, and then one size, only, of blocks is used. Some chimneys have been constructed on this plan; but their appearance is not so graceful as those having a slight taper.

The concrete blocks are usually made at the chimney site, although they can of course be molded at a concrete block factory; and this may be economical in case there are several chimneys under construction in the same district. The proportions for the concrete mixture vary somewhat, but the usual mixture consists of about five parts gravel, three of sand, and two of cement. Dust of stone is used sometimes, and has given very good results. From an architectural point of view, the chimneys constructed with this system present a pleasing appearance. Being thinner than brick chimneys, they rise more gracefully from their bases, and yet the strength and stability which they

actually possess is at once suggested to the eye by the appearance of strength which is presented by the protruding rounded angles.

A number of chimneys and water towers have been built in Europe after this system, and the two photographs presented in connection with this article show a water tower, and a combined water tower and chimney. The water tower, which is located in Uccle, a suburb of Brussels, Belgium, will be used in connection with the 1910 exposition to be held in that city. The tower and tank have a height of 145 feet and the latter has a capacity of 280,000 gallons. The structure is circular and is built entirely of concrete blocks and without molding of any kind excepting that used in the building of the concrete reinforcing struts surrounding the base of the tank proper. The inside of the tank is built up in practically six stories, connected by a winding stairway. These different floors are divided into rooms, which will all be occupied by engineers, foremen and other workmen during the exposition. The stairways are placed along the outer walls and the water remains in the center, inclosed by a concrete covering of square cross section.

Oil That Cold Will Not Affect.

It is often difficult to keep machinery properly oiled in cold weather, as the oil freezes in the oil holes and the cups, and the oil upon the ways of the lathe and planer becomes stiff, causing the machines to work hard. A good oil for winter use is made by mixing graphite with cylinder oil until in a thick or pasty consistency, and then adding kerosene until it flows freely. This oil will not become stiff at 14 degrees below zero, and is valuable to those operating machinery outside or in cold shops.—Power.

In his presidential address to the American Street and Interurban Railway Association, Mr. Shaw, at Denver, said that in round numbers there are 1,250 street and interurban railway companies in America, with a total of 35,000 miles of single-track and 75,000 passenger cars. The passenger carried annually is 10,000,000, and the gross income \$44,000,000.



THE CONSTRUCTION OF AN IMPROVED SILICON DETECTOR.

BY GEORGE F. WORTS.

The detector described here is one that can easily take the name "Improved," being a radical departure from the coarsely-adjusted detectors generally used. If properly constructed and connected, it will easily pick up wireless messages sent from very distant points. The component parts are shown in Fig. 1.

The base of the instrument is fashioned from hard rubber, $3 \times 2 \times \frac{1}{2}$ inches; $\frac{1}{8}$ -inch holes are bored in it one inch from either end. A support for the crystal cup is made from annealed brass, 4 inches in length, $\frac{3}{8}$ inch in width, and $\frac{3}{16}$ inch in thickness. It is bent to an L shape, as can be seen in Fig. 2.

The crystal cup is turned from brass rod $\frac{1}{2}$ inch in diameter. It is threaded, as seen in Figs. 1 and 2, to fit a thumb nut. The crystal is fastened in the cup by means of lead. This insures a good contact. The ad-




Fig. 1

SECTIONAL VIEW OF THE ASSEMBLED DETECTOR.

justing mechanism can be made to move a steel hair spiral, the point of which makes contact on the silicon, to the thousandth part of an inch. The phosphor-bronze strip upon which the spiral contact is fastened is 3 inches in length, $\frac{1}{2}$ inch in width, of No. 28 B. & S. gage sheet. It is bolted to a cube of brass which in turn is fastened by means of a machine screw to the base. This screw serves also as a binding post. The brass post supporting the adjusting screw is of $\frac{3}{16}$ inch brass of the same stock as the L-shaped post. It is $2\frac{1}{4}$ inches in length, $\frac{3}{8}$ inch in width, and $\frac{3}{16}$ inch in thickness. A $\frac{1}{8}$ -inch hole is bored $\frac{1}{2}$ inch from




Fig. 2 Fig. 3
SUPPORTS FOR THE CRYSTAL AND THE ADJUSTING DEVICE.

one end to admit the machine screw that binds it to the brass cube. Another hole is bored $\frac{1}{4}$ inch from the other end and tapped to fit the adjusting screw. The adjusting screw has a large knurled rubber handle for adjusting purposes, also a lock nut to be tightened when the detector is at its most sensitive point.

This detector is comparatively easy to construct and is inexpensive. The one undesirable quality in silicon detectors—their ability to get out of adjustment—is almost entirely eliminated in this detector, due to the use of the spiral instead of the solid contact.

INCREASING THE EFFICIENCY OF WIMSHURST ELECTRIC MACHINES.

BY GEORGE J. MURDOCK.

The Wimshurst static electric machine, as is well known, consists of two glass circles revolving on a compound axis in opposite directions. As usually made, this machine is inferior to the Toepler-Holtz type, although somewhat cheaper to make, and superior in simplicity. The latter quality has been without doubt one of the chief reasons why it is in general use where

ever the small electric discharge this machine will give as commonly made, will answer the purpose.

In building both kinds of these interesting machines, it is the practice to varnish the revolving glass circles with white shellac dissolved in alcohol. In the higher grade machines the best quality of shellac and grain alcohol are used for this varnish, but for the toy variety wood alcohol and the cheapest grades of shellac are used. Some years ago the writer was building both Wimshurst and Toepler-Holtz statics, but was unable to obtain a discharge from the Wimshurst type that could compare with the other kind, even when the glass circles were of the same diameter.

The development of the machines in both cases had extended over a series of years, and it was supposed the limit was reached. At this time the Toepler-Holtz machines were giving with 26-inch circles, sparks (using the Leyden jars) equal to the radius of the circles or 13 inches long, thick as the thumb, and when discharging detonating like the sound of a rifle.

The Wimshurst machines with an equally large circle would not give sparks over 4 inches long, and about as thick as a knitting needle. Finally, in building a lot of six machines it was found some were much better than others. Strenuous efforts were made to ascertain what caused the increase in efficiency, but without discovering anything different in the construction of those that showed the improvement from the others. In the next lot after this, however, all of the machines were capable of giving sparks 6 inches long, although the diameter of the glass circles was but 14 inches. The thickness of the spark had also increased to the size of a pipe stem, and this wonderful increase of efficiency was attributed to some quality inherent in the glass of which the circles were made, but inquiries made of the manufacturers of the glass failed to disclose any different methods of making the glass than had been followed for many years.

About this time the writer in varnishing some circles held one of them up to the light, and was struck by its light green appearance, and although giving it little attention at the time, gained the impression that this change in color might have something to do with the increased efficiency still unaccounted for. Shortly after this a new lot of machines were built, and every one of them had reverted to first principles so far as the spark was concerned, it being short, weak, and spindling. In the effort to find out what had caused the reversion, the writer called to mind that just before varnishing the last lot a new brush had been used in a new batch of varnish.

It is customary in making the varnish to dissolve the shellac gum in a glass jar with a mouth just large enough to get the brush in conveniently, and the brush is left in the jar between the construction of the different lots of machines. It was found that the old brush had been shedding its bristles, and to prevent this it had been bound around with some fine copper wire. The action of the varnish had been to corrode the copper, and the salt had given the varnish the faint green color noticed some time before on the glass circles, although there had been nothing different in the color of the body of varnish in the jar apparent.

The suspicion dawned on the mind of the writer that this had been the cause of the increase of efficiency, and the lack of it in the last lot of machines. Another batch of varnish was accordingly made, and in it was put about a quarter of a pound of fine bare copper wire. A new brush was procured, and placed in the jar, and the varnish allowed to stand in a warm, dark room about a week, when it had assumed a light green color, and was used to coat the circles of a new machine.

This machine was found on trial to be even more efficient than the best of the others.

In experimenting with the newly-discovered varnish, it was found that if it was allowed to become a dark green the voltage of the machine was interfered with, and while the spark would be thicker it would not jump as far. The best results were obtained when the color was a very light green. The reason for the increased efficiency was thought to be due to a decrease of the resistance of the shellac between the sectors on which the equalizing brushes bear.

This varnish was tried on Toepler-Holtz machines without their showing any marked increase, perhaps due to their being already capable of delivering sparks equal to the radius of the glass circles.

The use of varnish made in this way will be found by amateurs and others to add greatly to the capabilities of the Wimshurst machine, and besides the light green color on the glass adds to the beauty of the instrument.

Many builders of Wimshurst machines as well as those experimentally inclined have trouble in making the brass sectors stick to the shellac. As tinfoil soon wears through from contact with the equalizer brushes, thin sheet brass is used by many on the better grades of machines to secure durability. Brass sectors can be made to stick permanently in the following manner:

In varnishing the circles, about three coats is generally applied with a large flat camel's hair brush.

Each coat is allowed to become moderately hard before applying the next. After the last coat is applied, and has stood about fifteen minutes, mark the locations where the sectors are to go (they should be evenly spaced), and after applying some varnish to the under side of the sector, press it down into the soft varnish until a slight ring swells up around the margin of the sector. After the varnish is hard, an examination will show the sector dovetailed into the varnish, from which it will never separate, as it will if cemented in any other way on account of the expansion and contractions of the brass being so much greater than the glass, and causing the sector to become loose.

SILVERING GLASS AT HOME.

BY A. J. JARMAN.

A good glass mirror, made with one's own hands, is a thing to be proud of. Mirrors are now seldom made by the tinfoil and mercury process, because of the dangerous character of the work, but pure silver is used instead. The silver process is not in the least dangerous to the workman. The formula here given is one that has been in use in several looking glass and art mirror factories in the city of London. The




Fig. 1 Fig. 2
APPARATUS REQUIRED FOR SILVERING GLASS.

chemicals used must be of absolute purity (chemically pure) and all operations in preparing the glass must be carried out with care and scrupulous cleanliness. The surface to be silvered must not be pressed upon by the fingers or thumbs, they would leave an indelible impression.

The first thing to be done is to make a small table out of a piece of slate about $\frac{3}{4}$ or $\frac{1}{2}$ inch thick, 10 or 12 inches wide and 18 inches long. These measurements are not binding, any piece of slate about the above size will do. A wooden trough must be made with grooves at the top edges for the slate slab to rest in. There must be a space of 2 inches between the slate slab to the wooden bottom, as indicated in Fig. 1. In this space is a coil of pipe arranged as shown in Fig. 2. The pipe is of about $\frac{3}{4}$ inch bore, and through it steam is passed to raise the temperature of the slate slab to about 120 deg. F., in fact just hot enough for the hand to bear. The steam can be supplied from an ordinary tea kettle placed near the depositing table with a rubber tube connecting the coil to the spout of the kettle. Uniform heating of the slate slab is essential. The coil can be easily made of $\frac{1}{4}$ -inch iron gas piping, screwed into U-shaped cast-iron connectors, as shown in Fig. 2. The slate slab can be covered with black oilcloth and made perfectly level. The following stock solutions must be made up and carefully filtered through absorbent cotton, ready for use:

Stock Solution A.—Nitrate of silver, 3 ounces; distilled water, 10 ounces; strong water ammonia, 12 $\frac{1}{2}$ ounces. This solution must be stirred well and allowed to stand five or six hours, then add 10 ounces more of distilled water and filter.

Stock Solution B.—Rochelle salts, 4 ounces; distilled water, 20 ounces.

Stock Solution C.—Distilled water, 40 ounces, protochloride of tin, 5 grains.

Clean the glass plate or plates with very fine rouge and water, taking care that no trace of grease whatsoever comes into contact with the glass or the cloths or chamols leather used for polishing. When cleaned, the plate must be flooded all over with the tin solution. Pour this solution off and wash the plate well with distilled water. Lay the plate wet side up upon the table, with four clean wood wedges at each corner. Let the glass rest on the wedges, so as to allow a slight adjustment, if required, for leveling. The mixture for silvering is made up as follows:

Distilled water, 20 ounces; stock solution B, 1 drachm by measure; stock solution A, 1 ounce by measure. The glass plate being quite level, and still wet, pour this mixture carefully and slowly upon the center. It will flow evenly all over until it stands about one-eighth of an inch deep all over the plate. Any tendency to run to one end must be rectified by the wedges. The plate now being completely covered with the silvering mixture must be left to itself for about two hours, the heat being kept up during this time, and when it is found that the whole of the silver has been deposited, the liquid must be poured off by tilting and allowed to run into a stoneware crock and saved


for the waste silver it contains. If it is desired to increase the thickness of the deposit of silver, the operation must be repeated as soon as the silvering is complete; wash the plate well in a soft stream of running water, stand it cornerwise to drain and dry. When dry the following protective varnish must be used as a coating to protect the deposited silver: Shellac, $\frac{1}{2}$ pound; wood alcohol, 6 pints. As soon as this coating has dried it must be painted over again with the following paint: Red lead, $\frac{1}{2}$ pound; white lead, $\frac{1}{2}$ pound; mixed with enough boiled oil and a small quantity of turpentine to make a good covering with a single coating. A small quantity of gold size must also be added to insure quick drying and a tough adhering quality. The mirror is now ready for framing. If much work has to be done, it will be advisable to cover the slate all over with a piece of felt, and keep the felt wet during the operation for two reasons: First, no pieces of woollen fiber can settle upon the plate, and secondly, the heat from the slate slab is communicated to the glass better than from a dry surface.

For a regular workshop a very good size is 4 by 7 feet, with a gutter cut around the slab, so that the spent silvering liquid can run from the tilted plate, around the table, and be collected by running through a hole at one corner. In this case the liquid will be sure to come in contact with the felt. This will prove of no consequence, because in time it will become saturated with silver, which will realize twenty times its first cost when sent to the silver refiner, and not only pay for a new felt covering, but increase the size of the pocket book at the same time. The quantity of nitrate of silver required to coat a square foot of glass with a moderate coating of silver is 18 grains. An estimate as to cost can be made from this amount.

SELENIUM CELL WITH CONTACT BY PRESSURE.

BY W. S. GRIPENBERG.

The usual method of making a selenium cell consists in pressing the electrodes against a piece of crystallized selenium, which decreases its resistance to an electric current, when submitted to the action of light. The quality of selenium can be perfectly controlled, as it needs not come in contact with metal when fluid in which state it dissolves nearly all metals (i. e., the electrodes). This is of importance, because small quantities of other elements sometimes have considerable influence on its sensitiveness. Moreover a piece of selenium, that for some reason has lost its efficiency, can be easily replaced by another piece, at low cost. The most important point, however, is that the contraction or decrease in volume (5 to 8 per cent), which is inseparable from the process of crystallization, has no influence whatever upon the contact with the electrodes, as the piece of selenium is



SELENIUM CELL WITH CONTACT BY PRESSURE.

given its definite form after the contraction has taken place. Strong currents of short duration do not lead to the destruction of the cell, as there is full scope for expansion.

Despite these important facts, this method has not been hitherto used, because very thin plates of selenium are necessary, as the action of light is limited to an extremely thin layer of the exposed surface (calculated by Marc to be about $1/500,000$ inch thick). Moreover, selenium is rather fragile and being of high resistance, heavy pressure must be used in order to realize good contact.

The author discovered that selenium, when molten between a cold and a very hot glass plate, strongly adheres to the latter, after the crystallization. It is thus possible to cover a thin ($1/250$ inch) flexible glass plate with an exceedingly thin coating of selenium ($1/1,000$ to $1/30,000$ inch) which has a highly polished surface that gives very good contact with the electrodes. These consist of gilt stripes on a glass plate (Fig. 1). There are from 250 to 2,500 electrodes on every inch.

Cells constructed after this method are very reliable and show remarkable constancy. They are of small specific working surface. The following is a description of a cell actually made:

Working surface = $\frac{1}{4}$ by $\frac{1}{4}$ inch.

Resistance in the dark = 20,000 ohms.

Resistance in ordinary daylight = 10,000 ohms.

Resistance in strong light = 3,000 ohms.

Maximum intensity of current = 0.0018 ampere.


Fig. 2 gives a diagram of the cell.

Fig. 3 is an end view of same.

Glass plates with a thin coating of metal (silver) have before now been used as electrodes for substances sensitive to light. This combination or at least the results attained are new.

SOME SCIENTIFIC AMUSEMENTS.

The Candle and the Funnel.—Ask a person to extinguish a lighted candle, two feet distant from his mouth, by blowing through a common tin funnel with his lips applied to the stem. Almost invariably, he will fail to accomplish the feat, although he could easily have blown out the candle without using the funnel. Now put your own mouth to the stem of the funnel and blow out the candle. If you have any skill in performing tricks you can repeat this one many times without betraying its secret to the average spectator. The secret is this: When you blow into the small end of a funnel, your breath follows the inner surface of the cone, and not only shuns the axis, but produces eddies of such a character that there is actually a slight back draft or inward current at the center of the wide mouth of the funnel. You, therefore, hold the



RIGHT AND WRONG WAY OF BLOWING OUT A CANDLE.

funnel so that some part of its conical surface would, if extended, strike the candle flame. An inexperienced person naturally directs the axis of the funnel toward the candle and consequently fails to extinguish the flame. If he stands quite near the candle and blows gently the flame will even be drawn toward the funnel by the inward current. The whirling motion of the air may be made visible by using a glass funnel and filling it with tobacco smoke.

Paradoxes of Ebullition.—Everybody knows that water boils at the temperature of 212 deg. Fahr. But if an uncorked bottle partly filled with water is set in a saucepan containing water in which a good deal of salt has been dissolved, and the pan is heated over a spirit lamp or otherwise, the water in the bottle will begin to boil while the water outside still remains perfectly quiet. Yet the water outside must be at least as hot as the water inside (212 deg. Fahr.), for the latter is heated by the former. Hence we see that water which contains salt in solution does not boil at 212 deg. Fahr. The same effect is produced by dissolving any other solid substance in the water.

Now, if the bottle is taken from the hot brine and corked, the water in the bottle stops boiling, but it will boil again, even after it has cooled many degrees, if cold water is poured on the upper part of the bottle. The explanation is that the boiling point of water is affected by pressure. It is about 212 deg. Fahr. under the ordinary pressure of the atmosphere (exactly 212 deg. when the barometer stands at 30 inches), but if the pressure is reduced, water boils at a lower temperature. When the water bottle was corked and taken from the fire, its upper part was filled with steam at atmospheric pressure, which had expelled the air originally present. As the bottle cooled, this steam partly condensed and its pressure was diminished, but not sufficiently to permit the water to boil, because the water cooled also and its gradually diminishing temperature was always a little below the boiling point corresponding to the actual pressure. But the application of the cold water caused a rapid condensation of steam and a sudden lowering of the pressure without having much cooling effect on the water, which consequently began to boil.

Distillation.—The same apparatus may be employed to illustrate the process of distillation. The brine in the pan is replaced by fresh water, a hole is bored in the cork and a glass tube is fitted to the hole. To the water in the bottle is added one-tenth its volume of alcohol, or less. The bottle and pan are placed over the lamp, as before, and heated gently. Before the water in the pan has reached the boiling point the vapor of the more volatile alcohol (mixed with a lit-

tle water vapor) issues from the end of the glass tube, where its presence can be detected by its odor or by the application of a lighted match, which will result in the production of a tall blue flame. The jet should not be lighted until the mixture has been heated long enough to expel the air from the bottle, as the ignition of a mixture of air and alcohol would produce a violent explosion. For this reason the cork, though it should be air-tight, should not be inserted too tightly. With this precaution an explosion will drive out the cork, instead of shattering the bottle. This experiment, and the others performed with this apparatus, should not be attempted by children or careless persons.

Hero's Fountain.—If the jet of flame issuing from the tube is extinguished and the tube pushed down until it dips into the water, a fine liquid stream will




MODIFIED FORM OF HERO'S FOUNTAIN.

be thrown high in the air by the pressure of the mixed vapors of alcohol and water in the upper part of the bottle.—Kosmos.

A SIMPLE EFFECTIVE FILTER.

The filter here described was first made by the writer in 1878, and used originally for filtering gelatine emulsions. As a water filter it is both simple and effective. Procure an ordinary kerosene lamp chimney. Fit over the end of it two or three thicknesses of washed cheesecloth. Press a tuft of absorbent cotton into the small part of the neck for about three inches in depth, insert



HOME-MADE FILTER.

the chimney, and place it in a hole cut in a wooden shelf as a support. Pour the water in until the filter is filled, when it will be observed that any organic matter, chips of iron rust, etc., will be retained by the cotton. The fine organic matter may penetrate the cotton for about one inch, but no farther. The resultant filtered water will be bright, clean, and pure.

A paper dealing with "Research on Metallic Filament Lamps," by Mr. F. H. Reakes Lavender, was recently presented at a meeting of the Birmingham Institution of Electrical Engineers. The research was undertaken in order to investigate the conditions of working as regards voltage, and efficiency and percentage drop in candle-power, giving the most economical life in the case of metallic filament glow lamps, and to determine as far as possible the cost of illumination with this source of light. The author stated that the useful life of a lamp, and the drop in candle-power which it was advisable to allow for a given voltage, depended on the cost of current and the price of the lamp. The cheaper the current, the longer the life, and the greater the admissible drop. Taking the current at 5d. per unit as an average price, and the lamp run at rated voltage, then it paid in the case of the tantalum class of lamp to throw it away as soon as the candle-power had fallen to 3 per cent below its original value. This result appeared startling at first, considering the large initial cost of the lamp. However, by the time that point was reached the lamp had been burning for 1,500 hours at the best possible efficiency, so that the cost of the lamp per candle-power had become small.

RECENTLY PATENTED INVENTIONS. Pertaining to Apparel.

ARTIFICIAL AIGRET AND LIKE ARTICLE.—M. VEIT, New York, N. Y. The aim in this case is to provide an artificial ornament, such as an aigret, plume, feather, hat and dress trimming, military ornament, hair ornament and the like, and formed from a sheet of celluloid or other material, and arranged to provide graceful filaments projecting integrally from a self-sustaining core.

BODY BRACE.—R. F. MACCLEMMY, New York, N. Y. This invention relates more particularly to a shoulder brace, in which there are two back sections, each having an arm hole therein, lacing or cords connecting the sections together, and belt sections connected to the ends of the cords and buckling together in front to adjust the back sections in respect to each other. Mr. MacClemmy has invented another body-brace, and one of its main features resides in the construction of the upper ends of the stays, so that one of the stays is secured across its top and the other is left partially free; so that it may overlap the first-named stay, and the intermediate portion will be folded to a definite and predetermined position.

Of Interest to Farmers.

CONCAVE FOR THRESHING-MACHINES.—W. L. HAY, Franklin, Tenn. This improvement is for use for threshers of all kinds. It provides a concave having adjustable sections so that one of the sections may be shifted to disengage the teeth without disturbing the relative position of the teeth immediately adjacent. Simple means are provided for effecting the adjustment.

HARROW.—A. M. HAUCK, Seattle, Wash. This invention relates to harrows provided with wheels for cutting or pulverizing the soil or clods. The invention provides means whereby the shafts upon which the wheels are mounted may be moved toward and from one another, in order to vary the degree of fineness with which the earth is pulverized.

Of General Interest.

BATTLESHIP ARMOR.—E. P. WATSON, Sr., Bentonville, Ark. The armor is such as carried by battleships, protected cruisers, and other warships. Merchant ships can be constructed near the water-line in accordance with the present improvement, but the shell-resisting parts of the armor may be omitted during peace, but applied to the ships so as to transform them into armored ships of war.

PROCESS OF WIRING BOTTLES.—O. TOPP, Blagaardsgade 16a, Copenhagen, Denmark. The invention is especially adapted to prevent the twisted sharp edges of wire from sticking out and thereby constituting a common source of danger from cuts and wounds to those who later on have to handle the bottles. The process can be carried out by hand or with a pair of pliers.

LIQUID-COOLER.—E. RUSSELL, New York, N. Y. An object of the inventor is to provide a cooler in which ice or other refrigerating substance is contained in a vacuum and is surrounded by vacuum chambers, to minimize the melting of the refrigerating substance, owing to the transmission chamber, and which has means for conducting the fluid to be cooled, through the refrigerating chamber.

SCREEN FOR IRRIGATING-DITCHES.—T. A. POWERS, Slack, Wyo. This invention is an improvement in screens for ditches, especially for irrigating ditches to be placed at or near head gates. In operation the screen will stand normally when the gate is in position for use at an angle of about forty-five degrees, hinged at its lower end and adapted at its upper end to be depressed down stream by the action of pressure from above and to permit the debris to pass after which the screen may be readjusted to position for use.

DISPLAY-RACK.—J. A. BOGAR, Lyons, Pa. This invention relates more particularly to such racks as are provided with frames, on which rugs, wallpaper or the like can be suitably arranged for display purposes, and which are further provided with means whereby any number of objects on display can be temporarily removed from the frames to disclose a desired one originally concealed by the same on account of their super-position.

FOLDABLE TABLE AND ATTACHMENT THEREFOR.—H. F. THOMAS, Natrona, Pa. This invention refers to an improvement in foldable legs for tables and in a pedal attachment for such legs. It is particularly designed for use with tables, or like supports, for portable foldable dark rooms used for photographic purposes, but it is not restricted to such use.

Hardware and Tools.

COMBINATION PADLOCK.—L. ROSEN, Union Hill, N. J. In this case a locking mechanism is controlled by a combination mechanism. The device is intended to be strong in construction, inexpensive and of a type that cannot be readily picked. Simple means provide for a series of combinations that may be changed almost indefinitely.

LOCK.—J. JUNKUNC, Pocatello, Idaho. In the arrangement of this combination padlock the combination may be easily changed, and should any one attempt to discover the combination by bringing the recesses into register, with the bar withdrawn, such attempt would

be thwarted, since the combination would not answer after the disk was returned to its first position.

Machines and Mechanical Devices.

AUTOMATIC ADJUSTABLE REEL.—C. H. COON, Saugerties, N. Y. The aim of the inventor is to produce a reel in which the virtual diameter remains sufficiently constant. In other words, the diameter of the reel reduces itself automatically as the web of the material wraps upon it. In this way the length of material wrapped upon the reel in one revolution remains constant, and when the material on the full reel is cut, the sheets will all have the same length.

COUNTERBALANCE FOR WATER-PUMPS.—W. KOETHE, JR., Brinkman Ridge, Wis. The purpose of this invention is to provide a construction for a counterbalance that is an attachment for a water pump, which will balance the weight of the pump rod and the bucket on it, and of water lifted by the rod and bucket on it, and of water lifted by the rod and bucket, thus reducing labor in operating a pump having the improvement.

STEAM RENDERING-TANK AND PRESS.—C. H. STADLER, New York, N. Y. The objects here are, first, to provide a tank for cooking materials out of which grease, oils, etc., are rendered, under steam pressure; second, to draw off the grease, oils, etc., after the materials have been cooked; third, to drain the water and remaining grease from the materials left in the tank; fourth, to press the materials for the removal of any still remaining oil, grease, water, etc.

Prime Movers and Their Accessories.

ROTARY ENGINE.—W. G. SHEPARD, Indianapolis, Neb. The device consists, generally speaking, of a rotor having a vane fixed thereon, a fulcrum valve, means for letting a motive fluid in between said fulcrum valve and said vane on either side thereof, and means for exhausting the motive fluid from between the fulcrum valve and the vane.

INTERNAL-COMBUSTION ENGINE.—F. REAUGH, Oak Cliff, Texas. The invention resides in a peculiar arrangement of a plurality of cylinders in conjunction with a single main or engine shaft, with which shaft one or all of the cylinders may be connected independently and at will, thus enabling the main shaft to be driven from the operation of a single cylinder while the other cylinder or cylinders, with all of their immediately allied parts, remain absolutely inactive.

Railways and Their Accessories.

RAILROAD-TIE.—J. S. MILLER, Clinton, Neb. Mr. Miller's invention has for its purpose the provision of a concrete tie on which the rails may be supported, the tie being so constructed that it is reinforced by the means provided for securing the rails. Also the provision of means in connection with the reinforcing members for spacing the ties apart at a predetermined distance from each other.

Pertaining to Recreation.

BOWLING-CABINET.—R. H. MULFORD, Connelville, Pa. This cabinet is especially adapted to be used as part of the furniture of a bowling alley. The object is to produce a cabinet which will constitute a bench upon which the players or spectators may seat themselves, and which has a special construction enabling the cabinet to hold the bowling pins, the bowling balls, and also the hats and coats of the players.

PYROTECHNICAL BUTTON.—A. JEDEL, New York, N. Y. A special object of this invention is to provide a trick or joke device, which may be secured on the person, and which when ignited, produces a startling or unexpected effect. Means provide for safely and securely holding the compound, so that it may be worn and ignited, while on the person without liability of personal injury.

GAME APPARATUS.—C. F. DOERR, Yorkers, N. Y. The invention pertains to parlor games, and its aim is to provide an improved game apparatus, more especially designed for playing baseball, and arranged to afford amusement to the players and onlookers and to require considerable skill on the part of players to successfully play the game.

MUTOSCOPE.—A. S. FERGUSON, Springfield, Mo. The invention is adapted for use as a toy or parlor amusement, the same consisting essentially of a series of photos or other pictures arranged radially in a circle, thus forming what may be termed a picture-wheel, which being rotated, the pictures are successively turned back and thus exhibited to the onlooker.

Pertaining to Vehicles.

GASOLINE-FEED.—A. W. HOFACKER, Bottineau, N. D. The object here is to provide a means for insuring a constant supply of liquid fuel to the carburetor of a power driven vehicle, regardless of the inclination of the body of the same as when hill climbing. In vehicles having the engine in front, and the fuel tank beneath the seat, the carburetor will not get a sufficient supply of fuel when the front of the vehicle is elevated, as in hill-climbing, especially if the fuel supply is low.

NOTE.—Copies of any of these patents will be furnished by Munn & Co. for ten cents each. Please state the name of the patentee, title of the invention, and date of this paper.

NEW BOOKS, ETC.

MANUAL OF PHYSICAL GEOGRAPHY. By Frederick Valentine Emerson, Ph.D. New York: The Macmillan Company, 1909. 8vo.; 291 pp. Price, \$1.40.

The exercises in this manual have for the most part emanated from the author's classroom experiences. There is presented a variety of exercises, some of them advanced in character that will cover topics capable of laboratory illustration usually presented in a course in physical geography. Some of the questions are practical. For instance, let us take up the subject of fog. Here are a few of the questions. What is fog? What is its general cause? Where have you seen it occur? If over land or water, what is the apparent cause? How dense is it? Does it disappear suddenly or slowly? Did you see the fog around a piece of ice or a water pitcher on a hot day? What effect has fog on bodily sensations? What in economics? The fogs of London. The book is especially valuable to advanced students.

PRACTICAL ENGINEER POCKET BOOK FOR 1910. London: The Technical Publishing Company, Ltd. 16mo.; 684 pp. Cloth, price 1s. net; leather, gilt, with diary or ruled section paper, 1s. 6d. net; postage 3d. extra. Price, 60 cents.

We have reviewed various editions of this book for a number of years and have found that the information conveyed was reliable and is presented in such form as to be very readily available. The excellent indexes are to be particularly commended.

ETHER OF SPACE. By Sir Oliver Lodge, F.R.S. 16mo.; 168 pp.

Sir Oliver Lodge needs no introduction to the readers of this paper. He is well known as an exponent of the ultra-modern physical theory with which the English school of physicists have been identified. In this book he explains in a simple way the necessary conception of an ether and formulates theories which, although some of them have not yet gained current acceptance, will undoubtedly do so in time.

THE WATER SUPPLY, SEWERAGE, AND PLUMBING OF MODERN CITY BUILDINGS. By William Paul Gerhard, C.E. New York: John Wiley & Sons, Ltd., 1910. 8vo.; 493 pp. Price, \$4.

The present work is an extremely valuable one. The engineering problems connected with the modern city building are very complicated. The chapters, while correlated to each other, are purposely so written that each one is complete in itself and each one may be read or studied without reference to the others. The book is splendidly illustrated by means of helpful diagrams and half tones. The titles of the chapters are as follows: Essential Features of the Hydraulic and Sanitary Engineering of Buildings. Sanitary Fixtures and Appliances. Advanced and Simplified Plumbing. Plumbing in its Relation to Disease and Municipal Control of Plumbing. Domestic Water Supply. The Water Supply of Large Modern City Buildings. The Maintenance of Pipe Systems for Sewage, Gas and Water. Rules on Plumbing, Water Supply and Sewerage, chiefly for Hospital Buildings and other Public Institutions. Mr. Gerhard has an international reputation as a sanitary engineer, and this book may be looked upon as authoritative.

AUTOMOBILE DRIVING SELF-TAUGHT. By Thomas H. Russell, M.E., LL.B. Chicago: The Charles C. Thompson Company, 1908. 12mo.; 222 pp. Price, \$1.

As comfort and safety in automobiling depend to a very large extent upon the skill of the driver, it should be the aim of every one who intends to drive a car to acquire a knowledge of the approved methods of driving. It is the object of this book to present such information in a convenient practical manner so as to make it comparatively easy for any motorist to acquire skill in the management and care of his machine. Study and practice combined will surely develop the expertness which is needed nowadays at the wheel, being demanded alike by the interests of the automobilist and of the non-motoring public. The careless or ignorant driver is a menace not only to the safety of the public, but also to that of his passengers. The daily experience of every motorist demonstrates the need of carefulness in driving, and there is no longer any excuse for ignorance. The methods of driving are described in this work and those which have been found best in actual experience on the road. From these pages the motorist can learn how to start, drive and manage his car under all conceivable circumstances. Those methods of caring for the car when not in use are also plainly shown as well as the manner in which a car should be laid up when necessary. The book appears to be a most practical one.

CONCRETE. By John C. Trautwine, Jr., and John C. Trautwine, Third, Civil Engineers. New York: John Wiley & Sons, 1909. 16mo. Price, \$2 net.

Trautwine's Civil Engineer's Pocketbook is too well known to need any praise at our hands. The nineteenth edition of 1909 completed the hundredth thousand copy, which is a phenomenal sale for a scientific and technical book.

In fact, we believe this is the largest sale on record for any such book. The most notable of the new features in this new edition is a series of articles on concrete, plain, reinforced, natural cement, sand and water. Practically all this matter, occupying about 200 pages, is entirely new as far as its publication is concerned. For the convenience of many engineers the section on concrete has been reprinted in the form of a handy volume which should be in the hands of all engineers. Typographically, the book is perfect for an engineer's pocketbook. The high professional standing of the engineers who have compiled the book is sufficient guarantee of its accuracy.

RADFORD'S COMBINED HOUSE AND BARN PLAN BOOK. Edited by William A. Radford. New York and Chicago: The Radford Architectural Company, 1908. 4to.; 287 pp. Price, \$1.

The volume before us is a most practical one, giving designs for barns, livery stables, grain barns, dairies, cow barns, feed lots, cattle sheds, poultry houses, implement sheds, vehicle sheds, hog houses, corn cribs, smoke-houses, granaries, tank houses, etc. The illustrations serve the purpose, although they are rather coarse. Prices for blue prints, which would enable any one to build these barns, are listed.

PRACTICAL ENGINEER ELECTRICAL POCKET BOOK AND DIARY FOR 1910. London: Technical Publishing Company, Ltd. 16mo.; 670 pp. Price, cloth, 1s. net; leather, gilt, 1s. 6d. net; postage 2d. extra.

This welcome annual visitor contains as usual valuable statistics, data, rules, tables, formulae, etc., and should be in the hands of all who are interested in electrical matters.

PROBLEMS IN WOOD TURNING. By Fred D. Crawshaw, B.S., M.E. Peoria, Ill.: The Manual Arts Press, 1909. 12mo. Price, 80 cents.

Wood turning is considerable of an art, requiring quite a little knack of handling the tools. The present work is an extremely practical one, and the illustrations are the best we have ever seen in a book on wood turning. The various projects are admirably worked out.

HANDBUCH FÜR HEER UND FLOTTE. Enzyklopädie der Kriegswissenschaften und verwandter Gebiete, herausgegeben von Georg von Alten, Generalleutnant z. D., unter Mitwirkung von mehr als 200 der bedeutendsten Fachautoritäten. Complete in 108 instalments. Price per instalment, 50 cents. Berlin, Leipzig, Vienna and Stuttgart: Deutsches Verlagshaus Bong & Co.

The first three instalments of the second volume of this remarkable military and naval encyclopedia lie before us. The instalments extend from "Bayreuth" to "Bourkundung." In the care which has been taken in the individual articles these new instalments are well up to the standard of those which we have previously reviewed. Of particular interest are the articles on benzine and benzol. The essay on Belgium may well be regarded as a model of good military writing, for it discusses clearly and masterfully the military geography, history and military system of a small but important European body politic.

POWER, HEATING AND VENTILATION. A Treatise for Designing and Constructing Engineers, Architects and Students. By Charles L. Hubbard, B.S., M.E. Part II., Power and Lighting. First edition. Brattleboro, Vt.: The Technical Press, 1909. 8vo.; pp. 397. Price, \$2.

The author has produced a thoroughly practical book which will be warmly welcomed by all engineers who have charge of power and lighting plants. There is always room for a good book on this subject and the author has certainly produced a most admirable treatise which is worthy of a large sale.

POWER, HEATING AND VENTILATION. A Treatise for Designing and Constructing Engineers, Architects and Students. By Charles L. Hubbard, B.S., M.E. Part III., Heating and Ventilation. First edition. Brattleboro, Vt.: The Technical Press, 1909. 8vo.; pp. 647. Price, \$3.

This is a very practical book dealing with all phases of warming and ventilation. Even such subjects as electrical heating are taken up. The illustrations are excellent, the expensive, but eminently successful wax process being used. The tables are also of great value. The subject is treated with rare discrimination, and the book cannot help but be of great use to all engineers.

ROMANTIC GERMANY. By Robert Haven Schaffner. New York: The Century Company, 1909. 397 pp. Price, \$3.50 net.

The beautiful book with a charming cover so suggestive of old Germany is a delightful one. The plates are charming and they are beautifully reproduced in various tints and colors. The cities which are discussed are Danzig, Berlin, Potsdam, Brunswick, Goslar, Hildesheim, Leipzig, Meissen, Dresden, Munich, Augsburg, and Rothenburg—certainly a galaxy of names to conjure with. It has been a long time since a good book has been produced on Germany which

deals with the land itself and not with its politics, history, sociology, commerce and science. Indeed the would-be visitor has to look back to "Views Afoot" written by young Bayard Taylor in the year 1846. To those who have left the beaten track Germany still remains the land of the Nibelungenlied and of Grimm's Fairy Tales, of gnomes and giants, storks and turreted ring-walls, of Gothic houses in rows, and the glamor of medieval courtyards. Many of these towns have preserved almost intact their old-world magic, and a touch of real romance is to be found as well as in almost every one of the larger cities noted above which we have been taught to consider hopelessly prosaic. It is hoped that the present volume will lure the traveler from his hard beaten track in France, Switzerland and Italy to the fresh regions of Romantic Germany.

SIMPLIFIED MECHANICAL PERSPECTIVE. By Frank Forrest Frederick. Peoria, Ill.: The Manual Arts Press, 1908-1909. 8vo.; 54 pp. Price, 75 cents.

This is a treatise for the use of high schools, technical and manual training high schools, evening and industrial schools, and all schools. The author has used the methods outlined for more than twenty years, and he states that he has never had a student learn much about the subject unless he carefully worked each problem and thoroughly understood it before attempting the next. The problems are admirable and a thorough mastering of this work will give any one an excellent idea of perspective.

THE DESIGN AND EQUIPMENT OF SMALL CHEMICAL LABORATORIES. By Richard K. Meade, B.S. Chicago: The Chemical Engineer Publishing Company, 1908. 12mo.; 136 pp. Price, 75 cents.

It very often happens that the young chemist, perhaps fresh from college, is called upon to design and equip a laboratory when his knowledge of how it is to be done is rather meager. The experienced chemist confronted with the task can usually bring to bear upon the subject sufficient practical knowledge gained from other laboratories in which he has worked to arrange and equip a laboratory which will meet fully his requirements and can do so in many instances better than any body else can do it for him. Many things which are done in the college laboratory are impossible in the private laboratory, where means are limited; for instance, ventilation of the hoods, gas supply may be non-existent, etc. To these young chemists the suggestions in this book on the design and equipment of small laboratories are made. But even experienced chemists may gain valuable points from it. There is an extremely small amount of literature on this subject, so that a thoroughly practical book like this should be warmly welcomed.

NUTRITION AND DIETETICS. By Winfield S. Hall, Ph.D., M.D. New York and London: D. Appleton & Co., 1910. 8vo.; 315 pp.

This is a valuable manual for students of medicine, for trained nurses, and for dietitians in hospitals and other institutions. During more than ten years the author has been presenting the subject of nutrition to classes of undergraduates in medicine and to the nurses of two of the large city hospitals. There has been a repeated request for a concise text book suitable not only for undergraduates and nurses, but also for the general practitioner, and covering the whole field of dietetics; but no such book seemed available. The one thing which is notable in this volume is the absence of receipts. These are hardly necessary as the doctor does not require them and the nurses already have them in other forms. The book is a very excellent one, including a classification of diets. The book is printed in a good size type and is well bound.

MODERN LETTERING, ARTISTIC AND PRACTICAL. By William Heyny. New York: William T. Comstock, 1909. 8vo.; 136 pp. Price, 75 cents.

This is a book of instruction primarily valuable in the hands of the beginner and of assistance to the experienced workman. "Modern Lettering" essays the subject from the practical standpoint from cover to cover. The author, a man of experience and of artistic temperament, boldly sets forth his ideas and propounds his methods in concise language. Directions even to minute details are given, all of which are valuable to the student. The plates are all on a large scale and the letters are clear and sharp. The French Roman is a new letter in this country and will be appreciated for its refinement, beauty and legibility. Much valuable information, the fruit of the author's long experience, is given on the choice of alphabets, the arrangement of words, and the spacing of letters, with good criticism of faults of modern lettering.

IN A YORKSHIRE GARDEN. By Reginald Farrer. London: Edward Arnold, 1909. 8vo.; 316 pp.

The author is very much in love with his subject. He has already written "My Rock Garden," "Alpine and Bog Plants," as well as other works. The present volume deals with "The Broadleaf Dawn."

NATURAL SALVATION (SALVATION BY SCIENCE). By Charles Ashbury Stephens, M.D. Norway Lake, Me.: The Laboratory, 1910. 8vo.; 157 pp.



"Star" Lathes
Automatic Cross Feed
FOR FINE, ACCURATE WORK
Send for Catalogue to:
SENECA FALLS MFG. CO.
695 Water Street,
Seneca Falls, N. Y., U. S. A.

Engine and Foot Lathes
MACHINE SHOP OUTFITS, TOOLS AND SUPPLIES. BEST MATERIALS. BEST WORKMANSHIP. CATALOGUE FREE.
SEBASTIAN LATHE CO., 120 Culvert St., Cincinnati, O.

Foot and Power and Turret Lathes, Planers, Shapers, and Drill Presses.
SHEPARD LATHE CO., 125 W. 30 St., Cincinnati, O.

WORK SHOPS
of Wood and Metal Workers, with-out steam power, equipped with **BARNES' FOOT POWER MACHINERY** allow lower bids on jobs, and give greater profit on the work. Machines sent on trial if desired. Catalogue Free.
W. F. & JOHN BARNES CO.
1099 RUBY ST. ROCKFORD, ILL.

Noteworthy Articles

ON TIMELY TOPICS

Each number of the Scientific American Supplement costs 10 cents by mail.

SEWAGE AND ITS DISPOSAL. A review of modern methods. By H. LEMMOIN-CANNON. SCIENTIFIC AMERICAN SUPPLEMENT 1551.

ELECTRIC LIGHTING FOR AMATEURS. How a small and simple experimental installation can be set up at home. SCIENTIFIC AMERICAN SUPPLEMENT 1551.

CHEMICAL AFFINITY. Simply explained by SIR OLIVER LODGE. SCIENTIFIC AMERICAN SUPPLEMENT 1547.

CASE-HARDENING. By DAVID FLATHER. SCIENTIFIC AMERICAN SUPPLEMENT 1547.

ELECTRIC IGNITION SYSTEMS. A comprehensive article by E. W. ROBERTS. SCIENTIFIC AMERICAN SUPPLEMENT 1546.

CONCRETE. A general article on its merits and defects. SCIENTIFIC AMERICAN SUPPLEMENT 1545.

REINFORCED CONCRETE. Some of its Principles and Applications with practical illustrations. SCIENTIFIC AMERICAN SUPPLEMENTS 1547, 1548, 1551.

ELECTRONS AND THE ELECTRONIC THEORY are discussed by SIR OLIVER LODGE in SCIENTIFIC AMERICAN SUPPLEMENTS 1428, 1429, 1430, 1431, 1432, 1433, 1434.

THE PANAMA CANAL is described from the engineering standpoint in SCIENTIFIC AMERICAN SUPPLEMENT 1559.

WIRELESS TELEGRAPHY. Its Progress and Present Condition are well discussed in SCIENTIFIC AMERICAN SUPPLEMENTS 1425, 1426, 1427, 1428, 1429, 1430, 1431, 1432, 1433, 1434, 1435, 1436, 1437, 1438, 1439, 1440, 1441, 1442, 1443, 1444, 1445, 1446, 1447, 1448, 1449, 1450, 1451, 1452, 1453, 1454, 1455, 1456, 1457, 1458, 1459, 1460, 1461, 1462, 1463, 1464, 1465, 1466, 1467, 1468, 1469, 1470, 1471, 1472, 1473, 1474, 1475, 1476, 1477, 1478, 1479, 1480, 1481, 1482, 1483, 1484, 1485, 1486, 1487, 1488, 1489, 1490, 1491, 1492, 1493, 1494, 1495, 1496, 1497, 1498, 1499, 1500, 1501, 1502, 1503, 1504, 1505, 1506, 1507, 1508, 1509, 1510, 1511, 1512, 1513, 1514, 1515, 1516, 1517, 1518, 1519, 1520, 1521, 1522, 1523, 1524, 1525, 1526, 1527, 1528, 1529, 1530, 1531, 1532, 1533, 1534, 1535, 1536, 1537, 1538, 1539, 1540, 1541, 1542, 1543, 1544, 1545, 1546, 1547, 1548, 1549, 1550, 1551, 1552, 1553, 1554, 1555, 1556, 1557, 1558, 1559, 1560, 1561, 1562, 1563, 1564, 1565, 1566, 1567, 1568, 1569, 1570, 1571, 1572, 1573, 1574, 1575, 1576, 1577, 1578, 1579, 1580, 1581, 1582, 1583, 1584, 1585, 1586, 1587, 1588, 1589, 1590, 1591, 1592, 1593, 1594, 1595, 1596, 1597, 1598, 1599, 1600, 1601, 1602, 1603, 1604, 1605, 1606, 1607, 1608, 1609, 1610, 1611, 1612, 1613, 1614, 1615, 1616, 1617, 1618, 1619, 1620, 1621, 1622, 1623, 1624, 1625, 1626, 1627, 1628, 1629, 1630, 1631, 1632, 1633, 1634, 1635, 1636, 1637, 1638, 1639, 1640, 1641, 1642, 1643, 1644, 1645, 1646, 1647, 1648, 1649, 1650, 1651, 1652, 1653, 1654, 1655, 1656, 1657, 1658, 1659, 1660, 1661, 1662, 1663, 1664, 1665, 1666, 1667, 1668, 1669, 1670, 1671, 1672, 1673, 1674, 1675, 1676, 1677, 1678, 1679, 1680, 1681, 1682, 1683, 1684, 1685, 1686, 1687, 1688, 1689, 1690, 1691, 1692, 1693, 1694, 1695, 1696, 1697, 1698, 1699, 1700, 1701, 1702, 1703, 1704, 1705, 1706, 1707, 1708, 1709, 1710, 1711, 1712, 1713, 1714, 1715, 1716, 1717, 1718, 1719, 1720, 1721, 1722, 1723, 1724, 1725, 1726, 1727, 1728, 1729, 1730, 1731, 1732, 1733, 1734, 1735, 1736, 1737, 1738, 1739, 1740, 1741, 1742, 1743, 1744, 1745, 1746, 1747, 1748, 1749, 1750, 1751, 1752, 1753, 1754, 1755, 1756, 1757, 1758, 1759, 1760, 1761, 1762, 1763, 1764, 1765, 1766, 1767, 1768, 1769, 1770, 1771, 1772, 1773, 1774, 1775, 1776, 1777, 1778, 1779, 1780, 1781, 1782, 1783, 1784, 1785, 1786, 1787, 1788, 1789, 1790, 1791, 1792, 1793, 1794, 1795, 1796, 1797, 1798, 1799, 1800, 1801, 1802, 1803, 1804, 1805, 1806, 1807, 1808, 1809, 1810, 1811, 1812, 1813, 1814, 1815, 1816, 1817, 1818, 1819, 1820, 1821, 1822, 1823, 1824, 1825, 1826, 1827, 1828, 1829, 1830, 1831, 1832, 1833, 1834, 1835, 1836, 1837, 1838, 1839, 1840, 1841, 1842, 1843, 1844, 1845, 1846, 1847, 1848, 1849, 1850, 1851, 1852, 1853, 1854, 1855, 1856, 1857, 1858, 1859, 1860, 1861, 1862, 1863, 1864, 1865, 1866, 1867, 1868, 1869, 1870, 1871, 1872, 1873, 1874, 1875, 1876, 1877, 1878, 1879, 1880, 1881, 1882, 1883, 1884, 1885, 1886, 1887, 1888, 1889, 1890, 1891, 1892, 1893, 1894, 1895, 1896, 1897, 1898, 1899, 1900, 1901, 1902, 1903, 1904, 1905, 1906, 1907, 1908, 1909, 1910, 1911, 1912, 1913, 1914, 1915, 1916, 1917, 1918, 1919, 1920, 1921, 1922, 1923, 1924, 1925, 1926, 1927, 1928, 1929, 1930, 1931, 1932, 1933, 1934, 1935, 1936, 1937, 1938, 1939, 1940, 1941, 1942, 1943, 1944, 1945, 1946, 1947, 1948, 1949, 1950, 1951, 1952, 1953, 1954, 1955, 1956, 1957, 1958, 1959, 1960, 1961, 1962, 1963, 1964, 1965, 1966, 1967, 1968, 1969, 1970, 1971, 1972, 1973, 1974, 1975, 1976, 1977, 1978, 1979, 1980, 1981, 1982, 1983, 1984, 1985, 1986, 1987, 1988, 1989, 1990, 1991, 1992, 1993, 1994, 1995, 1996, 1997, 1998, 1999, 2000, 2001, 2002, 2003, 2004, 2005, 2006, 2007, 2008, 2009, 2010, 2011, 2012, 2013, 2014, 2015, 2016, 2017, 2018, 2019, 2020, 2021, 2022, 2023, 2024, 2025, 2026, 2027, 2028, 2029, 2030, 2031, 2032, 2033, 2034, 2035, 2036, 2037, 2038, 2039, 2040, 2041, 2042, 2043, 2044, 2045, 2046, 2047, 2048, 2049, 2050, 2051, 2052, 2053, 2054, 2055, 2056, 2057, 2058, 2059, 2060, 2061, 2062, 2063, 2064, 2065, 2066, 2067, 2068, 2069, 2070, 2071, 2072, 2073, 2074, 2075, 2076, 2077, 2078, 2079, 2080, 2081, 2082, 2083, 2084, 2085, 2086, 2087, 2088, 2089, 2090, 2091, 2092, 2093, 2094, 2095, 2096, 2097, 2098, 2099, 2100, 2101, 2102, 2103, 2104, 2105, 2106, 2107, 2108, 2109, 2110, 2111, 2112, 2113, 2114, 2115, 2116, 2117, 2118, 2119, 2120, 2121, 2122, 2123, 2124, 2125, 2126, 2127, 2128, 2129, 2130, 2131, 2132, 2133, 2134, 2135, 2136, 2137, 2138, 2139, 2140, 2141, 2142, 2143, 2144, 2145, 2146, 2147, 2148, 2149, 2150, 2151, 2152, 2153, 2154, 2155, 2156, 2157, 2158, 2159, 2160, 2161, 2162, 2163, 2164, 2165, 2166, 2167, 2168, 2169, 2170, 2171, 2172, 2173, 2174, 2175, 2176, 2177, 2178, 2179, 2180, 2181, 2182, 2183, 2184, 2185, 2186, 2187, 2188, 2189, 2190, 2191, 2192, 2193, 2194, 2195, 2196, 2197, 2198, 2199, 2200, 2201, 2202, 2203, 2204, 2205, 2206, 2207, 2208, 2209, 2210, 2211, 2212, 2213, 2214, 2215, 2216, 2217, 2218, 2219, 2220, 2221, 2222, 2223, 2224, 2225, 2226, 2227, 2228, 2229, 2230, 2231, 2232, 2233, 2234, 2235, 2236, 2237, 2238, 2239, 2240, 2241, 2242, 2243, 2244, 2245, 2246, 2247, 2248, 2249, 2250, 2251, 2252, 2253, 2254, 2255, 2256, 2257, 2258, 2259, 2260, 2261, 2262, 2263, 2264, 2265, 2266, 2267, 2268, 2269, 2270, 2271, 2272, 2273, 2274, 2275, 2276, 2277, 2278, 2279, 2280, 2281, 2282, 2283, 2284, 2285, 2286, 2287, 2288, 2289, 2290, 2291, 2292, 2293, 2294, 2295, 2296, 2297, 2298, 2299, 2300, 2301, 2302, 2303, 2304, 2305, 2306, 2307, 2308, 2309, 2310, 2311, 2312, 2313, 2314, 2315, 2316, 2317, 2318, 2319, 2320, 2321, 2322, 2323, 2324, 2325, 2326, 2327, 2328, 2329, 2330, 2331, 2332, 2333, 2334, 2335, 2336, 2337, 2338, 2339, 2340, 2341, 2342, 2343, 2344, 2345, 2346, 2347, 2348, 2349, 2350, 2351, 2352, 2353, 2354, 2355, 2356, 2357, 2358, 2359, 2360, 2361, 2362, 2363, 2364, 2365, 2366, 2367, 2368, 2369, 2370, 2371, 2372, 2373, 2374, 2375, 2376, 2377, 2378, 2379, 2380, 2381, 2382, 2383, 2384, 2385, 2386, 2387, 2388, 2389, 2390, 2391, 2392, 2393, 2394, 2395, 2396, 2397, 2398, 2399, 2400, 2401, 2402, 2403, 2404, 2405, 2406, 2407, 2408, 2409, 2410, 2411, 2412, 2413, 2414, 2415, 2416, 2417, 2418, 2419, 2420, 2421, 2422, 2423, 2424, 2425, 2426, 2427, 2428, 2429, 2430, 2431, 2432, 2433, 2434, 2435, 2436, 2437, 2438, 2439, 2440, 2441, 2442, 2443, 2444, 2445, 2446, 2447, 2448, 2449, 2450, 2451, 2452, 2453, 2454, 2455, 2456, 2457, 2458, 2459, 2460, 2461, 2462, 2463, 2464, 2465, 2466, 2467, 2468, 2469, 2470, 2471, 2472, 2473, 2474, 2475, 2476, 2477, 2478, 2479, 2480, 2481, 2482, 2483, 2484, 2485, 2486, 2487, 2488, 2489, 2490, 2491, 2492, 2493, 2494, 2495, 2496, 2497, 2498, 2499, 2500, 2501, 2502, 2503, 2504, 2505, 2506, 2507, 2508, 2509, 2510, 2511, 2512, 2513, 2514, 2515, 2516, 2517, 2518, 2519, 2520, 2521, 2522, 2523, 2524, 2525, 2526, 2527, 2528, 2529, 2530, 2531, 2532, 2533, 2534, 2535, 2536, 2537, 2538, 2539, 2540, 2541, 2542, 2543, 2544, 2545, 2546, 2547, 2548, 2549, 2550, 2551, 2552, 2553, 2554, 2555, 2556, 2557, 2558, 2559, 2560, 2561, 2562, 2563, 2564, 2565, 2566, 2567, 2568, 2569, 2570, 2571, 2572, 2573, 2574, 2575, 2576, 2577, 2578, 2579, 2580, 2581, 2582, 2583, 2584, 2585, 2586, 2587, 2588, 2589, 2590, 2591, 2592, 2593, 2594, 2595, 2596, 2597, 2598, 2599, 2600, 2601, 2602, 2603, 2604, 2605, 2606, 2607, 2608, 2609, 2610, 2611, 2612, 2613, 2614, 2615, 2616, 2617, 2618, 2619, 2620, 2621, 2622, 2623, 2624, 2625, 2626, 2627, 2628, 2629, 2630, 2631, 2632, 2633, 2634, 2635, 2636, 2637, 2638, 2639, 2640, 2641, 2642, 2643, 2644, 2645, 2646, 2647, 2648, 2649, 2650, 2651, 2652, 2653, 2654, 2655, 2656, 2657, 2658, 2659, 2660, 2661, 2662, 2663, 2664, 2665, 2666, 2667, 2668, 2669, 2670, 2671, 2672, 2673, 2674, 2675, 2676, 2677, 2678, 2679, 2680, 2681, 2682, 2683, 2684, 2685, 2686, 2687, 2688, 2689, 2690, 2691, 2692, 2693, 2694, 2695, 2696, 2697, 2698, 2699, 2700, 2701, 2702, 2703, 2704, 2705, 2706, 2707, 2708, 2709, 2710, 2711, 2712, 2713, 2714, 2715, 2716, 2717, 2718, 2719, 2720, 2721, 2722, 2723, 2724, 2725, 2726, 2727, 2728, 2729, 2730, 2731, 2732, 2733, 2734, 2735, 2736, 2737, 2738, 2739, 2740, 2741, 2742, 2743, 2744, 2745, 2746, 2747, 2748, 2749, 2750, 2751, 2752, 2753, 2754, 2755, 2756, 2757, 2758, 2759, 2760, 2761, 2762, 2763, 2764, 2765, 2766, 2767, 2768, 2769, 2770, 2771, 2772, 2773, 2774, 2775, 2776, 2777, 2778, 2779, 2780, 2781, 2782, 2783, 2784, 2785, 2786, 2787, 2788, 2789, 2790, 2791, 2792, 2793, 2794, 2795, 2796, 2797, 2798, 2799, 2800, 2801, 2802, 2803, 2804, 2805, 2806, 2807, 2808, 2809, 2810, 2811, 2812, 2813, 2814, 2815, 2816, 2817, 2818, 2819, 2820, 2821, 2822, 2823, 2824, 2825, 2826, 2827, 2828, 2829, 2830, 2831, 2832, 2833, 2834, 2835, 2836, 2837, 2838, 2839, 2840, 2841, 2842, 2843, 2844, 2845, 2846, 2847, 2848, 2849, 2850, 2851, 2852, 2853, 2854, 2855, 2856, 2857, 2858, 2859, 2860, 2861, 2862, 2863, 2864, 2865, 2866, 2867, 2868, 2869, 2870, 2871, 2872, 2873, 2874, 2875, 2876, 2877, 2878, 2879, 2880, 2881, 2882, 2883, 2884, 2885, 2886, 2887, 2888, 2889, 2890, 2891, 2892, 2893, 2894, 2895, 2896, 2897, 2898, 2899, 2900, 2901, 2902, 2903, 2904, 2905, 2906, 2907, 2908, 2909, 2910, 2911, 2912, 2913, 2914, 2915, 2916, 2917, 2918, 2919, 2920, 2921, 2922, 2923, 2924, 2925, 2926, 2927, 2928, 2929, 2930, 2931, 2932, 2933, 2934, 2935, 2936, 2937, 2938, 2939, 2940, 2941, 2942, 2943, 2944, 2945, 2946, 2947, 2948, 2949, 2950, 2951, 2952, 2953, 2954, 2955, 2956, 2957, 2958, 2959, 2960, 2961, 2962, 2963, 2964, 2965, 2966, 2967, 2968, 2969, 2970, 2971, 2972, 2973, 2974, 2975, 2976, 2977, 2978, 2979, 2

Catalytic and making same, T. J. Wrampelmeier	948,947
Cement seat, C. F. Price	948,770
Chair attachment, F. W. Bork	948,306
Cheese cutter, I. E. Lee	948,422
Cheese stirrer, O. H. Moldenhauer	948,933
Chopping machine, J. J. Kilman	948,510
Chuck, J. B. Hall	948,085
Chuck, T. J. Fogler	948,850
Chuck, lathe, R. H. Huribut	948,440
Churn, A. A. Hugclim	948,546
Churn, E. E. Conlhard	948,943
Cigar butt former, J. Carter	948,646
Circuit breaker for electrically heated devices, W. G. Nagel	948,704
Cloap, G. A. Larson	948,308
Cloap, A. G. Boyland	948,917
Clock, A. M. Yenkel	948,363
Clock, A. M. Yenkel	948,363
Clothes drying rack, J. R. Ruse	948,653
Clothes line reel and pin box, E. T. Eiser	948,625
Clothes rack, R. B. Meek	948,593
Clutch mechanism, C. L. Grohmann	948,663
Coating metals by cementation, A. Sang	948,344
Cock, automatic drain, J. G. Radick	948,748
Cock, ball, G. E. Van Deusen	948,810
Coin controlled lock, H. E. Lane	948,936
Coke oven door, J. F. Peters	948,407
Collar, sheep, C. P. Ballard	948,924
Collector, A. Goedecker	948,665
Combining fibrous materials, machine for, Schmidt & Frenaux	948,723
Concrete construction, plant for, T. Emtman	948,746
Concrete distributing device, A. L. Smith	948,854
Concrete fence, E. & C. Wagner	948,824
Concrete floor construction, reinforced, L. Patterson	948,432
Condenser, E. F. Hudson	948,835
Condenser, ammonia, B. Walter	948,858
Connecting pipe, flexible, G. W. Heug, Jr.	948,442
Controller, F. E. Case	948,444
Controller, A. T. Crocker	948,485
Conveying apparatus, Sovereign & Lenders	948,661
Conveyor, D. J. See	948,717
Cooking outfit, camp, A. J. Avery	948,491
Cooking utensil, Andrews & Schaub	948,491
Cooler, See Milk cooler	
Cooling apparatus for provisions, L. D. Seerest	948,581
Cop, brooding, A. W. Altorf	948,716
Cop spindle, Laurent & Bonahue	948,454
Copper and other metals, depositing, A. Sang	948,662
Cord or rope holder, C. C. Sprinkle	948,706
Corn from the stalks, machine for cutting ears of, P. M. Wideman	948,601
Costumer, J. C. Wilson	948,537
Cotton chopper, T. K. Boggs	948,495
Cotton gin, Bosch & von Oren	948,810
Cotton picking machine, S. S. Thompson	948,619
Couch, reclining, C. A. Lindner	948,735
Counter device, F. E. Northrop	948,708
Crane, floating, A. Bode	948,594
Cultivating shovel, surface, L. B. Peaton	948,522
Cultivator, P. Johnson	948,700
Culvert, N. S. Davis	948,500
Curtain pole bracket, B. Luffich	948,787
Curtain pole bracket, adjustable, C. Kirk	948,687
Cutter head, A. B. Landis	948,893
Cutter head for bolt cutting machines, A. B. Landis	948,886
Cycle frame, motor, C. L. W. Huser	948,507
Cycles, transmission mechanism for motor, P. S. Russell	948,623
Cylinder lubricator, C. C. League	948,455
Cylinder lubricator, F. B. Hubbard	948,582
Dental casting appliance, E. R. Steady	948,711
Dental plugging instrument, G. B. Snow	948,484
Depositor and collection receptacle, H. P. Turner	948,550
Derick, A. Forest	948,851
Dish, M. W. Scott	948,476
Dish stand, N. F. Dammeyer	948,521
Display cabinet, V. D. Payne	948,705
Door, T. M. Cole	948,690
Door check, J. A. Stuart	948,796
Door lock and switch, E. E. Saphore	948,737
Door opener, McKee & Gates	948,730
Drug, road, Carroll & Skiles	948,378
Drawer, furniture, T. C. Prouty	948,771
Drawers, knee, W. D. Richey	948,722
Dredging apparatus, W. R. Comfort	948,751
Drier, See Sand drier	
Drier, M. Whitelaw	948,477
Drying apparatus, D. Diver	948,763
Drying articles of jewelry, etc., means, A. W. Hutchins	948,472
Drilling machine, J. P. Barnes	948,582
Drilling machine, Barnes & Vincent	948,584
Drilling machine, W. F. Barnes	948,728
Duplicating machine stand, A. Hendricks	948,901
Eaves trough hanger, S. T. Nakashjian	948,750
Egg beater, R. Washburn	948,563
Electric cable connection, W. J. Littlehales	948,865
Electric conductor, G. A. Lutz, G. A. Lutz	948,343
Electric furnace and operating the same, A. L. J. Queneau	948,736
Electric generation, distribution, and control, system of, L. Lyndell	948,817
Electric generator, dynamo, G. Lewis	948,564
Electric snap switch, four-way, W. S. Mayer	948,441
Electric switch, D. G. Butts	948,810
Electrical distribution, appliance for systems of, G. A. Lutz	948,567
Electrical receptacle, F. J. Russell	948,526
Electrode, are light, L. Ladou	948,558
Electrode, storage battery, T. A. Edison	948,370
Electrode support, battery, Schoenmehl & Straw	948,624
Electromagnetic switch, E. V. Collins	948,822
Eraser, McSweney & Seelye	948,376
Evaporating apparatus, multiple effect, S. M. Little	948,822
Evaporator, Hanahan & Wenden	948,487
Everest coupling, G. F. Thompson	948,871
Excavating machine, C. S. Brown	948,958
Expansion bolt, C. B. Skidmore	948,700
Explosive, A. Mikolajczak	948,925
Explosive engine, H. G. Holmes	948,713
Eye-glass holder, P. H. Todd	948,356
Fan, fly, T. L. Thompson	948,530
Fastening, S. A. Smith	948,607
Fence post, M. Gage	948,426
Fence wire clamp, E. J. McCain	948,307
Fences, clamp for stretching wire, S. W. Berry	948,820
Fifth wheel for automobiles, Scheer & Hart	948,806
File for school desks, E. W. Lee	948,857
Filling compressor, vertical, O. Hankell	948,462
Filling machine, F. C. H. Strassberger	948,463
Filler or stuffing material, manufacture of, Caldwell & Plummer	948,845
Fireproof door and the like, J. B. Husey	948,450
Flask, See Molding flask	
Floor surfacing device, P. T. Lemaster	948,927
Flour bin, J. S. McQuinn	948,703
Fly trap, G. E. H. R. Lamb	948,843
Folding machine, H. K. King	948,547
Fondant mixing machine, S. E. Ball	948,940
Frame adjuster, C. Ehr	948,849
Fruit gatherer, T. Branch	948,405
Fruit gatherer, M. C. Nickell	948,579
Fuel and making the same, artificial, C. F. Bonhack	948,812
Furniture, combination article of, G. W. & G. E. Myers	948,377
Game apparatus, D. H. Talbert et al.	948,480
Game apparatus, T. C. Lane	948,776
Garment fastening cover, T. Wickersham	948,837
Gas, apparatus for making petrolized or air, W. Shearer	948,745
Gas, apparatus for purifying blast furnace, H. Savage	948,664
Gas burner, alcohol, W. E. Cochran	948,982
Gas burner safety attachment, C. Liaci	948,354
Gas engine, D. H. Bennett	948,950
Gas engine, two-cycle, J. M. Johnson et al.	948,860
Gas furnace, regenerative, G. H. Benjamin	948,538
Gas log, O. E. Hansen	948,561
Gas regulator, W. B. Park	948,540
Gas supply controlling device, H. O. Ewing	948,724
Gases, absorbing dilute nitrous, B. F. Halvorsen	948,726
Gassing apparatus, J. O. McKean	948,954
Gassing machine, J. O. McKean	948,955



HURRY Secure the agency for your territory and the right to sell all makes of automobiles. This advertisement will appear only once and you must act quickly if you wish to secure this unusual opportunity. A pleasant and healthful occupation for spare time. You will find that this is more profitable and requires less capital than the usual agency contract. Automobiles are here to stay. This opportunity will only be presented to you once, so write today for particulars. **HURRY**
Nyberg Automobile Works, Inc., 2434 Michigan Ave., Dept. G, Chicago, Ill.

DO YOU WANT GOOD INFORMATION CHEAP?

Write to us and we will refer you to a SCIENTIFIC AMERICAN SUPPLEMENT that will give you the very data you need; when writing please state that you wish SUPPLEMENT articles. SCIENTIFIC AMERICAN SUPPLEMENT articles are written by men who stand foremost in modern science and industry.

Each SCIENTIFIC AMERICAN SUPPLEMENT costs only 10 cents. But the information it contains may save you hundreds of dollars.

Send for a 1910 catalogue of SUPPLEMENT articles. It costs nothing.

Act on this suggestion!

MUNN & CO., Inc., Publishers
361 Broadway, New York

A Talk with Thoughtful Business Men of America

Are the Politicians Meddling in Your Business?

Are you puzzled over the rising cost of living, the Sugar Trust scandals, railway regulations, the relation between the white slave traffic and our municipal governments, the Ballinger muddle, the Standard Oil decision?

Surely Business Men are not All Bad—You Think?

With the Customs Service debauched by the big importers, with the tariff forced up by the big manufacturers, with our national resources looted by the financial pirates, do you sometimes wonder what this country is coming to?

In a Series of Epoch-making Articles in Success Magazine Russell is Setting Forth the First Intelligent Analysis of the Problem.

The Power Behind the Republic

AND NOW—

If you are a Stupid, Self-satisfied citizen—

stop right here. If you are an intelligent—but puzzled—citizen you have simply got to read these articles. You won't be able to evade them. The ideas they contain will seek you out and hammer themselves into your brain. Simple as truth, clear as light, Russell has here formulated the only proposition ever offered for reforming our business and political structure which business men can take seriously—as business men.

These Articles—Every One a Foundation Stone in the New America—are Appearing Monthly in

Success Magazine

10c. A COPY

\$1.00 A YEAR

FOR EXAMPLE—READ THIS "What Business Wants It Will Have"

"—because, in the present condition of society, the very first necessity overtopping all else is that Business shall go on; a great, primal, blind, relentless, universal instinct keeps driving it on. It will trample over whatever is in its way as a great herd of buffalo on the plains used to trample over a wayfarer—without the least ill-will, unconsciously, unintentionally, and merely because it must go on. Nothing must be allowed to stop it; under present conditions

"Business is the Nation's Heart!"

(Continued from page 170.)

lens a photographic plate 1 2/3 x 4 inches only is used, and in the center of this are some faint streaks of light about two inches long and possibly one-sixteenth of an inch in width. This tells the whole story of the star's motion. Naturally this photograph is placed under the microscope for examination and there it appears magnified and is measured. The physical constitution of the star, the metals that compose it, is known from the lines of the stellar spectrum, hydrogen for instance showing its badge by a series of prominent lines. The motion of the star is shown by the placing of these lines, whether they are shifted from their normal position, as given by the comparison spectrum, to the violet or toward the red end of the spectrum. If there is hydrogen in the star, then the lines of the hydrogen comparison spectrum give the position of rest or zero velocity with respect to the earth, and the amount of the shift measured under the microscope gives the motion of the star. If there are other lines in the spectrum of the star (as is usually the case) we can readily in an analogous fashion measure the motion. The photographs in the illustration were taken at the Yerkes Observatory with the great 40-inch telescope. Two separate spectra are there shown, taken but three days apart on January 5th and 8th, 1906. The star spectrum appears in each between the comparison spectrum of titanium, and it is widened to make the lines more prominent, and the whole greatly enlarged. The violet end is toward the left, red end to the right. Portions of the comparison spectra on both are cut away to bring the two closer. The numbers on the top give the wave-lengths. Notice that all the lines in the lower spectrum are shifted much more to the right with respect to the comparison lines than in the upper spectrum. This is specially noticeable at line 4501, and better still at 4481. A measure of the amount of these shifts gives the radial velocity of the star with respect to the earth. The variable velocity in the line of sight of this star shows it is not a single star but a system. Measures made by the writer on the star β Trianguli show the following results where the radial velocities are given in miles per second relative to the sun. The plus sign means that the star is increasing its distance from the sun, and a minus sign that it is moving toward the sun:

Date.	Velocity in line of sight.
1908—Sept. 7.....	+ 33 miles per second
Sept. 8.....	+ 31 miles per second
Sept. 18.....	— 5 miles per second
Oct. 5.....	+ 1 mile per second
Oct. 12.....	+ 20 miles per second
Nov. 8.....	+ 18 miles per second

The measures must be carried out with utmost care. If the spectrum of the star is good with many well defined lines, the radial velocity (i. e., toward or away from us) may be determined to an accuracy of one-tenth of a mile per second. Think of this when light travels at the rate of 186,000 miles per second, when six hundred millions of millions of waves enter the spectroscope every second, and when in addition the star is so far distant that its light even when traveling at such enormous velocities might take hundreds or thousands of years to reach us! To contemplate it makes our minds whirl at the enormity of space, and causes us to bow down in reverence to the wonderful human intellect that can solve such problems!

Investigations of certain stars show us that at one time it may be moving toward our sun, once in a few days or weeks the direction of motion may be reversed and it is traveling away from the sun. The star of itself is unable to change its motion, and another body must be present, so that variable velocities in the line of sight as in β Trianguli denote that two or more suns are present in a system and they are in revolution about each other. At our distance from the stars the

(Concluded on page 172.)

Practical and Instructive Scientific Books

Gale, J. W. Matthews.....	948,788
Gale, H. W. Street.....	948,869
Gale spring, D. L. Clement.....	948,498
Gear cutting machine, B. Sunderland.....	948,830
Gearing, J. S. Barnes.....	948,830
Gearing, B. W. Hanson.....	948,807
Gearing, H. H. Taylor.....	948,801
Gearing, change speed, A. B. Laidie.....	948,802
Gearing, power transmission, W. L. Fodren.....	948,804
Governor, J. P. Sikomow.....	948,791
Grading and ditching machine, W. Hay.....	948,810
Grain bucket, J. P. Zoller.....	948,805
Grain, steeping, A. W. H. Lenders.....	948,814
Graphophone, B. Morton.....	948,859
Greenhouse bench, W. Wait.....	948,820
Grinding mill, T. Cascard, Jr.....	948,406
Hammer, W. J. Ruffian.....	948,828
Handoff, G. Caveney.....	948,810
Hanger, S. Appareil hanger.....	948,799
Harrow, J. H. Foden.....	948,846
Harvester, cotton, W. T. Gomer.....	948,541
Heat insulating, C. J. Coleman.....	948,488
Heating apparatus, L. H. Freymuth.....	948,413
Heating boiler, house, L. S. Bush.....	948,850
Hinge, W. L. Young.....	948,818
Hinge, crank, L. S. Bush.....	948,818
Hinge spring, Brucker & Love.....	948,410
Hitching device, H. D. Gordon.....	948,826
Hog trough, J. H. Barnhart.....	948,342
Home plate, W. E. Piel.....	948,801
Hoof knife, A. P. Kelley.....	948,801
Horsehoe calks, machine for facing, A. Erickson.....	948,603
Horsehoe machine, K. Smith.....	948,470
Hose coupling, Wilson & Oldenburg.....	948,437
Hose coupling, E. H. Gould.....	948,967
Hose jacket, W. C. Shepard.....	948,288
Hub, automobile spring, M. C. Patten.....	948,524
Ice cream cone holder, J. F. Reid.....	948,906
Incubator, W. H. Somersall.....	948,504
Incubator alarm, F. Flora.....	948,483
Inductor generator for ignition, H. J. & T. E. Postleak.....	948,786
Insect catcher, A. H. Lee.....	948,805
Insectarium, G. A. Kierling.....	948,739
Insecticide, G. Obit.....	948,707
Insulating means for flush switches, C. D. Platt.....	948,222
Insulating knob, S. R. Gray.....	948,800
Insulator, section, R. M. McFadyen.....	948,308
Internal-combustion engine, H. A. Hart.....	948,336
Internal-combustion engine, E. Moore.....	948,732
Iron, double corrugated sheet, R. Knutson.....	948,595
Iron holder, smoothing, E. G. Patten.....	948,479
Ironing board, L. B. Jennings.....	948,774
Jewel cluster setting, B. I. Strutt.....	948,216
Keyboard guide, Hausdorfer & Murray.....	948,731
Kinetograph film, apparatus for the continuous drying of perforated, E. A. Ivitis.....	948,727
Knife handles, composition of user, H. C. Hart.....	948,469
Lace fastener, shoe, C. M. Partridge.....	948,570
Lamp, see M. Fortuny.....	948,754
Lamp socket, electric, W. S. McLeese.....	948,754
Lamp socket, incandescent, F. C. Aschenbrenner.....	948,754
Lamp socket, incandescent, E. R. Miller.....	948,754
Lath, Z. B. Coes.....	948,407
Lathe, automatic, J. P. Brophy.....	948,680
Lawn cleaner rake, rotary, C. H. Mosbet.....	948,382
Leather, artificial, J. C. Smith.....	948,815
Letter box, L. Ehrlich.....	948,570
Level, spirit, E. Anderson.....	948,517
Lifting jack, J. E. Morse.....	948,873
Lifting jack, G. B. Booth.....	948,615
Lighting arrester, B. E. Clarkson.....	948,572
Link mesh, machine for making, A. C. Pratt.....	948,588
Liquid dispensing apparatus, L. W. Hughes.....	948,762
Liquid into vessels through closed chambers of filling machines, means for introducing, J. M. Hicks.....	948,725
Liquids or semiliquids, apparatus for purifying, N. H. Freeman.....	948,554
Litter carrier, Schmechel & Beiler.....	948,628
Lock, see Ball bearing lock.....	948,804
Locket, metal, E. W. Jeffers.....	948,945
Locking device, F. D. Winterling.....	948,412
Loom for weaving, shuttleless, E. Smith.....	948,568
Loom, haircloth, G. S. Fox.....	948,599
Loom, shuttle, haircloth, G. S. Fox.....	948,778
Loom, self replenishing, H. Wyman.....	948,543
Magnetic separation, apparatus for electrostatic, H. M. Sutton et al.....	948,555
Mail bag catcher and deliverer, J. Wood.....	948,715
Mail bag lock, S. Fehnel.....	948,506
Mail bag or the like lock, C. Simmond.....	948,587
Mail marking machine, T. E. Stoddard.....	948,552
Mailing tube, G. D. Horton.....	948,823
Mangle, P. L. Brockard.....	948,803
Manure loader, W. Roberts.....	948,677
Marking gear, W. R. Perkins.....	948,544
Match box, E. E. Jones.....	948,684
Match receptacle, H. Park.....	948,872
Matrix forming machine, G. S. Williamson.....	948,830
Matress, A. Hupstad.....	948,861
Matress cover, E. L. Fuller.....	948,872
Measuring the flow of liquids, apparatus for, C. J. Clark.....	948,830
Mechanical movement, H. C. Gannett.....	948,950
Medicaments, preparing, A. Meyer.....	948,681
Menu cards, newspapers, and other articles, support for, Darcbe & Schwer.....	948,414
Metal, electrolytic separation of, Chance & Kent.....	948,960
Metal, expanded, N. E. Clark.....	948,440
Milk cooler, J. S. McNeil, Jr.....	948,360
Milking apparatus, cow, F. M. Beckrich.....	948,841
Milking machine, Waverly, Albion.....	948,608
Milking machine, B. J. Bigelow.....	948,080
Milking machine test cup, Bodge & Andersen.....	948,428
Milling spirals, machine for, B. W. W. Hays.....	948,475
Mittor box, N. G. Nelson.....	948,975
Mold, see Briguet mold.....	948,315
Mold for plastic bodies, W. H. Crum.....	948,528
Molding flask, C. D. Smith.....	948,975
Molding machine counterbalance, E. M. Huglin.....	948,574
Motor head, E. H. Fulton.....	948,908
Motor controller, automatic, A. E. Handy.....	948,511
Motor controlling device, electric, F. A. Hayes.....	948,323
Mouse trap, G. O. Terry.....	948,827
Mower, C. Larson.....	948,474
Muscle roll turner, F. Kohn.....	948,570
Muscle roll for mechanical musical instruments, H. P. Ball.....	948,790
Musical instrument, self-playing, B. L. Cartwell.....	948,790
Nail coating machine, Hart & Dobson.....	948,790
Napkin holder, H. H. Pricke.....	948,790
Net lifting machine, self-clearing gill, J. Gierke.....	948,790
Net making machine, C. Zane.....	948,790
Nipple threading mechanism, H. W. Oster.....	948,790
Nut lock, C. J. Tomlinson.....	948,790
Nut lock, S. Harvey.....	948,790
Nut lock for rail joints, J. J. O'Donnell.....	948,790
Nuts, manufacturing thumb, H. H. Smith.....	948,790
Office equipment, F. Stevenson.....	948,790
Oil burner, W. H. Creswell.....	948,790
Oil cake envelop or press cloth, N. W. L. Brown.....	948,790
Onion pulling attachment, F. A. Zappe.....	948,790
Operating table, E. E. Helfrich.....	948,790
Ore pulp treating apparatus, B. MacDonald.....	948,790
Ores for the extraction of metals, apparatus for treatment of, H. Rosall.....	948,790
Oscillations, apparatus for producing high frequency, L. Schenberg.....	948,790
Overthrow, J. J. Smith.....	948,790
Oxide of nitrogen from the air, producing, F. L. Du Paul.....	948,790
Package, J. S. Ferguson.....	948,790
Package, J. H. Boye.....	948,790
Peeling ring, McKim & Norris.....	948,790
Peeling rod, Johnston & Finley.....	948,790
Paddle, J. Hary.....	948,790
Padlock, mechanical, F. J. Gilman.....	948,790
Paint and varnish remover, M. Daxe.....	948,790
Paper bags or the like, rack for, J. J. Caylor.....	948,790
Paper folding machine, A. B. Colburn.....	948,790
Paper or similar fabric in web form, manipulating, Knapp & Pavecast.....	948,790
Paper weight and fan, combined, J. Keith.....	948,790
Paper and cover, combined vegetable, A. Chase.....	948,790

AGRICULTURE.—The New Agriculture. By T. Hyard Collins. 12mo.; 274 pages; 106 illustrations. \$2.00

A popular outline of the many changes which are revolutionizing the methods of farming, and the habits of farm life. It is one of the most practical treatises on the subject which has ever been issued.

ALCOHOL.—Industrial Alcohol. Its Manufacture and Uses. By John K. Brachvogel. 8vo.; 528 pages; 107 illustrations. \$4.00

A practical treatise based on Dr. Max Moser's "Industrie des Alkohols," as revised by Drs. Delbruck and Lange, comprising raw material, mashing and yeast preparation, fermentation, distillation, rectification and purification of alcohol, alcoholization, the value and significance of a false free alcohol, methods of denaturing, its utilization for light, heat, and power production, a statistical review, and the United States law.

AMATEUR MECHANICS.—Home Mechanisms for Amateurs. By George M. Hopkins. 12mo.; 370 pages; 328 illustrations. \$1.50

This is a thoroughly practical book by the most noted amateur experimenter in America. It appeals to the boy as well as the more mature amateur. Holidays and evenings can be profitably occupied by making useful articles for the home or in the building of small engines or motors or scientific instruments.

AMUSEMENTS.—The Scientific American Boy. By A. Russell Bond. 12mo.; 317 pages; 340 illustrations. \$2.00

This is a story of outdoor boy life, suggesting a large number of diversions which, aside from affording entertainment, will stimulate in boys the creative spirit. In each instance complete practical instructions are given for building the various articles.

COMPRESSED AIR.—Compressed Air. Its Production, Uses, and Application. By Gardner D. Hiscox. 8vo.; 665 pages; 540 illustrations. \$5.00

The most complete book on this subject. It treats on its physical and operative properties, and is written by an expert. Taken as a whole it might be called an encyclopedia of compressed air.

DIES.—Their Construction and Use for the Modern Working of Sheet Metals. By Joseph V. Woodworth. 8vo.; 384 pages; 505 illustrations. \$3.00

A most useful book, and one which should be in the hands of all engaged in the press working of metals; treating on the designing, constructing, and use of tools, fixtures and devices, together with the manner in which they should be used in the power press, for the cheap and rapid production of sheet metal articles.

ELECTRICITY.—The Standard Handbook for Electrical Engineers. Written and compiled by a Staff of Specialists. Second edition, corrected. 12mo.; 1285 pages; 1260 illustrations. Bound in flexible morocco. \$4.00

A new pocketbook consisting of twenty sections, each written by a specialist of engineering experience and containing the latest data and information regarding standard electrical practice.

ELECTRICITY.—Electrician's Handy Book. By T. O'Connor Sloane. 761 pages; 556 illustrations. Handsomely bound in red leather, pocket-book style. \$3.50

This work is intended for the practicing electrician who has to make things go. Although the principles of electricity and magnetism are treated, the greater part of the book is devoted to the handling of machinery, details of construction, and computations such as will be encountered in every-day practice.

GAS ENGINES.—Modern Gas Engines and Producer Gas Plants. By R. E. Mathot. 8vo.; 314 pages; 145 illustrations. \$2.50

A practical treatise setting forth the principles of gas engines and producer design, the selection and installation of an engine, conditions of perfect operation, production of gas, and the gas-bilities, the care of gas engines and producer gas plants, with a chapter on volatile hydrocarbon, and oil engines.

GAS ENGINES.—Gas, Gasoline, and Oil Engines. Including Producer Gas Plants. By Gardner D. Hiscox. 8vo.; 476 pages; 412 illustrations. \$2.50

A complete book on the subject for gas engine owners, gas engineers, and intending purchasers of gas engines, treating fully on the construction, installation, operation, and maintenance of gas, gasoline, kerosene, and crude petroleum engines, with special information on producer and suction gases.

GAS ENGINES.—Gas Engine Construction. By H. V. A. Parsell and A. J. Weed. 8vo.; 304 pages; 145 illustrations. \$2.50

A practical treatise describing the theory and principles of the action of gas engines of various types, and the design and construction of a half-horse-power gas engine, with illustrations of the work in actual progress, together with the dimensioned working drawings giving clearly the sizes of the various details.

HEATING.—Practical Steam and Hot Water Heating and Ventilation. By Alfred G. King. 8vo.; 402 pages; 804 illustrations. \$4.00

An original and exhaustive treatise prepared for the use of all engaged in the business of steam, hot water heating, and ventilation. The standard and latest book published. Describes all of the principal systems of steam, hot water, vacuum, vapor, and vacuum-vapor heating, together with the new accelerated systems of hot water circulation, including chapters on up-to-date methods of ventilation.

HYDRAULICS.—Hydraulic Engineering. By Gardner D. Hiscox. 8vo.; 315 pages; 305 illustrations. \$4.00

A practical work treating on the properties, power, and resources of water for all purposes, including the measurement of streams, the flow of water in pipes or conduits; the horse-power of falling water; turbine and impact water wheels; the water motors; centrifugal, reciprocating, and air-lift pumps, etc.

INDUCTION COILS.—The Design and Construction of Induction Coils. By A. Frederick Collins. 8vo.; 295 pages; 160 illustrations. \$3.00

This work gives in minute details full practical directions for making every kind of induction coil, varying from small one giving a 1/2-inch spark to a large one giving 12-inch sparks. The dimensions of each and every part down to the smallest are given, and the descriptions are written in language easily comprehended.

LATHE.—Modern American Lathe Practice. By Oscar E. Perrigo. 8vo.; 424 pages; 314 illustrations. \$2.50

A new book describing and illustrating the very latest practice in lathe and boring mill operations, as well as the construction of and latest developments in the manufacture of these important classes of machine tools.

MAGIC.—Magic, Stage Illusions, and Scientific Diversions. Including Trick Photography. Compiled and edited by Albert A. Hopkins. 8vo.; 568 pages; 420 illustrations. \$2.50

This very interesting volume is acknowledged to be the standard work on magic. It appeals to the professional and amateur alike. The illusions are all explained in detail, showing exactly how the tricks are performed.

MECHANICAL MOVEMENTS.—Mechanical Movements, Powers, and Devices. By Gardner D. Hiscox. 8vo.; 402 pages; 1,800 illustrations. \$3.50

This is a collection of different mechanical motions and appliances, accompanied by appropriate text, making it a book of great value to the inventor, the draftsman, and to all readers with mechanical tastes.

MECHANICAL APPLIANCES.—Mechanical Appliances, Mechanical Movements, and Novelties of Construction. By Gardner D. Hiscox. 8vo.; 396 pages; 970 illustrations. \$2.50

This book, while complete in itself, is in fact a continuation of the author's "Mechanical Movements, Powers, and Devices." The author presents to the reader information regarding nearly all conceivable devices for producing motion or accomplishing mechanical results.

SPECIAL OFFER: These two volumes sell for \$3 each, but when they are ordered at one time from us, we send them prepaid to any address in the world, on receipt of \$4.

PATENTS.—Practical Pointers for Patentees. By F. A. Cresce. 12mo.; 144 pages. \$1.00

Containing valuable information and advice on the sale of patents and elucidation of the best methods employed by the most successful inventors in handling their inventions. It gives exactly that information and advice about handling patents that should be possessed by every inventor who would achieve success.

PHYSICS.—Experimental Science. Elementary, Practical, and Experimental Physics. By George M. Hopkins. In two volumes. 8vo.; 1,105 pages; 918 illustrations. Cloth, \$5.00. Half morocco, \$7.00

This book treats on the various topics of physics in a popular way and deals with rare clearness and in detail the apparatus used, and explains the experiments in full, so that teachers, students, and others interested in physics may readily make their own experiments without great expense and perform the experiments without difficulty.

PLUMBING.—Modern Plumbing Illustrated. By R. M. Starbuck. 392 pages; 104 x 7 1/2; 55 full-page engravings. \$4.00

A comprehensive and up-to-date work illustrating and describing the drainage and ventilation of dwellings, apartments, and public buildings, etc. The very latest and most approved method in all branches of sanitary installation are given.

PUNCHES.—Punches, Dies, and Tools for Manufacturing in Presses. By Joseph V. Woodworth. 8vo.; 488 pages; 702 illustrations. \$4.00

This work is a companion volume to the author's other work entitled "Dies, Their Construction and Use," which is a complete encyclopedia on die making, punch making, die sinking, and sheet metal working.

RECEIPTS.—The Scientific American Encyclopedia of Receipts, Notes and Queries. Edited by Albert A. Hopkins. Containing 15,000 recipes, formulas, etc. 8vo.; 734 pages. Cloth, \$5.00. Sheep, \$6.00. Half morocco, \$6.50

Over 15,000 selected receipts are here collected, nearly every branch of the useful arts being represented. The alphabetical arrangement, with abundant cross references, makes it an easy work to consult. It has been used with equal success by chemists, technologists, and those unfamiliar with the arts, and is a book which is useful in the laboratory, factory, or home.

REFERENCE BOOK.—Scientific American Reference Book. Compiled by Albert A. Hopkins and A. Russell Bond. Containing 50,000 facts. 12mo.; 616 pages; illustrated. \$1.50

This book deals with matters of interest to everybody. It contains 50,000 facts, and is much more complete and more exhaustive than anything of the kind which has ever been attempted. It is indispensable to every family and business man. It is a book for everyday reference—more useful than an encyclopedia, because you will find what you want in an instant in a more condensed form.

STEAM ENGINE.—Modern Steam Engineering in Theory and Practice. By Gardner D. Hiscox. 8vo.; 487 pages; 405 illustrations. \$4.00

This is a complete and practical work issued for stationary engineers and firemen, dealing with the care and management of boilers, engines, pumps, superheated steam, refrigerating machinery, dynamos, motors, and compressors, and with many other branches with which the modern engineer must be familiar.

TELEPHONE.—Telephone Construction, Installation, Wiring, Operation, and Maintenance. By W. H. Radcliffe and H. C. Cushing, Jr. 16mo.; 171 pages; 125 illustrations. \$1.00

A practical book intended for electricians, wiremen, engineers, contractors, architects, and others interested in the installation of telephone devices in accordance with standard practice. Intricate mathematics are avoided, and all apparatus, circuits, and systems are thoroughly described. Selected wiring tables, which are very helpful, are also included.

TOOLS.—American Tool Making and Interchangeable Manufacturing. By Joseph V. Woodworth. 8vo.; 535 pages; 601 illustrations. \$4.00

A complete practical treatise containing a valuable collection of drawings and descriptions of devices, the results of the author's own experience. Intricate mathematics are avoided, and all apparatus, circuits, and systems are thoroughly described. Selected wiring tables, which are very helpful, are also included.

TOOLS.—Modern Machine Shop Tools. By W. H. Vandervoort. 8vo.; 552 pages; 673 illustrations. \$4.00

A new and fully illustrated work describing in every detail the construction, operation, and manipulation of hand and machine tools; being a work of practical instruction in all classes of machine shop practice.

WIRING.—Electric Wiring, Diagrams and Switchboards. By Newton Harrison. 12mo.; 272 pages; 105 illustrations. \$1.50

This work is a thoroughly practical treatise on electric wiring in all its branches, beginning with the simple circuit and working up to the practical every-day problems, all being presented in a simple and intelligible manner. It is in every respect a handy, well written, instructive, comprehensive volume on wiring for the wireman, foreman, contractor, or electrician.

(Concluded from page 171.)

sideways displacement is not of sufficient magnitude to make the stars appear separately, and hence we have a comparatively new class of stars, those which appear as single even in the most powerful telescopes, but whose motions in the spectroscopic show that they are really double stars. These are called spectroscopic binaries. Recent researches at the Lick Observatory, Yerkes Observatory and other places bring to our knowledge most startling results. Imagine two stars each many times more massive than our own, rapidly revolving about each other in a few hours! In addition to this comes the fact that at least one in every few stars so far investigated turns out to be not a single star but a system, and it has become necessary to reconstruct our ideas regarding the importance in the universe of this small ball which we call Mother Earth.

Dying Pearls.

(Concluded from page 162.)

chill which can very easily cause its tender outer layers to contract and its beautiful luster to disappear. Unfortunately the Thiers collar has been laid on red velvet, and this circumstance, too, can help to dull its shimmering surfaces day by day, for the color also, produced by chemical means, exercises a slow but sure influence. Besides it lies too near a window, and so the rays of light, too, have an injurious effect on it. The directors of the Museum of the Louvre have long deemed the collar one of their most precious curiosities; but now, in consequence of the evident steady diminution of its value, they would like to sell it and with the money obtained for it procure a few more good paintings. Permission therefore, however, is refused by the executrix and chief heiress of the Thiers estate, and consequently the jewelers of Paris consider the collar an object of experiment by which it will be shown in how many years a pearl can "die away" when nothing is done for its preservation. How long pearls "live," that is, how long they keep their luster, has not yet been ascertained, but, as many instances, especially in the successive inheritance of heirlooms, prove, some preserve their freshness through centuries in consequence of the habitual gentle treatment they receive. When treated thoughtlessly a pearl dies quickly.

Life Insurance and the Moral Responsibility of Employers.

BY DARWIN P. KINGSLEY.

The growth of life insurance and the development of a deep sense of responsibility on the part of employers of labor toward their employees are contemporaneous and kindred phenomena. They represent a better knowledge of the value of human life and a recognition of the increasing demand now fairly made on the controlling forces of society, by age and industrial misfortune, as well as by infancy, congenital incapacity, and weakness.

The middle-aged and the socially inefficient now form a relatively larger section of society than ever before. There are two reasons for this. The first is, that while there may not be as many children born now as formerly, among certain people, of the number born a much larger portion reach maturity. In other words, the ratio of adults to a given number of births has increased. The second reason is that modern business methods and the modern corporation, especially the manufacturing corporation, have created new conditions and complications. They have added to those who join the dependent classes under a simpler life, those who become dependent because their active lives have been devoted to highly specialized work.

Highly specialized labor is constantly menaced by loss of occupation, and this menace increases as the age of the worker advances. Under the fierce competition (Continued on page 173.)

Any of the above books will be sent postpaid on receipt of price.

Our complete catalogue of scientific and technical books sent free on application

MUNN & COMPANY, Inc., Publishers, 361 Broadway, New York City

Please mention the SCIENTIFIC AMERICAN when writing to advertisers

Pasteurizing apparatus, Cauffman & Best...	948,443
Paving block, composite, E. H. Benner...	948,808
Pen, foldable and portable stock, W. C. Smith...	948,351
Pen, stylographic, L. Trotsky...	948,832
Pen and pencil, retainer for fountain, L. D. Van Valkenburg...	948,802
Penholder, J. M. Geiger...	948,832
Penholder, R. B. Ward...	948,910
Penell, C. von Schmiedlitzky...	948,535
Petticoats, dounce for, D. J. McKenna...	948,821
Phonograph, W. H. Hoesche...	948,327
Phonograph, C. M. Hughes...	948,328
Phonograph, P. M. Ravensdale...	948,675
Photographic prints, etc., device for use in connection with the dry mounting of, G. W. Morgan...	948,807
Plano, Danquard & Fraumetall...	948,391
Plano, keyless, T. P. Brown...	948,984
Picture machines, adjusting mechanism for moving, W. N. Sell...	948,654
Pile fabric and weaving the same, M. J. Whittall...	948,384
Pin, F. M. Schwartz...	948,775
Pipe, See Blowpipe...	948,550
Pipe, cigar holder, etc., J. R. Perry...	948,634
Pipe coupling, train, R. M. Dixon...	948,312
Pipe hanger, A. A. Noyes...	948,302
Pipe joint filling device, P. J. Hatch...	948,586
Pipe threading machine, E. A. Hoefler...	948,394
Pipe support, wire, O. A. Muller...	948,671
Plow, E. Rosenfeld...	948,431
Plow attachment, C. W. Eschert...	948,478
Plow attachment, L. H. McCall...	948,614
Plow, hand, A. R. Corrington...	948,457
Plow moldboard, rotary, A. Morison...	948,457
Plumbing systems, test connection...	948,525
Pneumatic despatch tube system, F. H. Wolever...	948,714
Polisher, J. E. Curtis...	948,691
Post brace anchor, C. I. Stocking...	948,532
Potato cleaning and assorting machine, J. A. Riddle...	948,842
Poultry fountain, K. B. Martin...	948,528
Powder magazine, Ervin & Keeton...	948,923
Power transmission, J. G. P. Thomas...	948,436
Printing presses, ribbon cutting attachment for, A. Livermore...	948,632
Projecting device, W. H. Munshaw...	948,565
Pulley, driving, J. Mold...	948,516
Pump for cleaning drain pipes, suction, L. O. Landgren...	948,590
Pump for motor vehicles, tire, M. L. Bastian...	948,807
Pumps or motors, packing for rotary, R. F. Trattner...	948,534
Pumps, water regulator for jacketed, W. M. Austin...	948,471
Punch and die mechanism, C. A. Lindholm...	948,815
Punching machines, automatic attachment for withdrawing punchings from, Scott & Gale...	948,582
Rail clip, O. M. Knox...	948,375
Rail, guard, O. C. Sigmund...	948,597
Railway coupling, A. Lewis...	948,765
Railway tie, H. M. Levinson...	948,589
Railway tie and rail fastening, W. R. Gorrell...	948,577
Rake, See Lawn cleaner rake...	948,496
Rake cleaning attachment, hand, W. Bullard...	948,497
Rangy, H. S. Martin...	948,943
Razor blade holder, C. W. Levalley...	948,864
Razor stopping device, W. H. Nicholls...	948,673
Record keeping device, A. H. Wheeler...	948,676
Reeling and other textile machines, thread tightening device for, J. Schwellter...	948,580
Refrigerator, F. I. Armstrong...	948,404
Refrigerator, H. Bieder...	948,750
Refrigerator, Hans & Mefford...	948,880
Rein guide, W. Laudon...	948,453
Reversing mechanism, G. W. Freeland...	948,781
Ribbon fastener and sales index, D. H. Woodman...	948,490
Riveting device, J. Tischer...	948,980
Rotary engine, W. G. Dodd...	948,602
Router bit, C. Schrepper...	948,504
Rubber rings, machine for cutting, W. P. McGeouch...	948,401
Rupture appliance, Hogle & Meyer...	948,627
Sad iron, Spahr & Stichter...	948,773
Safe and vault protector, R. Menne...	948,920
Salting device, automatic stock, F. & T. L. Peifer...	948,794
Sand drier, Jackson & Fleischbein...	948,520
Sash fastener, A. Kissinger...	948,588
Sash fastener, E. L. Brenner...	948,918
Sash window, G. J. Miller...	948,513
Saw gauge, crosscut, J. Morin...	948,504
Saw gunner, C. A. Chandler...	948,853
Saw, N. Nilson...	948,705
Screen, R. M. Dixon...	948,313
Screen, E. C. Schofield...	948,433
Screw head turning and nicking machine, W. Avery...	948,492
Screw lock, J. P. Hesse...	948,326
Seal lock for receptacles, C. H. Johnson...	948,790
Sectional belt, E. Pongell...	948,559
Seed huller, cotton oil mill, Kappler & Gaines...	948,508
Separating, washing, and concentrating materials, A. W. H. Lenders...	948,512
Separating, washing, and concentrating materials, apparatus for, A. H. Lenders...	948,413
Sewer mold, E. E. Clark...	948,539
Sewing machine, M. G. & A. Rosenthal...	948,345
Sewing machine embroidering or darning foot, W. C. Ellis...	948,683
Sewing machine folding and trimming mechanism, D. Zeller...	948,364
Shade holder, E. E. Brock...	948,473
Shaper attachment, Kramer & Brown...	948,784
Sharpening, cutlery, J. A. Wilkinson...	948,502
Sharpening, tool, J. Noss...	948,429
Sharpening device, lawn mower, C. C. Rayl...	948,962
Sharpening machine, razor, E. A. Conway...	948,309
Sheet metal corrugating machine, J. J. Rigby...	948,551
Ship detector, F. S. Long...	948,424
Shipping case, interchangeable, N. J. Bushy...	948,380
Shoe loader, J. B. Schuman...	948,398
Shoe, H. McMaster...	948,338
Shoe vamp protective guard, Foley & Crowley...	948,410
Shovel, See Cultivating shovel...	948,494
Sifter, O. G. Boggs...	948,537
Sign, illuminated, R. B. Wiley et al...	948,979
Signal system, line, H. D. Stroud...	948,502
Signaling apparatus, G. Hughes...	948,502
Signaling system and appliances, J. G. Nolen...	948,738
Silo, R. J. & A. C. Klatt...	948,397
Sintering furnace, G. G. Vivian...	948,666
Skate, roller, Dodge & Alden...	948,866
Sled, O. J. Mennenga...	948,651
Sled brake, W. Nichols...	948,468
Smelting apparatus, E. Plank...	948,721
Soap dispensing machine, R. G. Clark...	948,314
Sound records and other objects, composition for, J. C. English...	948,825
Speed and reverse drive mechanism, change, A. C. Plett...	948,650
Spinning machine, doffer guard, R. S. Matteson...	948,500
Spinning machine, H. S. Kemp...	948,743
Spring fork, M. Schenck...	948,493
Spring support, A. G. Bodenstern...	948,383
Sprocket wheel, W. J. Yetter...	948,630
Squeegee or window cleaner, J. R. Laner...	948,423
Stalk cutter, W. R. Lemons...	948,854
Stalk cutter and cart, combined, J. T. Graves...	948,811
Stamp holder, multiple self-linking, W. W. Holler...	948,690
Staple forming and discharging mechanism, W. Hoxie...	948,913
Staple or clip, J. Yetter...	948,306
Steam boiler, T. Barrow...	948,373
Steam boiler, tubular, S. Elliott...	948,932
Steel working pit for manufacture of, Myers & Dill...	948,655
Stereotype matrices, apparatus for producing, H. Winter...	948,658
Stitcher, garment, L. B. Lardon...	948,553
Stitch or table, foldable, H. J. Swartz...	948,747
Stitch flue, E. A. Thompson...	948,833
Stitch, vapor, E. A. Gutermann...	948,692
Stitcher collar and anchor, E. E. Younts...	948,937
Stitcher holder, L. A. & W. J. Shaw...	948,937

Finder of Men



An average American knows many people. But he does not always know where they are.

He has a thousand friends and acquaintances. Where are they at this particular moment? He can be sure of some of them—perhaps a dozen. But he wants to locate one or more of the others.

The Bell system enables him to reach them.

If he finds his friend at home, or in his place of business, he talks with him at once. If he learns that his friend is in some other town the Bell System will furnish the connection.

Cities are larger than they used to be. Men know and need to know more people. Yet the need of keeping in touch is as great as ever. Without Bell service there would be hopeless confusion.

The range of the telephone is not confined to one town or one community. It is not satisfying simply to learn that a man is out of town; through the Long Distance Service of the Bell System he may be reached wherever he is.

The Bell Service extends to all communities. It reaches the millions of American people. One in twenty is a Bell subscriber. The other nineteen can be found, because Bell service is universal service.

The telephone does more work for less money than any other servant of mankind. There is economy as well as efficiency in one system, one policy, universal service. Every Bell Telephone is the Center of the System.

AMERICAN TELEPHONE AND TELEGRAPH COMPANY AND ASSOCIATED COMPANIES

MULLINS STEEL BOATS ARE FASTEST

They KEEP AFLOAT in the heaviest weather because the hull is made of pressed steel plates with air compartments like a lifeboat. They KEEP AHEAD of all other boats of equal H.P. because the smooth steel hull offers little resistance to the water, and they are equipped with the new Mullins Engine that is absolutely reliable under all conditions. Can't backfire; will not stall at any speed. STARTS AND RUNS LIKE AN AUTOMOBILE ENGINE. Every Mullins Boat is guaranteed to give perfect satisfaction.

Write for our complete catalog of Motor Boats, Launches, Row Boats, Hunting and Fishing Boats, and Marine Engines.

W. H. MULLINS CO., 208 Franklin St. Salem, Ohio, U. S. A.

ELECTRICIAN AND MECHANIC

A fairly illustrated monthly magazine publishing practical educational articles on all branches of electricity and mechanics. Complete directions and working drawings for making steam and gasoline engines, dynamos and motors, furniture, wiring instruction, wireless telegraphy, mechanical drawing, etc. Three months' trial, twenty cents. \$1.00 a year. Catalogue of electrical and mechanical books free.

SAMPSON PUBLISHING COMPANY, 1151 Beacon Building, Boston, Mass.

NOW READY!

THE FOURTH DIMENSION

SIMPLY EXPLAINED

WITH AN INTRODUCTION BY HENRY P. MANNING
Professor of Mathematics, Brown University

Price, \$1.50 net. 260 pages illustrated

A FRIEND of the Scientific American's donated a prize of \$500.00 for the best simply-worded non-mathematical explanation of the Fourth Dimension. The prize was won by Lieut. Col. G. D. Fitch, U. S. A. This essay, together with three others which were accorded honorable mention, was published in the columns of the Scientific American. As a result, so much interest was aroused in the subject of the Fourth Dimension that it seemed advisable to collect, in permanent form, the more meritorious of the 245 essays which were sent in from all parts of the world.

The present work presents twenty points of view, all of them interesting and no two quite alike. Each essay is 2500 words in length. The reading of one essay does not involve the reading of the entire work, yet the entire book gives a comprehensive view of what the layman wishes to know about the Fourth Dimension. No abstract mathematics will be found in the volume. The essays endeavor to explain to Fourth Dimension both by imagining the effect of transporting an ordinary third-dimensional human being into fourth-dimensional space and also by explaining a third-dimensional man's possibilities in one and two dimensional space.

Professor Manning, the leading American authority on the subject of the Fourth Dimension, contributes an introduction in which he explains how the concept of the Fourth Dimension gained mathematical prominence, and swiftly reviews the work that has been done in the field. He has also edited the essays and supplied explanatory footnotes where required.

ORDER FROM YOUR BOOKDEALER OR FROM

MUNN & COMPANY, Inc., 361 Broadway, NEW YORK

(Continued from page 172.)

which governs the greater portion of our industrial life, new processes, new methods, short cuts, labor-saving devices, new inventions, are all eagerly sought by the employer of labor. Some of these are revolutionary in their effects. They call for a readjustment of the whole plant. When that readjustment comes, the older men are invariably dropped. In short, the avenues which lead to employment, for all highly specialized labor, are practically open now only to youth. The middle-aged man enters with difficulty, and the man past middle life substantially cannot enter at all. The man who did many things, none of them highly specialized, from twenty to sixty-five, is likely never to become entirely dependent upon society. The man who did some highly specialized piece of work which involved only a part of some specific thing, or even a part of a part, may be forced into the dependent class before he reaches old age, and when he joins that class he is much more helpless than the man who has done many things. It is probable that the specialist, although he labored fewer years, rendered society the more valuable service of the two, and that therefore he has, morally at least, a clearer title to consideration. But however that may be, he is the inevitable product of the whole plan of society and business, and the obligation of the man who employs him, and the interest of general society in what finally becomes of him, are clear and unavoidable. That this class must be shown how to protect itself against the menace which it constantly faces or that it must be helped outright after disaster or age come, are compelling facts in the sociology of the times.

There can be no question that a system which teaches these people how to protect themselves against this menace, is more in harmony with the genius of our institutions than a system which coerces them into action or a system which finally places the burden of their support and care upon general society. It does not follow that a system which works well in Germany would work well here; or that a system which appeals to the needs of the people of Great Britain will answer here. There are distinct advantages in the German plan,—chiefly that it is compulsory and that the laborer is forced to make provision for certain benefits even though he may have no very intelligent understanding of the wisdom of the plan or its effects on society. There is a difference between the compulsion of government, which tells the workingman that certain things must be done, and the proposition of a corporation which tells a man what the conditions of his hiring are.

If the conditions named by the employer involve some system of life insurance, some system of deferred annuities, a man can study the question and take a position or leave it alone because it recommends itself to his judgment or otherwise. This is a slower process than the German method, and probably for a good many years will be more expensive; but it seems to me to be in harmony with our notions of individual responsibility and the rights as well as the obligations of American citizenship.

The efficient employee, in specialized labor, has a fair claim to something beyond the returns contained in the ordinary contract of hiring. This right may be strengthened and its realization advanced, but it cannot directly be met, in this country, by governmental action. The capable worker deserves and should demand a programme of hiring under which he shall be entitled—and entitled by contract, not by the grace of his employer—to certain protection for his family if he dies prematurely, and to certain protection for himself if in the vicissitudes of industrial war he is shelved and wholly or in part compelled to join the dependent class.

There are sound reasons why corpora
(Concluded on page 174.)

Classified Advertisements

Advertising in this column is 75 cents a line. No less than four nor more than 10 lines accepted. Count seven words to the line. All orders must be accompanied by a remittance. Further information sent on request.

READ THIS COLUMN CAREFULLY. You will find inquiries for certain classes of articles numbered in consecutive order. If you manufacture these goods write us at once and we will send you the name and address of the party desiring the information. There is no charge for this service. In every case it is necessary to give the number of the inquiry. Where manufacturers do not respond promptly the inquiry may be repeated.

MUNN & CO., Inc.

BUSINESS OPPORTUNITIES

WE ARE WELL EQUIPPED to manuf. some patent article—electrical and wood-working on royalty or other satisfactory basis. Will entertain exhibiting. Electrical, Box 774, N. Y.

Inquiry No. 8918.—For manufacturers of "Weld's Electro-Catalytic Sparking Plug."

PATENTS FOR SALE.

SENSATIONAL RIDING amusement device patent, sure winner. Write for descriptive illustration. Sell reasonable. J. W. Bourke, 17 Leyland St., Dorchester Mass.

FOR SALE.—U. S. Patent No. 913,542. An automatic brake to obviate danger to pedestrians and teamsters from depending live broken treadle wires, by providing means whereby broken sections of such wires are automatically thrown out of the circuit and thus rendered harmless. Henry Nannenborn, 321 Schiller St., Chicago.

Inquiry No. 9014.—For manufacturers of machinery, supplies, etc. to equip a small plant for the manufacture of sodium-tipped acid nit making for fountain pens.

FOR SALE.

FOR SALE.—Engine lathe, swing 9 1/2 in., takes 25 in. between centers. Complete with full set change gears to cut all size threads, 3 to 48 in. Price only \$44.95. Address L. F. Grammes & Sons, Allentown, Pa.

Inquiry No. 9016.—Wanted, machinery necessary for an installation of a plant for refining salt by a modification of the Bessemer process.

WANTED.

WANTED. by a corporation engaged in the manufacture of agricultural machinery, a competent draughtsman, reasonably well informed as to patent law, to take charge of its patent department, under the supervision of its general counsel. Reply only by mail, addressing the secretary of the advertiser, M. L. Lyon, 327 Seventh Avenue, New York City.

Inquiry No. 9023.—Wanted, to buy silk machines from reeling, twisting, doubling, to the final process of making it into cloth.

WANTED. partner to defray cost of patents on very striking and attractive toy. Guaranteed patentable. Rare opportunity for somebody. Address J. Thomas Houston, Henderson, Texas.

Inquiry No. 9029.—Wanted, catalogues and all information on machinery for braiding straw in manufacturing straw hats.

LISTS OF MANUFACTURERS.

COMPLETE LIST of manufacturers in all lines supplied at short notice at moderate rates. Small and special lists compiled to order at various prices. Estimates should be obtained in advance. Address Munn & Co., Inc., 1st Department, Box 774, New York.

Inquiry No. 9036.—Wanted, the address of the manufacturers of "Cyclo Ball Bearing Suspenders."

A LIST of 1,500 names and consulting engineers on cards. A very valuable list for circulating, etc. Price \$10.00. Address Munn & Co., Inc., 1st Department, Box 774, New York.

Inquiry No. 9038.—Wanted, the address of the Chipman Electric Purifying Co.

Inquiry No. 9042.—Wanted the address of Farney Safety Razor Co.

Inquiry No. 9046.—Wanted, machinery used for the manufacture of all kinds of fruit boxes, baskets and crates.

Inquiry No. 9049.—Wanted, to buy rotary brushes suitable for a shoe shining machine.

Inquiry No. 9053.—Wanted, address of firms who install plants to manufacture nitrogen.

Inquiry No. 9055.—Wanted, address of parties interested in Lost Cleaning Machines.

Inquiry No. 9057.—For manufacturers of class and chain balls, used as fixtures or ornaments on lighting rod equipment, also weather vanes for same purpose.

Inquiry No. 9058.—Wanted, firms who make machinery used for pulverizing soap-stone.

Inquiry No. 9060.—Wanted to buy machinery to manufacture seed corn racks.

Inquiry No. 9062.—Wanted to buy a plant for manufacturing muriatic acid.

Inquiry No. 9065.—Wanted to buy a second hand telephone generator.

Inquiry No. 9066.—Wanted complete outfit for export for making rice flares and wheat flares.

Inquiry No. 9067.—Wanted the address of makers of the Standard Folding Typewriter.

Inquiry No. 9068.—Wanted to buy machinery for manufacturing chewing gum, such as rollers, cutting or wrapping machinery.

Inquiry No. 9069.—For the address of firms making chain cloth, something like ladies' purses are made of.

Inquiry No. 9070.—Wanted, manufacturers of metal castings for car lamp shades.

Inquiry No. 9071.—Wanted, the address of parties making moulds for large concrete vases for flower pots.

Inquiry No. 9072.—Wanted, machinery for making fine chains, such as used by jewelers, etc.

Inquiry No. 9073.—Wanted, machinery to manufacture coconut oil; also the crude material.

Inquiry No. 9074.—Wanted, to buy old model locomotives or steamboats, such as were exhibited with Nickel-in-the-Road attachments in ferry-houses, etc.

A Home-Made 100-Mile Wireless Telegraph Set

Read **SCIENTIFIC AMERICAN** Supplement 1066 for a thorough, clear description, by A. Frederick Collins, of the construction of a 100-mile wireless telegraph outfit. Numerous adequate diagrams accompany the text. Price 10 cents by mail. Order from your newsdealer or from

MUNN & CO., Inc., 361 Broadway, New York

Strainer, E. V. Hax.....	948,421
Strainer, J. C. McKinn.....	948,900
Strainer, sink, G. W. Koon.....	948,954
Strainer, water, G. W. Koon.....	948,954
Strap joint, J. H. Skidmore.....	948,956
Stud or block, antislipping, T. Shaper.....	948,435
Subway, G. A. Jackson.....	948,431
Suik, H. J. Miller.....	948,432
Superheater, H. W. Jacobs.....	948,436
Surgical clip applicator, A. Le Witt.....	948,436
Switch, See Electric switch.....	
Switch box or casing, Ziegler & Woodburn.....	948,438
Switch thrower, automatic, E. McNeill.....	948,427
Table having hinged leaf, A. Hendricks.....	948,729
Table leveler, F. K. Sheppard.....	948,708
Target trap, W. J. Clow.....	948,499
Tape feeding mechanism for, D. P. Moore.....	948,944
Tape applying machine, M. B. Diskin.....	948,575
Tapper, beer, W. W. Frisholm.....	948,647
Taximeter, A. J. B. E. Harris.....	948,571
Telephone call system, W. E. Zahut.....	948,941
Telephone pay station box, C. A. Anderson.....	948,753
Telephone transmitter, wireless, A. A. Jahnke.....	948,600
Terminal clamp, H. P. Richter.....	948,596
Thread cutting tool, J. B. Phillips.....	948,706
The molding machine, Costello & Houston.....	948,982
Tiles, etc., apparatus for decorating, Meyer & Young.....	948,931
Time controlling mechanism, A. W. Bailey.....	948,718
Time from the plate working apparatus for, H. Brandenburg.....	948,679
Tire air pressure gauge, W. E. Sandham.....	948,526
Tire, pneumatic, Kitchen & Storey.....	948,701
Tire, pneumatic, W. Odell.....	948,563
Tire setter, W. Schau.....	948,637
Tire tightener or tire setter, W. Schau.....	948,638
Tire, vehicle wheel, J. Cairns.....	948,389
Transferring apparatus, pneumatic, J. K. Williams.....	948,489
Tobacco pipe, J. R. Perry.....	948,635
Tool holder, H. M. Hanson.....	948,608
Toy, educational, H. B. Palmer.....	948,633
Track brace, A. J. Coover.....	948,390
Train stopping and signal actuating mechanism, J. F. Webb, Jr.....	948,461
Transfering apparatus, material, L. Collins.....	948,719
Tread protector, T. J. McNamara.....	948,339
Tree wires and the like, suspension device for, G. A. Mead.....	948,789
Trowsers stretcher, R. B. Liddle.....	948,734
Trowsers stretcher and presser, W. V. Lane.....	948,805
Truck, cushion, J. Pfeiffer.....	948,482
Truck, hand, J. Buckner.....	948,964
Truck, Kallis & Berg.....	948,783
Truss, hernial, J. Bunker.....	948,305 to 948,307
Tube, See Mailing tube.....	
Tubes, manufacture of, M. Peters.....	948,961
Tug, hull, W. J. Campbell.....	948,780
Turbine, G. A. Boddy.....	948,916
Turn table, H. R. Stuckney.....	948,802
Twine cutter, H. I. Mattison.....	948,808
Type casting machine, W. N. Clements.....	948,605
Typewriter, R. L. Cary (now by marriage).....	948,932
Typewriter, expander.....	
Typewriter, H. S. McCormack.....	948,553
Typewriter, machine, A. W. Steiger.....	948,481
Typewriter, machine, A. W. Steiger.....	948,485
Typewriter, machine, J. C. McLaughlin.....	948,669
Typewriter, machine, A. M. Stone.....	948,799
Typewriter, machine, E. B. Hess.....	948,972
Typewriter, machine, supporting frame, D. Rice.....	948,826
Undercutter support, W. J. Whitworth.....	948,836
Undercutter, A. G. Jackvinsky.....	948,859
Valve, G. R. Keenings.....	948,871
Valve, C. W. A. Koelbeek.....	948,649
Valve and operating means therefor, hall cock, Neal & Childers.....	948,519
Valve, H. R. Keenings.....	948,871
Valve clean out, boiler check, J. R. Martin.....	948,702
Valve for blending hot and cold fluids, S. G. Neal.....	948,520
Valve, G. R. Keenings.....	948,871
Valve gear, J. Irving.....	948,976
Valve mechanism, air operated electrically controlled, J. F. Webb, Jr.....	948,465
Valve mechanism, air operated electrically controlled, J. F. Webb, Jr.....	948,466
Valve mechanism, non-return, E. Golden.....	948,445
Valve, pneumatic, W. E. Gelgel.....	948,469
Valve, universal controlling, W. C. Arp et al.....	948,571
Vaporizing and mixing device, F. Preston.....	948,402
Vehicle brake, automatic, W. E. Fisher.....	948,411
Vehicle driving mechanism, J. F. Walter.....	948,749
Vehicle, motor, G. W. Fuller.....	948,317
Vehicle, motor, G. W. Fuller.....	948,341
Vehicle, motor, E. Muller.....	948,331
Vehicle wheel, E. S. Williamson.....	948,621
Vehicles, elastic suspension for, L. Basso.....	948,689
Vending apparatus, A. H. Arnold.....	948,914
Vending machine, J. H. Canfield.....	948,699
Vending machine, W. Ashbury.....	948,838
Ventilating system, A. S. Johnson.....	948,629
Vessel closure, J. C. Schleicher.....	948,247
Voting mechanism, M. A. Deen.....	948,753
Wagon, dump, W. A. Underhill.....	948,358
Wagon seat lock, V. W. Heydlauff.....	948,905
Washboard, Ulrich & Weigert.....	948,969
Washboard, J. E. Terhune.....	948,901
Washbottle, S. C. Logan.....	948,897
Washer, See Vehicle washer.....	
Washer, J. B. Vannoy.....	948,690
Watch regulator, W. E. Porter.....	948,653
Water closet seat, auxiliary, J. G. Steffe.....	948,798
Water closet, etc., tank, G. H. Bailey.....	948,658
Water gate guard, D. Buisson.....	948,412
Water motor, L. L. Dadds.....	948,501
Water motor, current, H. B. Fenner.....	948,544
Water purifying apparatus, J. P. Lajole.....	948,785
Water purifying apparatus, automatic electric controller, E. H. Hartman.....	948,648
Water supply, automatic device for controlling, J. A. Anderson.....	948,203
Water wheel, Rangerier.....	948,755
Web manipulating mechanism, Knapp & Pancoast.....	948,748
Welding apparatus, E. G. Budd.....	948,965
Welding, brazing, or soldering, electric, O. Kjellberg.....	948,764
Well cover, B. D. Haining.....	948,329
Well drilling machine, G. D. Louis.....	948,425
Wheel, T. Benson.....	948,408
Wheel, R. B. Sandham.....	948,978
Wheel drive, magnetic traction, C. Scott.....	948,381
Wheel rim, removable, J. C. Cole.....	948,313
Whiffletree hook, J. M. Tanpan.....	948,354
Whiffletree hook, P. H. Skaven.....	948,327
Whip socket, Goldstein & Voigt.....	948,319
Winding machine, yarn, H. S. Golland.....	948,329
Window, H. J. Davidson.....	948,956
Window cleaner, J. R. Lane.....	948,631
Window cleaner, H. W. Bailey.....	948,641
Window pane fastener, W. G. Kueter.....	948,847
Window screen, L. I. Bright.....	948,844
Window ventilation, J. J. Best.....	948,779
Window ventilator and storm shield, R. A. Dunlap.....	948,417
Wire, means for applying coverings to, J. A. Hosen.....	948,324
Wood in salt water, protecting, Tatro & Dells.....	948,355
Wrench, F. Knobel.....	948,332
Wrench, L. L. Barlick.....	948,870
Wrench, C. Whitman.....	948,946
Writing machine, E. B. Hirsch.....	948,973
Zinc from zinciferous materials, obtaining, H. Pape.....	948,740

A printed copy of the specification and drawing of any patent in the foregoing list, or any patent in print issued since 1865, will be furnished from this office for 10 cents, provided the name and number of the patent desired and the date be given. Address Munn & Co., Inc., 361 Broadway, New York.

Canadian patents may now be obtained by the inventors for any of the inventions named in the foregoing list. For terms and further particulars address Munn & Co., Inc., 361 Broadway, New York.

Home-Made Experimental Apparatus

In addition to the following articles, the **Scientific American Supplement** has published innumerable papers of immense practical value, of which over 17,000 are listed in a carefully prepared catalogue, which will be sent free of charge to any address. Copies of the **Scientific American Supplement** cost 10 cents each.

If there is any scientific, mechanical, or engineering subject on which special information is desired, some papers will be found in this catalogue, in which it is fully discussed by competent authority.

A few of the many valuable articles on the making of experimental apparatus at home are given in the following list:

ELECTRIC LIGHTING FOR AMATEURS. The article tells how a small and simple experimental installation can be set up at home. **Scientific American Supplement 1551.**

AN ELECTRIC CHIME AND HOW IT MAY BE CONSTRUCTED AT HOME. is described in **Scientific American Supplement 1556.**

THE CONSTRUCTION OF AN ELECTRIC THERMOSTAT is explained in **Scientific American Supplement 1556.**

HOW TO MAKE A 100-MILE WIRELESS TELEGRAPH OUTFIT is told by A. Frederick Collins in **Scientific American Supplement 1065.**

A SIMPLE TRANSFORMER FOR AMATEUR'S USE is so plainly described in **Scientific American Supplement 1572** that anyone can make it.

A 1/2-H.P. ALTERNATING CURRENT DYNAMO. **Scientific American Supplement 1558.**

THE CONSTRUCTION OF A SIMPLE PHOTOGRAPHIC AND MICRO-PHOTOGRAPHIC APPARATUS is simply explained in **Scientific American Supplement 1574.**

A SIMPLE CAMERA SHUTTER MADE OUT OF A PASTEBOARD BOX, PINS, AND A RUBBER BAND is the subject of an article in **Scientific American Supplement 1578.**

HOW TO MAKE AN AEROPLANE OR GLIDING MACHINE is explained in **Scientific American Supplement 1582**, with working drawings.

EXPERIMENTS WITH A LAMP CHIMNEY. In this article it is shown how a lamp chimney may serve to indicate the pressure in the interior of a liquid; to explain the meaning of capillary elevation and depression; to serve as a hydraulic turbine, an aspirator, and intermittent siphon; to demonstrate the ascent of liquids in exhaustive tubes; to illustrate the phenomena of the bursting bladder and of the expansive force of gases. **Scientific American Supplement 1583.**

HOW A TANGENT GALVANOMETER CAN BE USED FOR MAKING ELECTRICAL MEASUREMENTS is described in **Scientific American Supplement 1584.**

THE CONSTRUCTION OF AN INDEPENDENT INTERRUPTER. Clear diagrams giving actual dimensions are published. **Scientific American Supplement 1615.**

AN EASILY MADE HIGH FREQUENCY APPARATUS WHICH CAN BE USED TO OBTAIN EITHER D'ARSONVAL OR OUDIN CURRENTS is described in **Scientific American Supplement 1618.** A plunge battery of six cells, a two-inch spark induction coil, a pair of one-pint Leyden jars, and an induction coil, and all the apparatus required, most of which can be made at home.

SIMPLE WIRELESS TELEGRAPH SYSTEMS are described in **Scientific American Supplements 1363 and 1361.**

THE LOCATION AND ERECTION OF A 100-MILE WIRELESS TELEGRAPH STATION is clearly explained, with the help of diagrams, in **Scientific American Supplement 1622.**

THE INSTALLATION AND ADJUSTMENT OF A 100-MILE WIRELESS TELEGRAPH OUTFIT. Illustrated with diagrams. **Scientific American Supplement 1623.**

THE MAKING AND THE USING OF A WIRELESS TELEGRAPH TUNING DEVICE. Illustrated with diagrams. **Scientific American Supplement 1624.**

HOW TO MAKE A MAGIC LANTERN. **Scientific American Supplement 1646.**

THE CONSTRUCTION OF AN EDDY KITE. **Scientific American Supplement 1555.**

THE DEMAGNETIZATION OF A WATCH is thoroughly described in **Scientific American Supplement 1661.**

HOW A CALORIC OR HOT AIR ENGINE CAN BE MADE AT HOME is well explained, with the help of illustrations, in **Scientific American Supplement 1573.**

Good articles on SMALL WATER MOTORS are contained in **Scientific American Supplement 1494, 1499, and 1496.**

HOW AN ELECTRIC OVEN CAN BE MADE is explained in **Scientific American Supplement 1472.**

THE BUILDING OF A STORAGE BATTERY is described in **Scientific American Supplement 1433.**

A SEWING-MACHINE MOTOR OF SIMPLE DESIGN is described in **Scientific American Supplement 1210.**

A WHEATSTONE BRIDGE. **Scientific American Supplement 1593.**

Good articles on INDUCTION COILS are contained in **Scientific American Supplements 1514, 1532, and 1537.** Full details are given so that the coils can readily be made by anyone.

HOW TO MAKE A TELEPHONE is described in **Scientific American Supplement 966.**

A MODEL STEAM ENGINE is thoroughly described in **Scientific American Supplement, 1587.**

HOW TO MAKE A THERMOSTAT is explained in **Scientific American Supplements 1561, 1563, and 1566.**

ANEROID BAROMETERS. **Scientific American Supplements 1500 and 1554.**

A WATER BATH. **Scientific American Supplement 1464.**

A CHEAP LATHE UPON WHICH MUCH VALUABLE WORK CAN BE DONE forms the subject of an article contained in **Scientific American Supplement 1562.**

Each number of the **Scientific American Supplement** costs 10 cents by mail.

Order from your newsdealer or from

MUNN & CO., Inc., 361 Broadway, New York

(Concluded from page 173.)

tions should avail themselves in this work of the highly developed system of insurance and annuities presented by the responsible insurance institutions of this and of other States. Any effective system if established by corporations independently, will be based on the principles and methods used by the insurance companies, and therefore the work for obvious reasons is in the end likely to be more effectively and more economically done by men who are experts and specialists than by men who undertake it with no special training and with minds chiefly occupied by the demands of other lines of work.

I shall therefore assume that life insurance, and probably other types of insurance, including accident and sickness insurance, as represented by existing corporations, is not only well equipped to help in the solution of this problem, but is a part of the evolution of the times which has produced the problem itself, and is another illustration of the curious fact that in the processes of evolution a solution of a problem often appears at the same time the problem itself is evolved. For example, what might have happened in the enormous industrial activity of the United States and its necessary output of securities seeking purchasers if millions of people combining their small savings in the reserves of the great life insurance companies had not appeared upon the scene contemporaneously seeking securities in which to invest their money? The function of life insurance and of other types of insurance on the one hand, and the obligation of the employer of labor to his employees on the other, bear, it seem to me, an identical relation.

Life insurance is already effectively at work. While the employer of labor has only in the most limited way used the idea or appreciated its beneficence, progress has been made toward the solution of this problem. Eliminating industrial companies and including only those companies whose business is supposed to be confined to people of means, we find the average policy the country over is a little under \$2,000. In other words, the mass of so-called regular insurance is held by people of small means. If now we add to these the millions who carry what is called "industrial" insurance, and the other millions who have so-called "fraternal" insurance, we have covered substantially the whole insurance field. We comprehend an interest whose accumulations surpass those of any other single line of human endeavor, except the accumulations of savings banks, and yet we have not gone outside of what may properly be called the laboring class. The energy of life insurance management, in other words, and the obligation which the laboring man feels toward his family, have in their development far outrun the sense of obligation of the employer. We have now reached the point when the employer is beginning to do his part—but as yet he has only made a beginning. That he will do more is certain; that he will do much is almost equally certain. That existing insurance institutions will be utilized is, I believe, a necessity.

Alloys Formed by the Compression of Metal Powders.

The ordinary method of preparing alloys consists in melting two or more metals together, and allowing the melt to crystallize after cooling. Can not the same alloys be obtained by compressing the component metals at ordinary temperatures in the shape of fine powders? Dr. W. Spring showed as far back as 1882 that under a pressure of 5,000 atmospheres the powders of the constituents of the Rose and Wood alloys will form conglomerates, the melting points of which nearly coincide with those of the alloys obtained by melting. In 1888 Hallcock showed that by merely mixing at ordinary pressures the powders of the same constituents there is obtained a mixture

(Concluded on page 175.)



For Everybody

wishing to bore a hole in steel, iron or wood. We make drills in 8 sizes. Our large size will drill a 2 1/2 inch hole in steel. Our Electric Midget weighs only 4 pounds, and will drill in steel up to 1-16 inch. Great for manual training schools. We also make electric driven grinders. Let us send one on 10 days' trial. Send for catalogue.

THE CINCINNATI ELECTRIC TOOL CO.
650 and 652 Evans Street, Cincinnati, Ohio, U. S. A.

BUILD YOUR OWN AEROPLANE

By becoming a member of the American Aeronautical Society the parts and accessories can be obtained at cooperative cost. Upon receipt of application and Two Dollars a volume of information and instruction containing **FIRST LESSONS IN AERONAUTICS** with drawings of ten up-to-date aeroplanes for selection. Membership entitles to entry at meets of society. Address M. K. Kasmar, Sec'y, 1827 N. Paulina St., Chicago.

Aeroplanes and Motors

We are building monoplanes of the Bleriot cross-channel type. Delivery 3 weeks after receipt of order. Flight guaranteed. Price \$5,000; one-third cash with order.

We also build several kinds of light-weight aeroplanes and motors and propellers. Particulars and prices furnished upon application.

SCIENTIFIC AEROPLANE AND AIRSHIP CO.
Box 75, New York

\$650 A. B. C. Automobile \$650

The biggest Automobile bargain in America. 2 or 4 Cylinders. Surveys, Runabouts and Delivery Wagon. 10 or 4 H. P. Solid or Pneumatic Tires. Write for FREE Catalog.

A. B. C. MOTOR VEHICLE MFG. CO., 3913 Morgan, St. Louis

J. E. LINDE PAPER CO.

Also proprietors of

NEW YORK ROLL WRAPPING PAPER CO.
Beckman and Cliff Streets
New York, U. S. A.

STUDY LAW

Leading Law School in correspondence instruction. Established 1882. Prepares for the bar. Three Courses: College, Post-graduate and Bar. Law, Method of instruction combines theory and practice. Approved by the bench and bar.

Classes begin each month. Send for catalog giving rules for admission to the bar of the several states.

Chicago Correspondence School of Law
506 Reape Block, Chicago

98c USE GRINDSTONES?
If so we can supply you. All sizes mounted and unmounted, always in stock. Remember, we make a specialty of selecting stones for all special purposes. Send for catalogue "L."

The CLEVELAND STONE CO.
6th Floor, Hickox Bldg., Cleveland, O.

Industrial Alcohol

Its Manufacture and Uses
By JOHN K. BRACHVOGEL, M.E.
Size 6 1/4 x 8 1/4 inches. 528 pages. 107 illustrations. Price \$4.00, postpaid.

PRACTICAL, treatise based on Dr. Max Maercker's "Introduction to Distillation," as revised by Drs. Delbruck and Lange, comprising raw material, making, mashing and yeast preparation, fermentation, distillation, rectification and purification of alcohol, alcoholometry, the value and significance of a tax-free alcohol, methods of denaturing, its utilization for light, heat and power production, a statistical review, and the United States law. The present work is based upon the researches and writings of the most eminent of Germany's specialists in the science of fermentation and distillation. It covers the entire manufacture of alcohol from the raw materials to the final rectified and purified product. It also contains chapters on the methods of denaturing, domestic utilization of alcohol for heating and lighting purposes, and alcohol as a fuel for power production. An illustrated circular and table of contents of this book will be sent on application.

MUNN & CO., Inc., Publishers
361 Broadway, New York

The Design and Construction of Induction Coils

By A. FREDERICK COLLINS
Size 6 1/4 x 9 1/4 inches. 295 pages. 159 illustrations. Price \$3.00, postpaid.

THIS work gives in minute details full practical directions for making eight different sizes of coils, varying from a small one giving a one-half-inch spark to a large one giving twelve-inch sparks. The dimensions of each and every part down to the smallest screw are given, and the descriptions are written in language easily comprehended.

Much of the matter in this book has never before been published, as, for instance, the vacuum drying and impregnating processes, the making of adjustable mica condensers, the construction of interlocking reversing switches, the set of complete wiring diagrams, the cost and purchase of materials, etc. It also contains a large number of valuable tables, many of which have never before been published. It is the most complete and authoritative work as yet published on this subject. The illustrations have all been made from original drawings which were made especially for this work. A large circular, containing a full table of contents and samples of the illustrations will be mailed on request.

MUNN & CO., Inc., Publishers
361 Broadway, New York

(Concluded from page 174.)

melting at a lower temperature than the melting point of the most fusible component. By compressing zinc and copper powders, Spring obtained a conglomerate which was distinguished from brass only by its slightly darker color.

In spite of these partial results the problem had not so far been definitely solved. It remained in fact to be seen whether, by augmenting the speed of fusion of the mixed metal powders, pressure really favors the formation of those compounds which are characteristic of alloys obtained by melting. This question is answered by Prof. G. Tammann on the basis of recent experiments by G. Masing.

When submitting a mixture of filings of two metals forming neither a chemical compound nor mixed crystals (e. g., zinc and cadmium or copper and silver) to a pressure of 4,000 atmospheres, and heating the conglomerate thus obtained, the rising curve of temperatures is seen at a given point to slacken down, after reaching a temperature 10 1/2 deg. C. higher than that at which the whole is found to melt. As far as its thermal properties and its structure are considered, this conglomerate is practically identical with alloys obtained by melting.

Again, by compressing under high pressure the powders of two metals forming a definite compound and capable of mixing in all proportions in a liquid condition, and by heating the conglomerate thus obtained, two stopping points are found in the curve of temperatures. The first of these points corresponds with the melting of a compound formed at the surface while the other corresponds with the formation of the alloy. This is the case, for instance, with mixtures of magnesium with zinc, lead, tin or bismuth. The conglomerate composed of magnesium and antimony has only a single stopping point situated at 300 deg. C. below the melting point of antimony. This corresponds with the formation of the compound Mg₂Sb₂.

The temperature then rises very rapidly in order to eventually fall down to the melting point of the alloy. The third case investigated by Masing relates to the conglomerate of two metals forming an uninterrupted series of mixed crystals, such as magnesium and cadmium on the one hand and lead and thallium on the other. When heating such conglomerates, only a single stopping point is observed corresponding to the melting point of the most fusible component. The form then assumed by the curve depends on the diffusion of the two components into one another.

The conglomerates obtained merely by compression do not contain any trace of mixed crystals. Microscopical examination thus only shows the existence of grains of copper and tin in recently prepared conglomerates. If, however, these mixtures be heated to 200 deg. C. (i. e., below the melting point of the tin) there are found between the grains of copper and tin, two layers corresponding to the compounds Cu₃Sn and CuSn respectively. If these conglomerates be heated during 20 hours to 400 deg., a layer of mixed crystals, corresponding to the formula Cu₃Sn, is found. This proves that compounds of these metals are permeable to their constituents.

The following conclusions are derived from these experiments:

The compression of two metals at ordinary temperatures will yield conglomerates containing only the pure metal, i. e., neither compounds nor mixed crystals as characteristic of alloys obtained by melting. Mere compression thus does not activate diffusion sufficiently to bring about combination or the formation of mixed crystals. If, however, heated metals (i. e., with increased speed of diffusion) are submitted to pressure, there is obtained not only a more coherent mass, but a portion of the metals is found to form compounds and mixed crystals, so as to produce a conglomerate which is very much like a real alloy.

Big Money In Drilling


Our customers all over the Country are making from \$25 to \$75 profit a day with the Cyclone Drill. No business offers such big returns for the money invested. Contractors, prospectors, well drillers, find the Cyclone Drill more economical, faster and easier to operate than any other.

We make Hollow Rod, Cable and Core Drills, to meet every need. We also make combination machines that will handle any or all of the systems equally well, a machine that will enable you to cover the entire field of drilling.

Cyclone Drill

Our Diamondite and Steel Shot Core Drills cut faster and at fraction of the cost of the old diamond drills. We sell Cyclone Drills on an easy payment plan. Some of our customers have made more than the price of the machine within one month. Our new traction Gasoline machine—only one made—is of particular value where fuel and water are scarce. Send for our free books on Drilling, and let us know in what branch of the work you are interested.

CYCLONE DRILL COMPANY, 11 Main St., Orrville, Ohio
Chicago Office, 419 Fisher Building



2 H.P. DETROIT ENGINE

\$29.50

Other sizes at proportionate prices in stock ready to ship. Single cylinder engines, 2 to 8 h. p.; double cylinders, 4 to 20 h. p.; four cylinder, 50 h. p. Engines start without cranking. No cams, no sprockets, only three moving parts. All engines counterbalanced. No vibration. Special fuel injector burns gasoline, kerosene, alcohol, naphtha distillate. Plastic bearings (no cheap babbit used).



Engined steel. Bearing surfaces ground. Adjustable steel connecting rod. Waterproof ignition system. For your launch, sailboat, rowboat, stern wheel boat or railroad track car. 20,000 satisfied users. Free catalog and testimonials. Demonstrating Agents wanted in every boating community. Special wholesale prices on first outfit sold.

DETROIT ENGINE WORKS
1332 Jefferson Ave., Detroit, Mich., U.S.A.

ICE MACHINES

Curtiss Engines, Brewers and Ice Cream Machinery. THE VILVER MFG. CO., 889 Clinton St., Milwaukee, Wis.

MODELS & EXPERIMENTAL WORK.

Inventions developed. Special Machinery. E. V. HALLARD CO., 24 Frankfort Street, New York.

CONSULTING ENGINEER.

ERNEST L. HANSOME
Reinforced Concrete
11 Broadway, New York

RUBBER

Expert Manufacturers Fine Jobbing Work
PARKER, STEARNS & CO., 288-290 Sheffield Av., B'klyn, N. Y.

SOUTHERN STAMPING & MFG. CO.

Manufacturers of special and patented articles.
H. S., Nashville, Tenn.

MODELS & CHICAGO MODEL WORKS

ESTABLISHED 1867. 1112 E. MADISON ST., CHICAGO, ILL.

MODELS & EXPERIMENTAL WORK.

Gears, Dies, Tools, Novelties manufactured.
M. P. SCHELL, 1739 Union Street, San Francisco

Experimental & Model Work

Orv. & advice free. Wm. Gardam & Son, 221 Fulton St., N.Y.

INVENTORS, ATTENTION!

We want to buy outright, or manufacture, or market on royalty practical inventions, electrical or otherwise, for household use. Have plenty of capital and large selling organization. Give full description of your invention, number and date of patent, if patented, blue print illustration, etc. Correspondence confidential. Address Manufacturer, care of Chas. H. Fuller Co., 838 Wabash Ave., Chicago, Ill.

A MACHINE SHOP

Good Work—Fair Prices
E. D'AMOUR
80 Cortlandt Street
New York

MAGICAL APPARATUS.

Grand Book Catalogue. Over 700 engravings. 25c. Parlor Tricks Catalogue, free.
MARTINKA & CO., Mfrs., 405 Sixth Ave., New York

TELESCOPES

W. D. MOORE
BAYNE CITY, MICH.

MASON'S NEW PAT. WHIP HOIST

For Outrigger hoists. Faster than Elevators, and hoist direct from teams. Saves handling at less expense. Mfrd. by VOLNEY W. MASON & CO., Inc. Providence, R. I., U. S. A.

Why I Can Afford to Send You Free



The Keenoh Automatic Razor Sharpener

Because you never had a razor sharpened any keener and smoother than your razor will be 20 seconds after you've used the Keenoh.

Because it will do equally wonderful work with the safety or the old style razor.

Because—being absolutely automatic—it can't fail, no matter how careless you may be, to put your razor into a condition as perfect as it would be if it had been sharpened and honed by the best barber in your town.

Because it will do these things every day, and keep on doing them for the rest of your life.

Because it will positively make your safety blade sharper than it was when new, and enable you to use every blade for 500 to 1,000 perfect shaves.

Because of these things which make it certain that no man will return a Keenoh after using it—I can afford to send you one for 10 days' free trial.

That's what I will do gladly if you will fill out the coupon and mail it to me.



S. J. Herman, Gen'l Manager, The "Keenoh" Company
575 W. Fort Street, Detroit, Mich.

Send me a "KEENOH" Automatic Razor Sharpener for ten days' free trial, through my dealer named below, to whom, if satisfactory, I will pay \$3.50.

Dealer's Name _____
Dealer's Address _____
My Name _____
My Address _____

The PRUDENTIAL

Home Office Buildings 1910
Newark, N. J.



MONTHLY INCOMES GUARANTEED TO YOUR FAMILY

The Massive Buildings Above are Owned and Occupied by The Prudential as Headquarters for the Three Thousand Five Hundred Employees required in the Home Offices alone for the Conduct of its Vast Business and the Protection and Benefit of the Holders of over Eight Million Policies in Force. Send for Particulars of the New Monthly Income Policy. Address, Dept. 131. Home Office, NEWARK, N. J.

JOHN F. DRYDEN, President

The Prudential Insurance Company of America
Incorporated in a Stock Company by the State of New Jersey

Address, Dept. 131
Home Office, NEWARK, N. J.

BROOKS BOATS
GUARANTEED TO BE SATISFACTORY

You Want A Boat
Build it Yourself and Save Two-thirds

We will furnish you with all the parts of a boat—machines, cut to shape, and accurately fitted together prior to shipment, so that, with a little labor on your part, you can own your own boat, at a price that is ridiculously low, or we will furnish you with instructions and full-sized paper patterns, from which you can build the boat yourself, by purchasing the material locally.

You want to know how it can be done? Then send today—not tomorrow—for OUR NEW CATALOG No. 24—IT'S FREE. The exceedingly low prices will amaze you.

For the year 1910 we have made the enormous out of 33 1-2 per cent. from our regular prices—just matched less than they were last year. Do you know that local boat-builders all over the country purchase our frames—build the boats and sell them at a handsome profit? You can do this yourself and save that profit. Anyone can put our Knock-Down boats together—no skill is required. The work is a clean, instructive form of recreation—a truly good thing for you or your boy. We save you (1) the boat-builder's profit; (2) labor expense; (3) big sailing expense; (4) seven-eighths the freight.

OUR GUARANTEE is that you will be perfectly satisfied with everything you purchase of us, or your money will be instantly refunded.

BROOKS MANUFACTURING CO.
402 Ship St., Saginaw, Mich., U.S.A.
Originators of the pattern and Knock-Down System of Boat-building. Established 1901.

Running Water in Kitchen Bathroom Laundry Stable At Small Expense

If there's a running stream or spring on your ground, install a **NIAGARA HYDRAULIC RAM** and pump the water where you want it. Write for booklet A-3 and estimate. **NIAGARA HYDRAULIC RAM CO.**, 140 Ransom Street, N. Y. Factory, Chicago, Ill.

CRUDE ASBESTOS
DIRECT FROM MINES

PREPARED ASBESTOS FIBRE for Manufacturers use

R. H. MARTIN,
OFFICE, ST. PAUL BUILDING
220 B'way, New York.

Pipe Cutting and Threading Machine
For Either Hand or Power

This machine is the regular hand machine supplied with a power base, piston, countershaft, etc., and can be worked as an ordinary power machine or taken from its base for use as a hand machine. Pipe 1/2 in. to 1 1/2 in. diameter handled easily in small room. Illustrated catalogue—price list free on application.

THE CURTIS & CURTIS CO.
6 Garden St., Bridgeport, Conn.

SOLAR LIGHTS SAVE MONEY

SALESMEN WANTED—Large profits. Make \$100 a month selling Solar Lighting Systems for stores, dwellings, streets, etc. Free catalogue. Write today. **CHICAGO SOLAR LIGHT CO.**, 812 N. Jefferson St., Chicago.

HELMET OIL LUBRICATES FOR ANYTHING THAT RUNS

SEND FOR SAMPLE FREE
10-11 S. CLINTON ST.
CHICAGO, ILL.

The Old-Style Razor Made Absolutely Safe—the Safety-Razor Made Absolutely Perfect

DURHAM-DUPLEX RAZOR

Everything a Razor Should Be

If you use a "Safety" Razor, you'll like the Durham-Duplex Razor better because it has every good feature of the best "safety" razor and the additional advantage that it shaves with the correct sliding diagonal stroke—something hoe-like devices cannot do.

The Durham-Duplex easily and quickly shaves the toughest beard.

If you use the old-style razor, you'll like the Durham-Duplex better, because it has every advantage of the long blade, with the additional advantage of removable blades, making stropping and honing unnecessary; insures a sharp, keen edge for every shave. The blades can, however, be honed and stropped like an ordinary razor. New blades, 6 for 50c.

FREE TRIAL OFFER

The Durham-Duplex Razor is new, and therefore is not yet sold by all retailers, but we will send you the complete outfit upon receipt of \$5.00, and if not entirely satisfactory, return it within 30 days and get your money back. Get one today.

Write for Free Booklet

DURHAM DUPLEX RAZOR CO., 111 Fifth Ave., New York

THE MATCHLESS SMOKE

Autolite 25c Self-Lighting Monolite 15c CIGARETTES

They strike and light on the box in a swift, windproof stroke.

The invention of the age—that's taking smokers by storm—is our cigarette without a match. A distinct innovation that makes an epoch in the history of tobacco. The Cigarette is made only of imported selected Turkish Tobacco—carefully blended under our personal supervision to produce a mellow flavor and fragrant aroma. Made by expert workmen in clean, sanitary workrooms.

Ideal for Motorists, Riders, Skaters, Sleighting, Walking, etc.

The self-lighting disc is guaranteed absolutely harmless and tasteless.

At all SMOKE SHOPS or sent prepaid on receipt of price.

JUST A SCRATCH WITHOUT A MATCH **AUTOLITE MANUFACTURING CO., Newark, N. J.**

COLD GALVANIZING.
AMERICAN PROCESS NO ROYALTIES.
SAMPLES AND INFORMATION ON APPLICATION.

Established 1870.

NICKEL
AND
Electro-Plating
Apparatus and Material
FOR
Hanson & VanWinkle
Co.
Newark, N. J.
109 North Canal St.
Chicago, Ill.

RUNABOUT—FAMILY CAR DELIVERY WAGON—ALL IN ONE CAR—AT \$850

The 1910 revelation in automobile convenience and in car-values. 3 cars in one—easily changed from one style to another in five minutes. For business and pleasure—simple and safe for anybody to drive. Low first-cost and upkeep expense, strong, durable and speedy enough for all. The car you can afford because it pays for itself in your business. This

INVINCIBLE SCHACHT THREE-PURPOSE CAR

is the necessity, accommodation and luxury car all in one. All have uses for it in each of its three styles. As good in each style as any car of similar price—yet here you get three distinct automobiles at the price of one—\$850. Let us tell you all about it. Book free. See this and other Schacht Models at Boston Auto Show, March 5 to 12.

SCHACHT MANUFACTURING CO.
2700 Spring Grove Avenue, Cincinnati, Ohio


Simple, Speedy, Convenient. 3 CARS IN ONE \$850



Used as a Light Delivery Wagon

1910 MODEL Ideal Lawn Mower Grinder

Grinds the Reel Knives to fit the straight blade even if the latter is bent or sprung—the most important feature of Lawn Mower sharpening. Has ball-bearing Grinding Wheel, rabbitted bearings, easier running than any other. Grinds all style Hand Mowers perfectly in 15 minutes without removing wheels or ratchets. We originated and have six years experience. Nearly 4,000 in use. Fully warranted. Write for catalog and price today.



The Heath Foundry & Mfg. Co., PLYMOUTH, OHIO

WE SHIP ON APPROVAL
without a cent deposit, prepaid the freight and allow 10 DAYS FREE TRIAL.

IT ONLY COSTS one cent to learn our method of prices and marvelous offers on highest grade 1910 model bicycles.

FACTORY PRICES Do not buy a pair of tires from anyone at any price until you write for our large Art Catalog and learn our wonderful proposition on first sample bicycle going to your town.

RIDER AGENTS everywhere are making big money churning and selling our bicycles. We sell cheaper than any other factory.

Tires, Coaster-Brakes, single wheels, parts, repairs and sundries at half retail prices. Do Not Wait; write today for our special offer.

MEAD CYCLE CO., Dept. L175 CHICAGO

Remoh Gems

Looks like a diamond—wears like a diamond—brilliantly guaranteed forever—stands filing like a diamond—stands heat like a diamond—has no paste, foil or artificial backing. 1-1/2 the cost of diamonds. Set only in solid gold mountings. A universally reconstructed gem, not an imitation. Sent on approval. Write for our catalog. It's free. No canvassers wanted.

REMOH JEWELRY CO., 458 N. Broadway, St. Louis

4 HP STATIONARY GASOLINE ENGINE \$76.00

For Farmwork, Irrigation or Pumping, Factory use and Electric Lighting.

3 to 20 h. p.—perfectly governed—guaranteed by a responsible firm. Write for particulars.

GRAY MOTOR CO., 121 Leis St., DETROIT, MICH

Saffa Mixture

The Finest Tobacco Grown

Do you know what Saffa Mixture of Turkish tobacco means to the smoker? Briefly—extreme pleasure—no touching tobacco in the world compares with this mixture of Saffa Turkish Tobacco, 9 of them hand-mixed, blending a mixture for Pipe or Cigarette, so delicious—so aromatic—so rich and mild that once you use it you will never consider anything else smoking. Let us write you about our expert blend-master—maturity of tobacco and full particulars. Address Dept. 5.

SAFFA TURKISH TOBACCO CO., St. Louis, Mo.

Incorporate Your PATENTS and BUSINESS in ARIZONA

Laws the most liberal. Expense the least. Hold meetings, transact business anywhere. Blanks, By-Laws and forms for making stock full-paid for cash, property or services, free. President Stoddard, FORMER SECRETARY OF ARIZONA, resident agent for many thousand companies. Reference: Any bank in Arizona.

STODDARD INCORPORATING COMPANY, Box 8000 PHOENIX, ARIZONA